



Queensland

Electrical Safety Act 2002

Electrical Safety Regulation 2002

Reprinted as in force on 1 March 2008

Reprint No. 2C

This reprint is prepared by
the Office of the Queensland Parliamentary Counsel
Warning—This reprint is not an authorised copy

Information about this reprint

This regulation is reprinted as at 1 March 2008. The reprint shows the law as amended by all amendments that commenced on or before that day (Reprints Act 1992 s 5(c)).

The reprint includes a reference to the law by which each amendment was made—see list of legislation and list of annotations in endnotes. Also see list of legislation for any uncommenced amendments.

This page is specific to this reprint. See previous reprints for information about earlier changes made under the Reprints Act 1992. A table of reprints is included in the endnotes.

Also see endnotes for information about—

- **when provisions commenced**
- **editorial changes made in earlier reprints.**

Dates shown on reprints

Reprints dated at last amendment All reprints produced on or after 1 July 2002, hard copy and electronic, are dated as at the last date of amendment. Previously reprints were dated as at the date of publication. If a hard copy reprint is dated earlier than an electronic version published before 1 July 2002, it means the legislation was not further amended and the reprint date is the commencement of the last amendment.

If the date of a hard copy reprint is the same as the date shown for an electronic version previously published, it merely means that the electronic version was published before the hard copy version. Also, any revised edition of the previously published electronic version will have the same date as that version.

Replacement reprint date If the date of a hard copy reprint is the same as the date shown on another hard copy reprint it means that one is the replacement of the other.



Queensland

Electrical Safety Regulation 2002

Contents

		Page
Part 1	Preliminary	
1	Short title	13
2	Commencement	13
3	Purposes	13
4	How purposes are to be achieved	13
5	Definitions	14
6	References to standards and other documents	15
7	Meaning of qualified business person and qualified technical person	16
Part 2	Electrical work	
Division 1	Preliminary	
8	Purpose of divs 2 to 5	17
Division 2	Basic requirements for electrical work	
9	Definition for div 2	18
10	Application of div 2	18
11	Requirements for electrical work	18
12	Requirements for performance of live work	18
Division 3	High voltage live line work	
13	Performance of high voltage live line work	21
Division 4	Testing of work	
14	Testing of electrical equipment after electrical work	22
15	Certificate of testing and safety	23
Division 5	Requirements applying to employers and self-employed persons	
16	Application of div 5	24
17	Testing and maintenance of safety equipment	24
18	Employer or self-employed person to ensure suitability of testing instruments	25

Division 6	Other requirements	
19	Electrical equipment with serious defect not to be connected to electricity source.	26
20	Signs on switches and disconnection points	26
21	Rescue and resuscitation training	27
Division 7	Documents about electrical work	
22	Application of div 7	28
23	Who may sign documents about electrical work	28
Division 8	General provisions	
24	Misrepresentations about electrical equipment or work	29
24A	Misrepresentations about lawful authority to contract for the performance of electrical work	29
Part 3	Licensing	
Division 1	Electrical work licences	
25	Classes of electrical work licences.	30
26	What electrical mechanic licence authorises	30
27	What electrical linesperson licence authorises.	30
28	What electrical fitter licence authorises	31
29	What electrical jointer licence authorises	31
30	What restricted electrical work licence authorises	31
31	What electrical work training permit authorises	32
32	External licence equivalents.	32
Division 2	Electrical work licence requirements	
33	General requirements.	32
34	Eligibility requirements for electrical mechanic licence	34
35	Eligibility requirements for electrical linesperson licence	36
36	Eligibility requirements for electrical fitter licence.	38
37	Eligibility requirements for electrical jointer licence	40
38	Eligibility requirements for restricted electrical work licence	43
38A	Eligibility requirements for electrical work training permit.	46
39	Term of electrical work licence	46
Division 3	Electrical contractor licence requirements	
40	Eligibility requirements for electrical contractor licence for individual	47
41	Eligibility requirements for electrical contractor licence for partnership	49
42	Eligibility requirements for electrical contractor licence for corporation	50

Electrical Safety Regulation 2002

43	Financial and insurance requirements for applicant for electrical contractor licence	52
44	Change of name of corporation or partnership	53
45	Change in membership of partnership	54
46	Term of electrical contractor licence	55
Division 4	Miscellaneous	
47	Eligibility requirements for renewal or reinstatement of electrical licence	55
48	Application requirements	56
49	Giving chief executive cancelled or suspended licence or licence to be endorsed	56
50	Replacement of electrical licence	56
51	Surrender of electrical licence	56
52	Register of electrical licences	57
53	Examinations	58
54	Approved examiners	58
55	Refund of fees	59
55A	Operation of trade contractor's licence	59
56	Advertising by licensed electrical contractor	59
57	Performing electrical work without electrical licence	60
57A	Details to be included in register of workers	60
Part 4	Working around electrical parts	
Division 1	Preliminary	
58	Purpose of pt 4	61
59	Definitions for pt 4	62
60	Meaning of direct contact	63
61	Meaning of exclusion zone	64
Division 2	Requirements for working around electrical parts and underground electrical services	
62	Employer or self-employed person to ensure work is performed in accordance with requirements	66
62A	Principal contractor for construction workplace—excavating and underground electrical services	67
62C	Employer or self-employed person at construction workplace—excavating and underground electrical services	68
62D	Employer or self-employed person not at construction workplace—excavating and underground electrical services	68
63	Work involving direct contact with electrical part	69
64	Work within exclusion zone for electrical part	70

Division 3	Consultation with persons in control of electric lines	
64A	Requirement to consult	71
Part 5	Electrical installations	
Division 1	Performing electrical work	
65	Purpose of div 1	73
66	Licensed electrical worker to comply with wiring rules	73
67	Employer to ensure electrical installation complies	73
67A	Self-employed person to ensure electrical installation complies	74
68	Work involving water equipment.	74
69	Work involving electric motor forming part of vehicle	75
Division 2	Defects and earthing	
70	Requirement on person in control to fix defect.	76
71	Earthing	76
Division 3	Electric lines	
72	Service line.	76
73	Structure supporting electric line or equipment to comply with wiring rules	77
74	Obligation to preserve insulation of electric line	77
75	Trimming of trees near overhead electric line.	78
76	Obligation to ensure safety of disconnected overhead electric line	78
Division 4	Installation of approved safety switches in domestic residences	
77	Definitions for div 4.	79
78	Notice to transferee about approved safety switch.	80
79	Notice to chief executive about approved safety switch and other matters	81
80	Installation of approved safety switch in particular residences.	82
80A	Installation of approved safety switch if residential tenancy agreement entered into or to be entered into.	83
81	Performing electrical installation work for domestic residences	85
Division 5	Workplace electrical installations	
Subdivision 1	Preliminary	
82	Purpose of div 5	85
83	Definitions for div 5.	86
83A	Meaning of rural industry work	89
Subdivision 2	All work	
84	Application of sdiv 2	90

85	Cord extension sets and flexible cables	91
Subdivision 3	Construction work	
86	Application of sdiv 3	91
87	Requirements for construction wiring and electrical equipment . .	91
Subdivision 4	Manufacturing work	
88	Application of sdiv 4	93
89	Double adaptors and piggyback plugs prohibited	93
90	Specified electrical equipment	93
90A	Manufacturing work—safety switch	95
90B	Exemption for safety switches	96
91	Safety switches, including portable safety switches	96
Subdivision 5	Service work or office work	
92	Application of sdiv 5	97
93	Specified electrical equipment	97
94	Safety switches, including portable safety switches	99
Subdivision 6	Amusement work	
94A	Application of sdiv 6	99
94B	Double adaptors and piggyback plugs prohibited	100
94C	Specified electrical equipment	100
94D	Amusement devices and amusement rides	101
94E	Safety switches, including portable safety switches	102
Subdivision 7	Rural industry work	
94F	Application of sdiv 7	103
94G	Requirements for rural industry work	103
Part 6	Electrical equipment	
Division 1	Preliminary	
95	Definitions for pt 6.	105
96	Meanings of prescribed class and type	106
97	Meaning of relevant standard	107
98	Queensland approvals	107
99	External approvals	107
Division 2	Restriction on hire or sale of particular items of electrical equipment	
100	Hire or sale of electrical equipment of prescribed class	108
Division 3	Queensland approvals of types of electrical equipment of prescribed classes	
101	Application for approval of type of electrical equipment	109

102	Approval of type of electrical equipment.	110
103	Term of approval.	111
103A	Extension of term of approval by up to 1 year	111
103B	Renewal of approval.	112
104	Register of approved types of electrical equipment	114
Division 4	Changes to approvals	
105	Changing name and address	114
106	Application to change approval to include new type.	115
107	Changing approval of type of electrical equipment to include new type	115
Division 5	Transfer and cancellation of approvals	
108	Transfer of approval of type of electrical equipment.	116
109	Cancellation of approval of type of electrical equipment	117
110	Procedure before cancellation	118
111	Type approval holder to return type approval certificate for cancelled approval	118
Division 6	Marking of equipment of approved type	
112	Marking of item of electrical equipment of approved type	119
113	Approval by the chief executive not to mark item of electrical equipment	119
Division 7	Chief executive may require testing of item of electrical equipment of approved type	
114	Chief executive may require item of electrical equipment of approved type to be submitted	120
115	Procedure for obtaining item of electrical equipment for testing.	120
116	Identification of item of electrical equipment to be tested.	121
117	Cost of testing and examining and liability for damage	121
118	Return of item of electrical equipment given to chief executive	122
Division 8	Nonprescribed electrical equipment	
119	Chief executive may put into effect program for certification	123
120	Sale of particular nonprescribed electrical equipment prohibited.	123
Division 9	Prohibition of hire or sale of particular electrical equipment	
121	Chief executive may prohibit the hire, sale or use of electrical equipment on safety grounds.	124
Division 10	Second-hand electrical equipment	
122	Limitation on sale of second-hand electrical equipment.	124
123	Limitation on offering second-hand electrical equipment for sale.	125
Division 11	Labelling and inspection of electrical equipment	
124	Labelling faulty portable electrical equipment	126

Division 12	Hire electrical equipment	
125	Purpose of div 12	126
126	Hiring electrical equipment	126
Division 13	Miscellaneous	
126A	Refund of fees	128
Part 7	Works of an electricity entity	
Division 1	Compliance with part	
127	Purpose of pt 7	129
128	Compliance with this part	129
Division 2	Earthing and protection	
129	Systems of earthing	129
130	Connection of high voltage circuit to earth	130
131	Performance and other requirements for works	131
132	Insulation of stay wire	132
133	Protection of earth conductors	132
Division 3	Substations	
134	Substation requirements	132
Division 4	Electric lines and control cables	
134A	Application of div 4	133
135	Measurement of vertical and horizontal distances	133
136	Electric lines and control cables	134
137	Clearance from exposed conductive parts and separation of conductors in same circuit	134
138	Location of overhead circuit in relation to another overhead circuit	135
139	Clearance of overhead electric lines from ground	135
140	Clearance of overhead electric lines from structures	136
141	Building or adding to structure near electric line	136
142	Clearance of stay wires and control cables over road	137
143	Connection to consumer's premises	137
Division 5	Termination requirements for low voltage overhead service lines	
144	Termination of low voltage overhead service line	138
Division 6	Service lines generally	
145	Fuses and disconnectors for service line	138
146	Disused service lines to be disconnected	139
Division 7	Maintenance of works	
147	Inspection and maintenance of integrity of insulation	140

148	Trimming of trees near overhead electric line.	140
Part 8	Electricity supply	
Division 1	Connection to source of electricity	
149	Electrical installation with serious defect not to be connected to electricity source.	141
150	Electrical installation not to be connected to electricity source if work not tested.	141
151	Electrical installation not to be initially connected to electricity source without examination and testing.	142
152	Reconnection of electrical installation to electricity source.	142
153	High voltage or hazardous area electrical installation not to be connected to electricity source without inspection.	143
154	Licensed electrical contractor not to connect electricity source without being satisfied of compliance with Act and regulation.	144
155	Disconnection and reconnection of low voltage electrical installation.	144
Division 2	Private generating plant	
156	Generating plant for emergency supply.	145
157	Generating plant for interconnection to works of electricity entity.	146
Division 3	Testing	
158	Notice by licensed electrical contractor of test.	146
159	Certificate of testing and compliance.	147
160	Performance of examination or test.	148
161	Reasons to be given for not connecting to source of electricity after examination.	148
162	Keeping copy of report.	148
Division 4	Requests and advice to distribution entities	
163	Request to distribution entity for examination of electrical work.	149
164	Telling distribution entity of need for change to metering.	149
Part 9	Safety management systems	
Division 1	Prescribed electricity entities	
165	Prescribed electricity entities.	150
Division 2	Requirements for safety management systems	
166	Safety management system requirements.	150
Part 10	Accredited auditors	
167	Appointment.	152
168	Refund of part of fee.	153
169	Term of office as accredited auditor.	153

Part 11	Cathodic protection systems	
Division 1	Preliminary	
170	Definitions for pt 11	153
171	Electrical terms apply for direct current	154
172	Exclusion from application	154
Division 2	Installation and design	
173	Installation of cathodic protection system only if preliminary steps taken	155
174	Correct design and installation of cathodic protection system . . .	155
Division 3	Operating requirements	
175	Operation of cathodic protection system only on conditions	156
Division 4	Testing requirements	
176	Tests before registration or operation of system.	156
177	Further tests during period of registration of system	157
178	Further tests during operation of system	158
179	Further tests of new foreign structure if required by the chief executive	159
180	Records of tests to be kept.	159
181	Testing by chief executive.	159
Division 5	System requirements	
182	Electrical limits	160
183	Maximum potential change	160
184	Tolerances	161
185	Identification of anode groundbed	162
Division 6	Registration of registrable systems	
186	Register	162
187	Application for registration of registrable system	162
187A	Refund of fees	163
188	Registration of registrable system	163
189	Term of registration.	164
190	Change of name and address	164
191	Cancellation of registration.	165
192	Taking away or making a registered system inoperable	165
193	Change to registered system to be notified	165
Part 12	Incident notification and reporting	
194	Definitions for pt 12.	166
195	Meaning of distribution entity for incident or event	166

196	Employer or self-employed person to advise chief executive of serious electrical incident or dangerous electrical event	167
197	Recording serious electrical incident or dangerous electrical event	167
198	Distribution entity to advise chief executive of serious electrical incident or dangerous electrical event	168
199	Action required by distribution entity on report of electric shock	169
200	Report of incident records	169
201	Scene not to be interfered with	169
201A	Storage of electrical equipment after serious electrical incident	170
202	Requirement on distribution entity to take action in interests of electrical safety	170
Part 13	Miscellaneous provisions	
Division 1	Electrical safety contributions	
203	Context of div 1	171
204	Definitions for div 1	171
205	Fixing electrical safety contribution for each distribution entity for current financial year	172
206	Payment of electrical safety contribution by instalments	172
Division 2	Mines, petroleum plants and prescribed workplaces	
207	Application of regulation at mine or petroleum plant	172
207A	Prescribed workplaces—Act, s 18(2)(d)	173
Division 3	Other matters	
208	Climbing poles of electricity entity prohibited	174
209	Obligations of employer about supervising training person	174
209A	Electrical distribution entity may isolate powerlines in emergency	175
210	Inspection of entries in registers	176
210A	Time for giving electrical safety undertaking	176
211	Provision of information by retail entity	176
211AA	Provision of information by Residential Tenancies Authority	177
211A	Person chief executive may appoint as inspector	177
211B	Fees	177
Part 14	Transitional provisions	
Division 1	Interpretation	
212	Definitions for pt 14	178
Division 2	Transitional provisions for 2002 SL No. 260	
Subdivision 1	Electrical licences	
213	Equivalent licences to previous licences	178

214	Eligibility for electrical jointer licence	179
215	Eligibility for electrical linesperson licence	179
Subdivision 2	Matters in place before 1 October 2002	
216	Registered cathodic protection system	180
217	Approval of type of prescribed electrical article	180
218	Clearances for lines built before 1 January 1995	180
219	Termination of low voltage overhead service line built before 1 January 1995.	181
220	Clearances for lines built before commencement.	181
Division 3	Transitional provisions for Electrical Safety and Another Regulation Amendment Regulation (No. 1) 2007	
221	Further provision for electrical jointer licences	182
222	Further provision for electrical linesperson licences.	182
Schedule 1	External licences and electrical work licence equivalents . .	184
Schedule 2	Exclusion zones for electrical parts	186
Schedule 3	Prescribed classes of electrical equipment and relevant standards	196
Schedule 4	Clearance of overhead electric lines (other than low voltage service lines)	203
Schedule 5	Clearance of low voltage overhead service lines	211
Schedule 6	Prescribed electricity entities	214
Schedule 6A	Prescribed workplaces	215
Schedule 7	Fees	217
Schedule 8	Classes of electrical equipment for fees	219
Schedule 9	Dictionary	222
Endnotes		
1	Index to endnotes.	230
2	Date to which amendments incorporated.	230
3	Key	230
4	Table of reprints	231
5	List of legislation.	231
6	List of annotations	233

Electrical Safety Regulation 2002

[as amended by all amendments that commenced on or before 1 March 2008]

Part 1 Preliminary

1 Short title

This regulation may be cited as the *Electrical Safety Regulation 2002*.

2 Commencement

This regulation commences on 1 October 2002.

3 Purposes

The purposes of this regulation include the following—

- (a) ensuring the electrical safety of licensed electrical workers, other workers, licensed electrical contractors, consumers and the general public;
- (b) enhancing consumer protection in relation to electrical work;
- (c) stopping cathodic protection systems from damaging or interfering with the property of others;
- (d) ensuring a safe supply of electricity;
- (e) ensuring electrical equipment hired or sold is electrically safe.

4 How purposes are to be achieved

The ways adopted by this regulation for the achievement of its purposes include the following—

- (a) prescribing matters in support of the electrical licensing

- arrangements established under the Act;
- (b) prescribing requirements for working around exposed parts;
 - (c) prescribing requirements for electrical installations;
 - (d) prescribing matters about electrical equipment, including—
 - (i) requirements for electrical equipment; and
 - (ii) requirements for particular electrical equipment to be approved by the chief executive; and
 - (iii) requirements about the hiring, selling, testing and using of electrical equipment; and
 - (iv) requiring particular electrical equipment to be approved and marked for compliance with prescribed standards; and
 - (v) requirements for the testing of electrical equipment;
 - (e) prescribing requirements and procedures for the design, building and maintenance of electric lines and the works of electricity entities;
 - (f) prescribing requirements for the performance of electrical work;
 - (g) providing for the preparation, lodging and auditing of safety management plans;
 - (h) prescribing requirements for the operation of cathodic protection systems and requirements for particular systems to be registered by the chief executive;
 - (i) prescribing notification and reporting requirements for serious electrical incidents and dangerous electrical events.

5 Definitions

- (1) The dictionary in schedule 9 defines particular words used in this regulation.
- (2) If a word used in this regulation is not defined in the

dictionary, and is not defined in the Act, but is used in the wiring rules, it must, to the greatest practicable extent, be taken to have the same meaning in this regulation as it has in the wiring rules.

6 References to standards and other documents

(1) In this regulation, unless otherwise stated—

- (a) a reference to a standard using the designation made up of ‘AS’ and a number is a reference to the standard as in force from time to time under that designation; and

Example—

‘AS 3127’ is a reference to the standard that is currently in force under that designation.

- (b) a reference to a joint standard using the designation made up of ‘AS/NZS’ and a number is a reference to the joint standard as in force from time to time under that designation; and

Example—

‘AS/NZS 3350.2.11’ is a reference to the joint standard that is currently in force under that designation.

- (c) a reference to a standard or other document using ‘ENA’ as part of its name is a reference to the standard or other document as first published under the name quoted; and

Example—

A reference to the document known as the ENA LLM 01-2006 (Guidelines for live line barehand work) is a reference to that guideline as first published under that name.

- (d) subject to paragraphs (a) to (c), a reference to a standard or other document is a reference to the standard or other document as in force from time to time.

(2) Subsection (1)(a), (b) and (d) applies regardless of the edition or year of the standard, joint standard or other document.

Example of operation of subsection (2)—

In this regulation, a reference to AS/NZS 3000 is a reference to that standard as amended from time to time, and as remade from time to time.

- (3) Bracketed words appearing after a standard's designation are included for information purposes only.

7 Meaning of *qualified business person* and *qualified technical person*

- (1) A ***qualified business person***, for an individual, partnership or corporation, is an individual who satisfies the chief executive that he or she—
- (a) is a fit and proper person; and
 - (b) is competent to perform the business aspects of performing electrical work as, or for, a licensed electrical contractor; and
 - (c) either—
 - (i) has satisfactorily finished a course of instruction, or an examination required by the chief executive, on business aspects of performing electrical work; or
 - (ii) has been operating a business for a period of, or periods totalling, 5 years.
- (2) A ***qualified technical person***, for an individual, partnership or corporation, is an individual who satisfies the chief executive that he or she—
- (a) is a fit and proper person; and
 - (b) either—
 - (i) if the electrical work to be performed by the licensed electrical contractor may be performed only by the holder of an electrical work licence—has held for at least a year, or a shorter period considered acceptable by the chief executive, and still holds, an electrical work licence; or
 - (ii) has held for at least a year, or a shorter period considered acceptable by the chief executive, and still holds, an external contracting authority; and
 - (c) is competent to perform electrical work as, or for, a licensed electrical contractor; and

- (d) has satisfactorily finished a course of instruction, or an examination required by the chief executive, on technical aspects of performing electrical work.
- (3) Despite subsections (1) and (2), for a person who is an individual to be a qualified business person or qualified technical person—
- (a) for an individual who holds, or has applied for, an electrical contractor licence, the person must also be, or be an employee of, the individual; or
 - (b) for a partnership that holds, or has applied for, an electrical contractor licence, the person must also be a member or an employee of the partnership; or
 - (c) for a corporation that holds, or has applied for, an electrical contractor licence, the person must also be an executive officer, a member or an employee of the corporation.
- (4) In deciding whether a person who is an individual is a fit and proper person, the chief executive may only consider—
- (a) the standard of honesty and integrity demonstrated by the person in commercial and other activities in which the person has been involved; and
 - (b) any failure by the person to perform commercial or statutory obligations and the reasons for the failure.

Part 2 Electrical work

Division 1 Preliminary

8 Purpose of divs 2 to 5

Divisions 2 to 5 each prescribe a way of discharging the electrical safety obligation of an employer or self-employed person to ensure the person's business or undertaking is conducted in a way that is electrically safe.

Division 2 Basic requirements for electrical work

9 Definition for div 2

In this division—

electrical work does not include high voltage live line work.

10 Application of div 2

This division applies to the performance of electrical work for the purposes of the business or undertaking of an employer or self-employed person.

11 Requirements for electrical work

- (1) An employer or self-employed person must ensure that, unless the circumstances required under this division for the performance of live work apply, live work is not performed.

Maximum penalty—40 penalty units.

- (2) Without limiting what the employer or self-employed person must do to ensure compliance with subsection (1), the employer or self-employed person must ensure that—
 - (a) each exposed part is treated as if it is energised until it is isolated and proved not to be energised; and
 - (b) each high voltage exposed part is earthed.

12 Requirements for performance of live work

- (1) The following circumstances are required for the performance of live work—
 - (a) it is not practicable to perform the electrical work other than by live work because of 1 or more of the following—
 - (i) it is necessary in the interests of safety, whether or not electrical safety, for the work to be performed while the electrical equipment the subject of the electrical work is energised;

Electrical Safety Regulation 2002

Example for subparagraph (i)—

It may be necessary in the interests of road safety for a set of traffic lights to remain operating while electrical work is performed on the lights.

- (ii) a supply of electricity is necessary for the proper performance of the electrical work;
- (iii) there is no reasonable alternative to performing the electrical work by live work;

Example for subparagraph (iii)—

It may be necessary, to avoid widespread outages, to perform electrical work on works of an electricity entity by live work.

- (b) the employer or self-employed person has prepared, in a document,¹ a risk assessment of the performance of the live work;
- (c) the performance of the electrical work is in accordance with a safe system of work;

Example—

A safe system could include preventing persons from accessing the area where live work is being performed if the persons are not needed for the performance of the work.

- (d) the employer or self-employed person authorises the performance of the live work only after consultation with the person in control of the electrical equipment the subject of the electrical work;
- (e) the person who performs the live work has appropriate training for the performance of the live work;
- (f) testing equipment appropriate to the performance of the live work has been given to the person performing the electrical work, the testing equipment has been properly maintained, and the person performing the electrical work makes proper use of the testing equipment in performing the work;
- (g) clothing and personal protective equipment appropriate to the performance of the live work has been given to the

¹ See the *Acts Interpretation Act 1954*, section 36, definition *document*.

Electrical Safety Regulation 2002

person performing the electrical work and the person performing the electrical work makes proper use of the clothing and equipment in performing the work;

- (h) other than for electric line work, the isolation point of the electricity supply for the electrical equipment the subject of the electrical work—
 - (i) has been clearly identified; and
 - (ii) is able to be reached quickly without the need to climb over or shift obstructions;
- (i) the area where the electrical work is performed is clear of obstructions to the extent necessary for easy access to and from the area;
- (j) there is a safety observer observing the performance of the electrical work unless—
 - (i) the work involves testing electrical equipment; and
 - (ii) the risk assessment prepared under paragraph (b) does not show there is a high risk to electrical safety in performing the testing of the electrical equipment.

Example for subparagraph (ii)—

If a risk assessment does not show there is a high risk to electrical safety in performing the testing of the polarity of an installed outlet, a safety observer is not required to observe the performance of the work.

- (2) In this section—

safe system of work, for live work on a low voltage electrical installation, includes, but is not limited to, a system of work that complies with the provisions of AS/NZS 4836 (Safe working on low-voltage electrical installations) about ensuring the safety of persons while performing live work.

safety observer means a person who—

- (a) observes the performance of electrical work; and
- (b) is competent to help a person performing the electrical work; and

- (c) has been assessed in the last 6 months to be competent to rescue a person performing electrical work and provide resuscitation.

Division 3 High voltage live line work

13 Performance of high voltage live line work

- (1) A person must not perform high voltage live line work unless the person's performance of the work—
 - (a) is authorised in writing by the person in control of the electrical equipment the subject of the work; and
 - (b) is in accordance with a high voltage live line work management plan.

Maximum penalty—40 penalty units.

- (2) A person in control of electrical equipment may authorise a person's performance of high voltage live line work in relation to the electrical equipment only if—
 - (a) the person in control is satisfied the person—
 - (i) has successfully finished an appropriate course of training; and
 - (ii) has been assessed by the provider of the course as competent to perform the work; and
 - (b) the written authorisation states the voltages of the electrical equipment on which the high voltage live line work may be performed.

- (3) If the written authorisation provides for the performance of work on more than 1 occasion, the entity that gives the authorisation must, while the authorisation is in force, cause the person authorised to perform the high voltage live line work to be regularly assessed to ensure the person remains competent to perform the work.

Maximum penalty—40 penalty units.

(4) In this section—

high voltage live line work management plan means a plan for the performance of high voltage live line work that—

- (a) includes procedures developed in accordance with each of the following guidelines—
 - (i) ENA LLM 01-2006 (Guidelines for live line barehand work);
 - (ii) ENA LLM 02-2006 (Guidelines for live line stick work);
 - (iii) ENA LLM 03-2006 (Guidelines for live line glove and barrier work); and
- (b) is developed in conjunction with all of the following—
 - (i) representatives of workers who are to perform high voltage live line work in accordance with the plan;
 - (ii) if the high voltage live line work involves the works of an electricity entity—the electricity entity;
 - (iii) other persons who might reasonably be expected to have an interest in the performance of the high voltage live line work; and
- (c) has been approved by a person who—
 - (i) is an electrical engineer who has expertise as a professional engineer in the performance of high voltage live line work; or
 - (ii) has expertise the person in control of the electrical equipment the subject of the high voltage live line work decides is equivalent to the expertise mentioned in subparagraph (i).

Division 4 Testing of work

14 Testing of electrical equipment after electrical work

- (1) This section applies if electrical work is performed on electrical equipment.

- (2) A person who performs part or all of the electrical work, and is responsible for bringing the electrical equipment to a state of readiness for connection to a source of electricity for use for its intended purpose, must ensure the electrical equipment is tested, as required under subsections (5) and (6).

Maximum penalty—40 penalty units.

- (2A) However, if subsection (2) applies to a training person who is being supervised by a licensed electrical worker who is licensed to perform the work, subsection (2) applies to the licensed electrical worker and not the training person.

- (3) A licensed electrical contractor or electricity entity who performs the electrical work of connecting the electrical equipment to a source of electricity for use for its intended purpose must ensure the electrical equipment is tested as required under subsections (5) and (6).

Maximum penalty—40 penalty units.

- (4) Subsection (3) does not require a distribution entity to ensure the testing of the electrical equipment if—
- (a) the electrical work is, or is part of, electrical work performed on an electrical installation; and
 - (b) a licensed electrical contractor has given the distribution entity a notice under section 158² about the testing of the electrical work performed on the electrical installation.
- (5) The testing of the electrical equipment must be directed at ensuring that the electrical equipment, to the extent it is affected by the electrical work, is electrically safe.
- (6) If the electrical equipment is energised for testing, the person who performs the test must ensure persons not necessary for the testing are electrically safe.

15 Certificate of testing and safety

- (1) This section applies if a licensed electrical contractor performs electrical work that must be tested under this division.

² Section 158 (Notice by licensed electrical contractor of test)

- (2) The contractor must, as soon as practicable after the testing, ensure that the person for whom the electrical work was performed is given a certificate complying with this section.

Maximum penalty—40 penalty units.

- (3) The certificate must state the following—
- (a) the name and address of the person for whom the work was performed;
 - (b) the electrical equipment tested;
 - (c) the day the electrical equipment was tested;
 - (d) the number of the electrical contractor licence under which the electrical equipment was tested.
- (4) The certificate must certify that the electrical equipment, to the extent it is affected by the electrical work, is electrically safe.
- (5) A licensed electrical contractor must keep a copy of a certificate given under this section for at least 5 years after the certificate is given.

Maximum penalty for subsection (5)—20 penalty units.

Division 5 Requirements applying to employers and self-employed persons

16 Application of div 5

This division applies to the performance of electrical work for the purposes of the business or undertaking of an employer or self-employed person.

17 Testing and maintenance of safety equipment

- (1) An employer or self-employed person must ensure that—
- (a) safety equipment is used in the performance of electrical work; and
 - (b) the safety equipment is—

- (i) a suitable type for the electrical work being performed; and
- (ii) maintained so that it is suitable for use in the electrical work being performed; and
- (iii) if it is safety equipment that can not be visually confirmed as being correctly functioning and safe—tested at least every 6 months to ensure it provides the protection it is intended to provide; and
- (iv) labelled to state the day on or before which it is next due for testing; and
- (v) in good repair and condition.

Maximum penalty—40 penalty units.

- (2) The employer or self-employed person must keep records of the tests performed under subsection (1)(b)(iii) for at least 5 years.

Maximum penalty for subsection (2)—20 penalty units.

18 Employer or self-employed person to ensure suitability of testing instruments

- (1) This section applies to the following—
 - (a) an employer of a person required to perform tests on electrical work or safety equipment;
 - (b) a self-employed person required to perform tests on electrical work or safety equipment.
- (2) The employer or self-employed person must ensure—
 - (a) the test instruments used for the testing are designed for, and capable of correctly performing, the required tests; and
 - (b) if a testing instrument can not be visually confirmed as being correctly functioning and safe—that the instrument is tested at least every 6 months to ensure it is in proper working order; and

- (c) records of tests performed under paragraph (b) are kept for at least 5 years.

Maximum penalty—40 penalty units.

Division 6 Other requirements

19 Electrical equipment with serious defect not to be connected to electricity source

If an item of electrical equipment has a serious defect, a licensed electrical worker must not connect the equipment to a source of electricity for use for its intended purpose.

Maximum penalty—40 penalty units.

20 Signs on switches and disconnection points

- (1) This section applies if—
 - (a) a licensed electrical worker is performing electrical work; and
 - (b) to perform the work, the worker has de-energised, or otherwise isolated from electricity, an item of electrical equipment that is the subject of the electrical work or that is near where the electrical work is being performed; and
 - (c) to de-energise, or otherwise isolate, the item of electrical equipment, the licensed electrical worker has operated a device; and
 - (d) while the worker is performing the work, the worker does not have the device under the worker's sole effective control.
- (2) The licensed electrical worker must ensure that there is attached to the device, in a prominent position, a warning sign that is suitable in the circumstances, having regard to AS 1319 (Safety signs for the occupational environment).

Maximum penalty—40 penalty units.

- (3) The electrical worker must also ensure that—

- (a) the device, when in the open position, is locked; or

Examples for paragraph (a)—

- using a personal lock to lock an air conditioner isolator in the open position
- using a locking device that stops a miniature circuit breaker from being closed
- placing a lockable shroud on the male inlet plug of electrical equipment

- (b) other precautions are taken to stop the device being accidentally closed.

Examples for paragraph (b)—

- disengaging a circuit breaker so that the circuit breaker is separated from the busbars
- removing circuit cables from the fuse or circuit breaker
- insertion of a mechanical restriction

Maximum penalty—40 penalty units.

- (4) If the electrical work is being performed for the purposes of the business or undertaking of an employer or self-employed person, the employer or self-employed person must ensure that—

- (a) the licensed electrical worker has all the signs and equipment necessary for the worker to comply with subsections (2) and (3); and

- (b) the signs and equipment are used in the way required under the subsections.

Maximum penalty—40 penalty units.

- (5) In this section—

device means a circuit-breaker, disconnection point, fuse or switch.

21 Rescue and resuscitation training

- (1) An employer must ensure workers who are required to perform, or help in performing, electrical work are competent in rescue and resuscitation in accordance with recognised practices in the electricity industry.

- (2) Subsection (1) does not apply in relation to a worker if it is a condition of the worker's electrical work licence that the person must not act in a role for which it is a requirement that the worker be competent in rescue and resuscitation, including as a safety observer.

Maximum penalty—40 penalty units.

Division 7 Documents about electrical work

22 Application of div 7

This division applies to the performance of electrical work as part of the business or undertaking of a licensed electrical contractor.

23 Who may sign documents about electrical work

A person must not sign a document required under the Act, or by an electricity entity, about the performance of electrical work unless the person is—

- (a) if the electrical work was performed as part of the business or undertaking of a licensed electrical contractor who is an individual—a qualified technical person for the individual; or
- (b) if the electrical work was performed as part of the business or undertaking of a licensed electrical contractor that is a partnership—a qualified technical person for the partnership; or
- (c) if the electrical work was performed as part of the business or undertaking of a licensed electrical contractor that is a corporation—a qualified technical person for the corporation.

Maximum penalty—20 penalty units.

Division 8 General provisions

24 Misrepresentations about electrical equipment or work

- (1) A person must not, in trade or commerce, represent that someone who is not a licensed electrical worker may lawfully—
- (a) connect to a source of electricity an item of electrical equipment that may only be connected to a source of electricity by a licensed electrical worker; or
 - (b) do electrical work that may only be done by a licensed electrical worker.

Maximum penalty—40 penalty units.

- (2) An employer must take all reasonable steps to ensure the employer's workers do not contravene subsection (1).

Maximum penalty—40 penalty units.

24A Misrepresentations about lawful authority to contract for the performance of electrical work

- (1) A person must not, in trade or commerce, represent that someone who is not a licensed electrical contractor may lawfully contract for the performance of electrical work the person may not otherwise perform under the Act.

Example of electrical work that may be performed under the Act by someone who is not a licensed electrical contractor—

minor emergency repairs to make electrical equipment electrically safe performed by a licensed electrical mechanic³

Maximum penalty—40 penalty units.

- (2) An employer must take all reasonable steps to ensure the employer's workers do not contravene subsection (1).

Maximum penalty—40 penalty units.

3 See section 56(3) and (5) (Requirement for electrical contractor licence) of the Act.

Part 3 Licensing

Division 1 Electrical work licences

25 Classes of electrical work licences

The following classes of electrical work licences may be issued—

- (a) electrical mechanic licence;
- (b) electrical linesperson licence;
- (c) electrical fitter licence;
- (d) electrical jointer licence;
- (e) restricted electrical work licence;
- (f) electrical work training permit.

26 What electrical mechanic licence authorises

Subject to particular conditions or restrictions included in the licence, an electrical mechanic licence authorises the holder to perform all electrical work.

Examples of what the holder of an electrical mechanic licence may do—

- installing or changing an electrical installation or electric line
- maintaining, repairing, or connecting to a source of electricity, an item of electrical equipment

27 What electrical linesperson licence authorises

Subject to particular conditions or restrictions included in the licence, an electrical linesperson licence authorises the holder to perform all electric line work.

Examples of what the holder of an electrical linesperson licence may do—

- electrical work in the building or maintenance of an overhead electric line
- electrical work in the building or maintenance of street lighting connected to an overhead or underground electric line
- tests to ensure overhead electric lines are correctly connected

28 What electrical fitter licence authorises

Subject to particular conditions or restrictions included in the licence, an electrical fitter licence authorises the holder to perform all electrical equipment work.

Example of what the holder of an electrical fitter licence may do—

electrical work, whether in a workshop or on site, of building, manufacturing, fitting, assembling, erecting, operating, testing or repairing electrical equipment

29 What electrical jointer licence authorises

Subject to particular conditions or restrictions included in the licence, an electrical jointer licence authorises the holder to perform electrical work to the extent of the following—

- (a) installing, jointing and terminating cables to the extent the work requires specialised knowledge or skill;
- (b) electrical equipment work necessary for the work mentioned in paragraph (a).

30 What restricted electrical work licence authorises

- (1) A restricted electrical work licence authorises the holder to perform electrical work only of a particular type stated in the licence.

Example of what the holder of a restricted electrical work licence may do—

A restricted electrical work licence may restrict the holder to the performance of electrical work incidental or special to a particular calling.

- (2) A restricted electrical work licence—
 - (a) does not entitle the holder to another electrical licence; and
 - (b) must not be taken into account in deciding whether the holder is qualified to obtain or hold another electrical licence.

31 What electrical work training permit authorises

- (1) An electrical work training permit authorises the holder to perform electrical work stated in the permit in accordance with the conditions about training stated in the permit.
- (2) An electrical work training permit—
 - (a) does not entitle the holder to another electrical licence; and
 - (b) must not be taken into account in deciding whether the holder is qualified to obtain or hold another electrical licence.

32 External licence equivalents

An external licence mentioned in schedule 1 is equivalent to the electrical work licence stated in the schedule for the external licence.

Division 2 Electrical work licence requirements**33 General requirements**

- (1) This section states requirements that apply generally for the issue of an electrical work licence, other than an electrical work training permit, to an applicant for the licence.
- (2) The chief executive must be satisfied that—
 - (a) the applicant satisfies the eligibility requirements stated for the licence in this division; and
 - (b) the applicant is adequately able to understand, and read and write in, the English language without the aid of an interpreter.
- (3) The chief executive may consider the following about the applicant's activities, whether before or after the commencement of this section, as a licensed electrical worker—

Electrical Safety Regulation 2002

- (a) disciplinary action taken against the applicant under a law regulating the activities of licensed electrical workers;
 - (b) the applicant's non-performance of an obligation under a law about electrical work and the reasons for the non-performance.
- (4) The chief executive must be satisfied the applicant has been trained in, and is competent to carry out, resuscitation on an individual who has stopped breathing or is unconscious because of electric shock.
- (5) For an application for an electrical linesperson licence, the chief executive must also be satisfied the applicant has been trained in, and is competent to carry out, resuscitation and rescue at a pole-top or transmission tower on an individual who has stopped breathing or is unconscious because of electric shock.
- (6) Subsection (4) does not prevent the chief executive renewing or reinstating an electrical work licence if the chief executive is satisfied—
- (a) the applicant has a medical condition that prevents the applicant carrying out the resuscitation but does not otherwise affect the applicant's ability to perform electrical work under the licence; and
 - (b) in the particular circumstances, it is reasonable to allow the applicant to carry out electrical work under the licence subject to a condition that the applicant must not act in a role for which it is a requirement that the applicant be competent in resuscitation, including as a safety observer.
- (7) Subsection (5) does not prevent the chief executive renewing or reinstating an electrical linesperson licence if the chief executive is satisfied—
- (a) the applicant has a medical condition that prevents the applicant carrying out the resuscitation but does not otherwise affect the applicant's ability to perform electrical work under the licence; and
 - (b) in the particular circumstances, it is reasonable to allow the applicant to carry out electrical work under the

licence subject to a condition that the applicant must not act in a role for which it is a requirement that the applicant be competent in rescue at a pole top or transmission tower and in resuscitation, including as a safety observer.

34 Eligibility requirements for electrical mechanic licence

- (1) To be issued an electrical mechanic licence, an applicant must comply with subsection (2), (3) or (4).
- (2) The applicant must have—
 - (a) satisfactorily finished an apprenticeship under the *Vocational Education, Training and Employment Act 2000* to achieve competence in the trade work of an electrical mechanic; and
 - (b) satisfactorily finished a course of instruction decided by the chief executive; and
 - (c) produced to the chief executive a written statement that—
 - (i) states that the applicant is competent in the trade work of an electrical mechanic; and
 - (ii) is verified by the registered training organisation that issues a qualification or statement of attainment for training delivered to the applicant under the apprenticeship; and
 - (d) produced to the chief executive a written statement that—
 - (i) states that the applicant has satisfactorily finished the training to be delivered under the training plan or training plans for the apprenticeship; and
 - (ii) is verified by the person who as an employer is a party to the training plan under which the applicant finished the apprenticeship; and
 - (e) satisfied the chief executive the applicant is competent in the trade work of an electrical mechanic.

- (3) The applicant must have—
- (a) satisfactorily finished an apprenticeship outside Queensland that is, in the chief executive's opinion, at least equivalent to an apprenticeship mentioned in subsection (2)(a); and
 - (b) satisfactorily finished a course of instruction related to the apprenticeship that is, in the chief executive's opinion, at least equivalent to the course of instruction mentioned in subsection (2)(b); and
 - (c) produced to the chief executive a written statement that—
 - (i) states that the applicant is competent in the trade work of an electrical mechanic; and
 - (ii) is verified by the equivalent non-Queensland training organisation that issues a qualification or statement of attainment for training delivered to the applicant under the apprenticeship; and
 - (d) produced to the chief executive a written statement that—
 - (i) states that the applicant has satisfactorily finished the training to be delivered to the applicant under the apprenticeship; and
 - (ii) is verified by the employer under whom the applicant finished the apprenticeship; and
 - (e) satisfied the chief executive the applicant is competent in the trade work of an electrical mechanic.
- (4) The applicant must satisfy the chief executive that the applicant—
- (a) has a relevant qualification; and
 - (b) has complied with the chief executive's examination requirements; and
 - (c) is competent in the trade work of an electrical mechanic.
- (5) An applicant who satisfies the chief executive that the applicant held an electrical mechanic licence that was issued under the Act and has expired is taken to have a relevant qualification for subsection (4)(a).

(6) In this section—

relevant qualification, for an applicant, means that the applicant—

- (a) is the holder of a current electrical fitter licence; or
- (b) has served an apprenticeship to the calling of electrical mechanic under the *Vocational Education, Training and Employment Act 2000*, but has not satisfactorily finished the course of instruction mentioned in subsection (2)(b); or
- (c) is the holder of a tradesman's certificate within the meaning of the *Tradesmen's Rights Regulation Act 1946* (Cwlth) in the classification of electrical mechanic.

35 Eligibility requirements for electrical linesperson licence

- (1) To be issued an electrical linesperson licence, an applicant must comply with subsection (2), (3) or (4).
- (2) The applicant must have—
 - (a) satisfactorily finished an apprenticeship under the *Vocational Education, Training and Employment Act 2000* to achieve competence in the trade work of an electrical linesperson; and
 - (b) satisfactorily finished a course of instruction decided by the chief executive; and
 - (c) produced to the chief executive a written statement that—
 - (i) states that the applicant is competent in the trade work of an electrical linesperson; and
 - (ii) is verified by the registered training organisation that issues a qualification or statement of attainment for training delivered to the applicant under the apprenticeship; and
 - (d) produced to the chief executive a written statement that—

Electrical Safety Regulation 2002

- (i) states that the applicant has satisfactorily finished the training to be delivered under the training plan or training plans for the apprenticeship; and
 - (ii) is verified by the person who as an employer is a party to the training plan under which the applicant finished the apprenticeship; and
 - (e) satisfied the chief executive the applicant is competent in the trade work of an electrical linesperson.
- (3) The applicant must have—
 - (a) satisfactorily finished an apprenticeship outside Queensland that is, in the chief executive's opinion, at least equivalent to an apprenticeship mentioned in subsection (2)(a); and
 - (b) satisfactorily finished a course of instruction related to the apprenticeship that is, in the chief executive's opinion, at least equivalent to the course of instruction mentioned in subsection (2)(b); and
 - (c) produced to the chief executive a written statement that—
 - (i) states that the applicant is competent in the trade work of an electrical linesperson; and
 - (ii) is verified by the equivalent non-Queensland training organisation that issues a qualification or statement of attainment for training delivered to the applicant under the apprenticeship; and
 - (d) produced to the chief executive a written statement that—
 - (i) states that the applicant has satisfactorily finished the training to be delivered to the applicant under the apprenticeship; and
 - (ii) is verified by the employer under whom the applicant finished the apprenticeship; and
 - (e) satisfied the chief executive the applicant is competent in the trade work of an electrical linesperson.
- (4) The applicant must satisfy the chief executive that the applicant—

- (a) has a relevant qualification; and
 - (b) has complied with the chief executive's technical and practical requirements, including any examination requirements; and
 - (c) is competent in the trade work of an electrical linesperson.
- (5) An applicant who satisfies the chief executive that the applicant held an electrical linesperson licence that was issued under the Act and has expired is taken to have a relevant qualification for subsection (4)(a).
- (6) In this section—
- relevant qualification*, for an applicant, means that the applicant—
- (a) is the holder of a current electrical mechanic licence; or
 - (b) has served an apprenticeship of electrical linesperson under *Vocational Education, Training and Employment Act 2000*, but has not satisfactorily finished the course of instruction mentioned in subsection (2)(b); or
 - (c) is the holder of a tradesman's certificate within the meaning of the *Tradesmen's Rights Regulation Act 1946* (Cwlth) in the classification of electrical linesperson.

36 Eligibility requirements for electrical fitter licence

- (1) To be issued an electrical fitter licence, an applicant must comply with subsection (2), (3) or (4).
- (2) The applicant must have—
 - (a) satisfactorily finished an apprenticeship under the *Vocational Education, Training and Employment Act 2000* to achieve competence in the trade work of an electrical fitter; and
 - (b) satisfactorily finished a course of instruction decided by the chief executive; and
 - (c) produced to the chief executive a written statement that—

Electrical Safety Regulation 2002

- (i) states that the applicant is competent in the trade work of an electrical fitter; and
 - (ii) is verified by the registered training organisation that issues a qualification or statement of attainment for training delivered to the applicant under the apprenticeship; and
 - (d) produced to the chief executive a written statement that—
 - (i) states that the applicant has satisfactorily finished the training to be delivered under the training plan or training plans for the apprenticeship; and
 - (ii) is verified by the person who as an employer is a party to the training plan under which the applicant finished the apprenticeship; and
 - (e) satisfied the chief executive the applicant is competent in the trade work of an electrical fitter.
- (3) The applicant must have—
- (a) satisfactorily finished an apprenticeship outside Queensland that is, in the chief executive's opinion, at least equivalent to an apprenticeship mentioned in subsection (2)(a); and
 - (b) satisfactorily finished a course of instruction related to the apprenticeship that is, in the chief executive's opinion, at least equivalent to the course of instruction mentioned in subsection (2)(b); and
 - (c) produced to the chief executive a written statement that—
 - (i) states that the applicant is competent in the trade work of an electrical fitter; and
 - (ii) is verified by the equivalent non-Queensland training organisation that issues a qualification or statement of attainment for training delivered to the applicant under the apprenticeship; and
 - (d) produced to the chief executive a written statement that—

- (i) states that the applicant has satisfactorily finished the training to be delivered to the applicant under the apprenticeship; and
 - (ii) is verified by the employer under whom the applicant finished the apprenticeship; and
- (e) satisfied the chief executive the applicant is competent in the trade work of an electrical fitter.
- (4) The applicant must satisfy the chief executive that the applicant—
 - (a) has a relevant qualification; and
 - (b) has complied with the chief executive's examination requirements; and
 - (c) is competent in the trade work of an electrical fitter.
- (5) An applicant who satisfies the chief executive that the applicant held an electrical fitter licence that was issued under the Act and has expired is taken to have a relevant qualification for subsection (4)(a).
- (6) In this section—

relevant qualification, for an applicant, means that the applicant—

 - (a) is the holder of a current electrical mechanic licence; or
 - (b) has served an apprenticeship to the calling of electrical fitter under the *Vocational Education, Training and Employment Act 2000*, but has not satisfactorily finished the course of instruction mentioned in subsection (2)(b); or
 - (c) is the holder of a tradesman's certificate within the meaning of the *Tradesmen's Rights Regulation Act 1946* (Cwlth) in the classification of electrical fitter.

37 Eligibility requirements for electrical jointer licence

- (1) To be issued an electrical jointer licence, an applicant must comply with subsection (2), (3) or (4).

- (2) The applicant must have—
- (a) satisfactorily finished an apprenticeship under the *Vocational Education, Training and Employment Act 2000* to achieve competence in the trade work of an electrical joiner; and
 - (b) satisfactorily finished a course of instruction decided by the chief executive; and
 - (c) produced to the chief executive a written statement that—
 - (i) states that the applicant is competent in the trade work of an electrical joiner; and
 - (ii) is verified by the registered training organisation that issues a qualification or statement of attainment for training delivered to the applicant under the apprenticeship; and
 - (d) produced to the chief executive a written statement that—
 - (i) states that the applicant has satisfactorily finished the training to be delivered under the training plan or training plans for the apprenticeship; and
 - (ii) is verified by the person who as an employer is a party to the training plan under which the applicant finished the apprenticeship; and
 - (e) satisfied the chief executive the applicant is competent in the trade work of an electrical joiner.
- (3) The applicant must have—
- (a) satisfactorily finished an apprenticeship outside Queensland that is, in the chief executive's opinion, at least equivalent to an apprenticeship mentioned in subsection (2)(a); and
 - (b) satisfactorily finished a course of instruction related to the apprenticeship that is, in the chief executive's opinion, at least equivalent to the course of instruction mentioned in subsection (2)(b); and
 - (c) produced to the chief executive a written statement that—

Electrical Safety Regulation 2002

- (i) states that the applicant is competent in the trade work of an electrical joiner; and
 - (ii) is verified by the equivalent non-Queensland training organisation that issues a qualification or statement of attainment for training delivered to the applicant under the apprenticeship; and
 - (d) produced to the chief executive a written statement that—
 - (i) states that the applicant has satisfactorily finished the training to be delivered to the applicant under the apprenticeship; and
 - (ii) is verified by the employer under whom the applicant finished the apprenticeship; and
 - (e) satisfied the chief executive the applicant is competent in the trade work of an electrical joiner.
- (4) The applicant must satisfy the chief executive that the applicant—
- (a) has a relevant qualification; and
 - (b) has complied with the chief executive's technical and practical requirements, including any examination requirements; and
 - (c) is competent in the trade work of an electrical joiner.
- (5) An applicant who satisfies the chief executive that the applicant held an electrical joiner licence that was issued under the Act and has expired is taken to have a relevant qualification for subsection (4)(a).
- (6) In this section—
- relevant qualification***, for an applicant, means that the applicant—
- (a) is the holder of a current electrical mechanic licence; or
 - (b) has served an apprenticeship to the calling of electrical joiner under *Vocational Education, Training and Employment Act 2000*, but has not satisfactorily finished the course of instruction mentioned in subsection (2)(b);
or

- (c) is the holder of a tradesman's certificate within the meaning of the *Tradesmen's Rights Regulation Act 1946* (Cwlth) in the classification of electrical joiner.

38 Eligibility requirements for restricted electrical work licence

- (1) To be issued a restricted electrical work licence, an applicant must comply with subsection (2), (3), (4) or (5).
- (2) The applicant must have—
 - (a) satisfactorily finished a course of training under the *Vocational Education, Training and Employment Act 2000* the chief executive considers to be appropriate; and
 - (b) satisfactorily finished a course of instruction decided by the chief executive; and
 - (c) produced to the chief executive a written statement that—
 - (i) states that the applicant is competent in performing electrical work the subject of the application; and
 - (ii) is verified by the registered training organisation that delivered training to the applicant to finish the course of training; and
 - (d) if the course is training delivered to the applicant under a training plan—produced to the chief executive a written statement that—
 - (i) states that the applicant has satisfactorily finished the training to be delivered under the training plan; and
 - (ii) is verified by the person who as an employer is a party to the training plan; and
 - (e) satisfied the chief executive the applicant is competent to perform electrical work the subject of the licence.
- (3) The applicant must have—
 - (a) satisfactorily finished a course of training outside Queensland that is, in the chief executive's opinion, at

Electrical Safety Regulation 2002

- least equivalent to the course of training mentioned in subsection (2)(a); and
- (b) satisfactorily finished a course of instruction that is, in the chief executive's opinion, at least equivalent to the course of instruction mentioned in subsection (2)(b); and
 - (c) produced to the chief executive a written statement that—
 - (i) states that the applicant is competent in performing electrical work the subject of the application; and
 - (ii) is verified by the equivalent non-Queensland training organisation that issues a qualification or statement of attainment for the course; and
 - (d) if the course is training delivered to the applicant under an apprenticeship or traineeship—produced to the chief executive a written statement that—
 - (i) states that the applicant has satisfactorily finished the training to be delivered to the applicant under the apprenticeship or traineeship; and
 - (ii) is verified by the employer under whom the applicant finished the apprenticeship or traineeship; and
 - (e) satisfied the chief executive the applicant is competent to perform electrical work the subject of the licence.
- (4) The applicant must be the holder of a current licence, permit, certificate or other authority issued under a law of the Commonwealth, another State or New Zealand that the chief executive decides is equivalent to the restricted electrical work licence.
- (5) The applicant must have—
- (a) satisfied the chief executive that the applicant has a relevant qualification; and
 - (b) satisfactorily finished a course of instruction decided by the chief executive; and
 - (c) produced to the chief executive a written statement that—

Electrical Safety Regulation 2002

- (i) states that the applicant is competent in performing electrical work the subject of the application; and
- (ii) is verified by the registered training organisation that delivered training to the applicant to finish the course of instruction; and
- (d) if the course is training delivered to the applicant under a training plan, produced to the chief executive a written statement that—
 - (i) states that the applicant has satisfactorily finished the training to be delivered under the training plan; and
 - (ii) is verified by the person who as an employer is a party to the training plan; and
- (e) satisfied the chief executive the applicant is competent to perform electrical work the subject of the licence.
- (6) An applicant who satisfies the chief executive that the applicant held a restricted electrical work licence that was issued under the Act and has expired is taken to have a relevant qualification for subsection (5)(a).
- (7) In this section—

corresponding training department means a department of government of another State in which a law corresponding to the *Vocational Education, Training and Employment Act 2000* is administered.

relevant qualification, for an applicant, means that the applicant—

- (a) is the holder of a tradesperson's certificate within the meaning of the *Tradesmen's Rights Regulation Act 1946* (Cwlth) in a calling that the chief executive has decided requires the tradesperson to perform electrical work; or
- (b) is the holder of a tradesperson's certificate issued by a corresponding training department in a calling that the chief executive has decided requires the tradesperson to perform electrical work; or
- (c) has equivalent qualifications or experience in a calling that the chief executive decides requires the person to perform electrical work.

38A Eligibility requirements for electrical work training permit

- (1) To be issued an electrical work training permit to perform electrical work stated in the permit, an applicant must satisfy the chief executive that the applicant has a relevant qualification under section 34(6), 35(6), 36(6), 37(6) or 38(7) for the stated electrical work.

Example—

A person applies for an electrical mechanic licence. The person does not satisfy the eligibility requirements for an electrical mechanic licence under section 34(2), (3) or (4). The person may be issued an electrical work training permit if the person has a relevant qualification under section 34(6).

- (2) The chief executive may also consider the following about the applicant's activities, whether before or after the commencement of this section—
 - (a) disciplinary action taken against the applicant under a law regulating the activities of licensed electrical workers;
 - (b) the applicant's non-performance of an obligation under a law about electrical work and the reasons for the non-performance.

39 Term of electrical work licence

- (1) Each of the following may be issued, renewed or reinstated for a maximum of 5 years—
 - (a) electrical mechanic licence;
 - (b) electrical linesperson licence;
 - (c) electrical fitter licence;
 - (d) electrical jointer licence;
 - (e) restricted electrical work licence.
- (2) An electrical work training permit may be issued, renewed or reinstated for a maximum of 1 year.

Division 3 Electrical contractor licence requirements

40 Eligibility requirements for electrical contractor licence for individual

- (1) To be issued an electrical contractor licence, an individual must—
 - (a) have at least 1 qualified business person and 1 qualified technical person; and
 - (b) satisfy the financial and insurance requirements prescribed in this division for an individual for an electrical contractor licence; and
 - (c) satisfy the chief executive electrical work to be performed by the individual as a licensed electrical contractor is proposed to be—
 - (i) performed by a qualified technical person for the individual under the person's electrical work licence; or
 - (ii) supervised by a qualified technical person for the individual who is authorised to perform the work under the person's electrical work licence.
- (2) The chief executive must endorse the electrical contractor licence with the name of at least 1 qualified business person and 1 qualified technical person for the individual.
- (3) The individual may, before the issue of the electrical contractor licence, or at any time after its issue but while the electrical contractor licence is in force, apply to the chief executive to have other names endorsed on the electrical contractor licence as the names of qualified business persons or qualified technical persons for the individual.
- (4) The chief executive must endorse a person's name in accordance with the application if the chief executive is satisfied the person is a qualified business person or qualified technical person for the individual.
- (5) If a person whose name is endorsed on the electrical contractor licence as a qualified technical person is no longer

- the holder of an electrical work licence or external contracting authority, or is no longer an employee of the individual—
- (a) the individual must advise the chief executive of the fact within 1 month after the person stops being—
 - (i) the holder of the licence or authority; or
 - (ii) an employee of the individual; and
 - (b) the chief executive must, on receiving the advice, take the endorsement from the electrical contractor licence.
- (6) If a person whose name is endorsed on the electrical contractor licence as a qualified business person is no longer an employee of the individual or a qualified business person—
- (a) the individual must advise the chief executive of the fact within 1 month after the person stops being—
 - (i) an employee of the individual; or
 - (ii) a qualified business person; and
 - (b) the chief executive must, on receiving the advice, take the endorsement from the licence.
- (7) The electrical contractor licence is automatically suspended if, for a period of 1 month, there is no person—
- (a) who is a qualified business person for the individual and whose name is endorsed on the electrical contractor licence as a qualified business person for the individual; or
 - (b) who is a qualified technical person for the individual and whose name is endorsed on the electrical contractor licence as a qualified technical person for the individual.
- (8) If, within 1 month after a licence for an individual is automatically suspended under subsection (7), there is still no person whose name is endorsed on the electrical contractor licence for the individual as mentioned in subsection (7)(a) or (b), the licence is automatically cancelled.

41 Eligibility requirements for electrical contractor licence for partnership

- (1) To be issued an electrical contractor licence, a partnership must—
 - (a) have at least 1 qualified business person and 1 qualified technical person; and
 - (b) satisfy the financial and insurance requirements prescribed in this division for an applicant for an electrical contractor licence; and
 - (c) satisfy the chief executive electrical work to be performed by the partnership as a licensed electrical contractor is proposed to be—
 - (i) performed by a qualified technical person for the partnership under the person's electrical work licence; or
 - (ii) supervised by a qualified technical person for the partnership who is authorised to perform the work under the person's electrical work licence.
- (2) The chief executive must endorse the electrical contractor licence with the name of at least 1 qualified business person and 1 qualified technical person for the partnership.
- (3) The partnership may, before the issue of the electrical contractor licence, or at any time after its issue but while the electrical contractor licence is in force, apply to the chief executive to have other names endorsed on the electrical contractor licence as the names of qualified business persons or qualified technical persons for the partnership.
- (4) The chief executive must endorse a person's name in accordance with the application if the chief executive is satisfied the person is a qualified business person or qualified technical person for the partnership.
- (5) If a person whose name is endorsed on the electrical contractor licence as a qualified technical person is no longer the holder of an electrical work licence or external contracting authority, or is no longer an employee of the partnership—
 - (a) the partnership must advise the chief executive of the fact within 1 month after the person stops being—

- (i) the holder of the licence or authority; or
 - (ii) an employee of the partnership; and
 - (b) the chief executive must, on receiving the advice, take the endorsement from the electrical contractor licence.
- (6) If a person whose name is endorsed on the electrical contractor licence as a qualified business person is no longer an employee of the partnership or a qualified business person—
- (a) the partnership must advise the chief executive of the fact within 1 month after the person stops being—
 - (i) an employee of the partnership; or
 - (ii) a qualified business person; and
 - (b) the chief executive must, on receiving the advice, take the endorsement from the licence.
- (7) The electrical contractor licence is automatically suspended if, for a period of 1 month, there is no person—
- (a) who is a qualified business person for the partnership and whose name is endorsed on the electrical contractor licence as a qualified business person for the partnership; or
 - (b) who is a qualified technical person for the partnership and whose name is endorsed on the electrical contractor licence as a qualified technical person for the partnership.
- (8) If, within 1 month after a licence for a partnership is automatically suspended under subsection (7), there is still no person whose name is endorsed on the electrical contractor licence for the partnership as mentioned in subsection (7)(a) or (b), the licence is automatically cancelled.

42 Eligibility requirements for electrical contractor licence for corporation

- (1) To be issued an electrical contractor licence, a corporation must—

Electrical Safety Regulation 2002

- (a) have at least 1 qualified business person and 1 qualified technical person; and
 - (b) satisfy the financial and insurance requirements prescribed in this division for an applicant for an electrical contractor licence; and
 - (c) satisfy the chief executive electrical work to be performed by the corporation as a licensed electrical contractor is proposed to be—
 - (i) performed by a qualified technical person for the corporation under the person's electrical work licence; or
 - (ii) supervised by a qualified technical person for the corporation who is authorised to perform the work under the person's electrical work licence.
- (2) The chief executive must endorse the electrical contractor licence with the name of at least 1 qualified business person and 1 qualified technical person for the corporation.
- (3) The corporation may, before the issue of the electrical contractor licence, or at any time after its issue but while the electrical contractor licence is in force, apply to the chief executive to have other names endorsed on the electrical contractor licence as the names of qualified business persons or qualified technical persons for the corporation.
- (4) The chief executive must endorse a person's name in accordance with the application if the chief executive is satisfied the person is a qualified business person or qualified technical person for the corporation.
- (5) If a person whose name is endorsed on the electrical contractor licence as a qualified technical person is no longer the holder of an electrical work licence or external contracting authority, or is no longer an employee of the corporation—
- (a) the corporation must advise the chief executive of the fact within 1 month after the person stops being—
 - (i) the holder of the licence or authority; or
 - (ii) an employee of the corporation; and
 - (b) the chief executive must, on receiving the advice, take the endorsement from the electrical contractor licence.

- (6) If a person whose name is endorsed on the electrical contractor licence as a qualified business person is no longer an employee of the corporation or a qualified business person—
 - (a) the corporation must advise the chief executive of the fact within 1 month after the person stops being—
 - (i) an employee of the corporation; or
 - (ii) a qualified business person; and
 - (b) the chief executive must, on receiving the advice, take the endorsement from the licence.
- (7) The electrical contractor licence is automatically suspended if, for a period of 1 month, there is no person—
 - (a) who is a qualified business person for the corporation and whose name is endorsed on the electrical contractor licence as a qualified business person for the corporation; or
 - (b) who is a qualified technical person for the corporation and whose name is endorsed on the electrical contractor licence as a qualified technical person for the corporation.
- (8) If, within 1 month after a licence for a corporation is automatically suspended under subsection (7), there is still no person whose name is endorsed on the electrical contractor licence for the corporation as mentioned in subsection (7)(a) or (b), the licence is automatically cancelled.

43 Financial and insurance requirements for applicant for electrical contractor licence

- (1) This section prescribes the financial and insurance requirements for an applicant for an electrical contractor licence.
- (2) An applicant for an electrical contractor licence must give to the chief executive—
 - (a) evidence that the applicant has public liability insurance for at least \$5000000, under a contract of insurance approved by the chief executive; and

- (b) if the applicant is an individual or partnership—
 - (i) evidence that the applicant has net realisable assets of \$5000; or
 - (ii) evidence, in a form approved by the chief executive, that the applicant has \$5000 available for its disposal; and
- (c) if the applicant is a corporation—
 - (i) a document, in a form approved by the chief executive, stating that the applicant has net realisable assets of \$10000; or
 - (ii) evidence, in a form approved by the chief executive, that the applicant has \$10000 available for its disposal.

44 Change of name of corporation or partnership

- (1) This section applies if, for a corporation or partnership that is the holder of an electrical contractor licence, there is a change in either of the following—
 - (a) the name of the corporation or partnership;
 - (b) if the corporation or partnership carries on business under a name other than its name—the name (*business name*) under which it carries on business.
- (2) The corporation or partnership must, within 1 month after the change of name or business name, give written notice of the change to the chief executive.

Maximum penalty—20 penalty units.
- (3) The written notice must be accompanied by the electrical contractor licence, and may be accompanied by an application about how the chief executive is to act under subsection (4).
- (4) After receiving the written notice and considering any accompanying application, the chief executive may—
 - (a) endorse the licence with information about the change of name or business name and reissue it to the corporation or partnership; or

- (b) cancel the licence and issue a new licence; or
 - (c) cancel the licence.
- (5) A licence reissued by the chief executive with an endorsement of the change of the name or business name of the corporation or partnership, subject to the endorsement, has continuing effect as the original electrical contractor licence.
- (6) A new licence issued by the chief executive under this section must be endorsed with a memorandum stating the reasons for the issue of the new licence.
- (7) If the chief executive acts under subsection (4)(c) to cancel the licence, the chief executive must give the corporation or partnership an information notice for the decision to cancel.

45 Change in membership of partnership

- (1) This section applies if—
- (a) a partnership is the holder of an electrical contractor licence; and
 - (b) there is a change in the membership of the partnership, whether by the death or retirement of a member or the admission of a new member.
- (2) The partnership must, within 1 month after the membership change, give written notice of the change to the chief executive.
- Maximum penalty—20 penalty units.
- (3) The written notice must give full information and particulars of the change.
- (4) The written notice must be accompanied by the electrical contractor licence, and may be accompanied by an application about how the chief executive is to act under subsection (5).
- (5) After receiving the written notice and considering any accompanying application, the chief executive may—
- (a) endorse the licence with information about the membership change and reissue it to the partnership; or

- (b) cancel the licence and issue a new licence; or
 - (c) cancel the licence.
- (6) A licence reissued by the chief executive with an endorsement of the change of the membership of the partnership, subject to the endorsement, has continuing effect as the original electrical contractor licence.
- (7) A new licence issued by the chief executive must be endorsed with a memorandum stating the reasons for its issue.
- (8) The chief executive may issue a new licence to the partnership only if the chief executive is satisfied that—
- (a) the entire business of electrical contracting work carried on by the partnership in Queensland before the membership change is to be carried on by the partnership after the new licence is issued; and
 - (b) the partnership complies with the eligibility requirements for the issue of the licence.
- (9) If the chief executive acts under subsection (5)(c) to cancel the licence, the chief executive must give the partnership an information notice for the decision to cancel.
- (10) Nothing in this section affects the requirement under this division for the endorsement of an electrical contractor licence issued to a partnership

46 Term of electrical contractor licence

An electrical contractor licence may be issued, renewed or reinstated for a maximum of 1 year.

Division 4 Miscellaneous

47 Eligibility requirements for renewal or reinstatement of electrical licence

To renew or reinstate an electrical licence, the chief executive must be satisfied the applicant for the renewal or reinstatement continues to satisfy the eligibility requirements applying under this part for the issue of the licence.

48 Application requirements

- (1) An electrical licence application under part 4, division 2⁴ of the Act must be accompanied by the fee for the application.
- (2) An application under this part about an electrical licence must—
 - (a) be made in the approved form; and
 - (b) be accompanied by the fee for the application.

49 Giving chief executive cancelled or suspended licence or licence to be endorsed

The holder of an electrical licence, or other person who has control of the licence, must, if required by the chief executive, give the licence to the chief executive if the licence—

- (a) has been cancelled or suspended; or
- (b) has ended; or
- (c) is required to have anything endorsed on it.

Maximum penalty—20 penalty units.

50 Replacement of electrical licence

- (1) If, on application by the holder of an electrical licence, the chief executive is satisfied that the licence has been lost, damaged or destroyed, the chief executive may issue a replacement licence.
- (2) However, if a fixed fee applies to the application, the application must be accompanied by the fixed fee.

51 Surrender of electrical licence

The holder of an electrical licence may surrender the licence by written notice given to the chief executive.

4 Part 4 (Licences), division 2 (Electrical licence applications) of the Act

52 Register of electrical licences

- (1) The chief executive must keep a register containing information about electrical licences, in the form the chief executive considers appropriate to ensure the information in the register can be efficiently recorded and accessed.

Example—

The chief executive may decide to keep the register of electrical licences in electronic form.

- (2) The chief executive may order the information in the register of electrical licences in the way the chief executive considers appropriate.

Example—

The chief executive may decide to separate historical information about electrical licences from current information.

- (3) Without limiting subsections (1) and (2), the register of electrical licences must include, for each electrical licence—
- (a) the full name and address of the holder; and
 - (b) an identifying number; and
 - (c) when the licence was issued; and
 - (d) details of every renewal and reinstatement of the licence, and of any failure to renew the licence; and
 - (e) details of disciplinary action taken by the licensing committee against the holder; and
 - (f) details of anything else the chief executive considers should be included in the register of electrical licences.

Example for paragraph (f)—

the conditions or restrictions on an electrical work licence

- (4) If contact details recorded in the register of electrical licences for the holder of an electrical licence, including the name and address of the holder, are no longer correct, the holder must, within 14 days after the details become incorrect, give the chief executive notice of the correct details.
- (5) Subsection (4) does not apply to—
- (a) the change of name of a corporation or partnership that is the holder of an electrical contractor licence; or

- (b) the change of the membership of a partnership that is the holder of an electrical contractor licence.
- (6) The chief executive may publish some or all of the information included in the register in the way the chief executive considers appropriate.

Example for subsection (6)—

publishing the register on the internet in a database form allowing consumers to obtain licensing details about electrical contractors, or allowing an employer to check the validity of an employee's electrical work licence

53 Examinations

- (1) In deciding examinations for assessing a person's competency, or conditions with which a person must comply under this part, the chief executive may decide that the person must—
 - (a) undertake an examination conducted by the chief executive; or
 - (b) satisfactorily finish a course of instruction recognised by the chief executive at which the student's performance is assessed during the course; or
 - (c) undertake 1 or more examinations, oral or written tests, or practical tests.
- (2) The examinations and tests may be conducted by—
 - (a) the chief executive; or
 - (b) an examiner approved by the chief executive under section 54; or
 - (c) a registered training organisation under the *Vocational Education, Training and Employment Act 2000*.

54 Approved examiners

The chief executive may approve examiners to conduct examinations or tests required by the chief executive.

55 Refund of fees

- (1) This section applies if any of the following applications is refused by the chief executive or is withdrawn before it is decided—
 - (a) an application for an electrical licence;
 - (b) an application for renewal or reinstatement of an electrical licence.
- (2) The amount stated in schedule 7 as the administration component of the fee paid for the application must be refunded.

55A Operation of trade contractor's licence

- (1) For the conduct of a business or undertaking that includes the performance of electrical work, a person is taken to be the holder of an electrical contractor licence to the extent that performance of the electrical work is a necessary part of, or is incidental to, the performance of work under a trade contractor's licence.

- (2) In this section—

electrical work does not include electrical installation work.

trade contractor's licence means a trade contractor's licence under the *Queensland Building Services Authority Regulation 2003*.

56 Advertising by licensed electrical contractor

The holder of an electrical contractor licence who publishes an advertisement about the holder's business must ensure the advertisement—

- (a) states—
 - (i) the name under which the holder is licensed; or
 - (ii) if the holder carries on business under a registered business name, the holder's registered business name; and

- (b) states that the holder is licensed under the Act and the identifying number of the holder's electrical contractor licence.

Maximum penalty—40 penalty units.

57 Performing electrical work without electrical licence

For section 55(3)(d)⁵ of the Act, the following testing is authorised—

- (a) the testing of electrical equipment by a competent person, if the testing is required under part 5, division 5 or section 126;⁶
- (b) the testing of the works of an electricity entity by a competent person;

Example for paragraph (b)—

a competent person testing protection relay operation that is part of the works of an electricity entity

- (c) the testing of electrical equipment by a person, other than testing mentioned in paragraph (a) or (b), if the testing does not interfere with the integrity of the electrical equipment.

Examples for paragraph (c)—

- a person testing a safety switch in a domestic electrical installation by operating a test button on the safety switch
- a person using an appropriate voltmeter to measure voltage

57A Details to be included in register of workers

The following details are prescribed for the Act, schedule 2, definition *prescribed details* for the holder of an electrical work licence engaged to perform or supervise prescribed electrical work—

5 Section 55 (Requirement for electrical work licence) of the Act

6 Part 5 (Electrical installations), division 5 (Workplace electrical installations) or section 126 (Hiring electrical equipment)

- (a) the holder's name;
- (b) the following details about the holder's electrical work licence—
 - (i) the number of the licence or, if it is an external licence, the number, code or another way of identifying the licence;
 - (ii) the class of the licence;
 - (iii) if the licence is a restricted electrical work licence—the type of electrical work stated on the licence;
 - (iv) the conditions or restrictions included in the licence;
 - (v) the day the licence expires;
 - (vi) if the licence is an external licence—the jurisdiction in which the external licence was issued.

Part 4 Working around electrical parts

Division 1 Preliminary

58 Purpose of pt 4

- (1) This part prescribes a way of discharging the electrical safety obligation of an employer or self-employed person to ensure that the person's business or undertaking is conducted in a way that is electrically safe.
- (2) In particular, this part prescribes requirements about persons performing work in contact with, or near to, electrical parts.

59 Definitions for pt 4

In this part—

authorised person, for an electrical part, means a person who—

- (a) has enough technical knowledge and experience to do work that involves contact with, or being near to, the electrical part; and
- (b) has been approved by the person in control of the electrical part to do work that involves contact with, or being near to, the electrical part, or is authorised to act for the person in control of the electrical part.

direct contact see section 60.

electrical part means—

- (a) an exposed part; or
- (b) an overhead insulated electric line.

exclusion zone see section 61.

handling includes any of the following—

- (a) carrying;
- (b) connected to, whether or not temporarily;
- (c) controlling;
- (d) holding;
- (e) lifting.

instructed person, for an electrical part, means a person who is acting under the supervision of an authorised person for the electrical part.

operating plant means plant being operated for its intended purpose, unless the operation of the plant can not materially affect the distance between the plant and any electrical part in relation to which there is an exclusion zone under this part.

Examples of operating plant—

- a tip truck tipping a load
- a fixed crane operating at a building site

Electrical Safety Regulation 2002

- a vehicle that includes an elevated work platform being used for clearing vegetation from around overhead electric lines
- a concrete pumping truck pumping concrete
- a harvester with height changeable attachments being used to transfer grain to a truck

Example of plant that is not operating plant—

a furniture removal van under an electric line raising or lowering the electrically or hydraulically operated platform located at the rear of the van, if neither the platform nor anything on the platform rises above the roof of the van

untrained person, for an electrical part, means a person who is not an authorised person or an instructed person for the electrical part.

work means work of any type, whether or not electrical work, other than live work or electrical welding performed in accordance with a safe system of work.

60 Meaning of ***direct contact***

- (1) A person is in ***direct contact*** with an electrical part if—
 - (a) the person is touching the electrical part with the person's bare hands or another bare part of the person's body; or
 - (b) the person is touching a conductive object with the person's bare hands or another bare part of the person's body, and the conductive object is touching the electrical part; or
 - (c) an article of clothing worn by the person is touching the electrical part; or
 - (d) an article of clothing worn by the person is touching a conductive object, and the conductive object is touching the electrical part.
- (2) Operating plant is in ***direct contact*** with an electrical part if—
 - (a) any part of the operating plant is touching the electrical part; or
 - (b) anything the operating plant is handling is touching the electrical part.

- (3) A vehicle is in ***direct contact*** with an electrical part if—
 - (a) any part of the vehicle is touching the electrical part; or
 - (b) anything being carried or otherwise handled by the vehicle is touching the electrical part.

61 Meaning of *exclusion zone*

- (1) The ***exclusion zone***, for a person for an electrical part, or for operating plant or a vehicle for an electrical part, means the distance from the part stated for the person, plant or vehicle in schedule 2.
- (2) For applying schedule 2 to a person, the person includes any article of clothing worn by the person, and any conductive object the person is handling.
- (3) For applying schedule 2 to operating plant, the operating plant includes anything the operating plant is handling other than—
 - (a) a person; or
 - (b) a hand-held object the person is handling.
- (4) For applying schedule 2 to a vehicle, the vehicle includes anything the vehicle is carrying or otherwise handling.
- (4A) Despite subsections (2) to (4), the person, operating plant or vehicle does not include an object, for example, a tool, that alone or with another object or objects is an extension from the person, operating plant or vehicle if the object—
 - (a) is an insulated device; and
 - (b) the device has been tested and found to be safe for use on and near the electrical part.
- (5) For applying schedule 2 to operating plant operated by an authorised person or instructed person who does not have a safety observer or another safe system as required under the schedule, the authorised person or instructed person must be taken to be an untrained person.
- (6) However, the exclusion zone, for an electrical part, for operating plant operated by an authorised person or instructed person for the electrical part, is taken to be the same as the

exclusion zone for an authorised person or instructed person for the electrical part if—

- (a) the operating plant is fitted with a device capable of stopping the operation of the operating plant immediately the operating plant is at the exclusion zone for an authorised person or instructed person for the electrical part; and
 - (b) there is in place a safe system of work for the use of the operating plant; and
 - (c) the safe system of work has been developed in consultation with persons who are broadly representative of industrial organisations of employees whose members commonly operate operating plant of the operating plant's type; and
 - (d) without limiting paragraph (b), the safe system of work ensures the device mentioned in paragraph (a)—
 - (i) is operating properly; and
 - (ii) is set for at least the correct exclusion zone distance.
- (7) A reference in schedule 2 to a vehicle does not include a reference to—
- (a) an aircraft; or
 - (b) a vehicle that is operating plant.

Examples for paragraph (b)—

- A tip truck tipping a load would not be a vehicle for schedule 2. However, a tip truck travelling between sites would be a vehicle for schedule 2
 - A vehicle that includes an elevated work platform being used for clearing vegetation would not be a vehicle for schedule 2. However, when the platform is not being used for clearing vegetation, the vehicle would be a vehicle for schedule 2.
- (8) For applying schedule 2 to operating plant, a reference to 'another safe system' is a reference to a system of work that—
- (a) has been developed in consultation with persons who are broadly representative of industrial organisations of

employees whose members commonly operate operating plant of the operating plant's type; and

- (b) provides, for persons and property, the same level of electrical safety as, or a greater level of electrical safety than, the level of electrical safety provided with a safety observer.

Division 2 Requirements for working around electrical parts and underground electrical services

62 Employer or self-employed person to ensure work is performed in accordance with requirements

- (1) An employer or self-employed person must ensure that work performed in the conduct of the person's business or undertaking does not involve, other than in accordance with the requirements of this division—
 - (a) a person coming into direct contact with an electrical part; or
 - (b) any operating plant or vehicle coming into direct contact with an electrical part; or
 - (c) a person coming within the exclusion zone for the person for an electrical part; or
 - (d) any operating plant or vehicle coming within the exclusion zone for the operating plant or vehicle for an electrical part; or
 - (e) a person coming into direct contact with an underground electrical service as a result of which—
 - (i) the service is damaged; and
 - (ii) live parts of the service are exposed; or
 - (f) any operating plant or vehicle coming into direct contact with an underground electrical service as a result of which—

- (i) the service is damaged; and
- (ii) live parts of the service are exposed.

Maximum penalty—40 penalty units.

- (2) Subsection (1)(a) and (c) does not apply to a person if—
 - (a) the person is an authorised person or instructed person for the electrical part; and
 - (b) the electrical part is a low voltage overhead insulated electric line.
- (3) Subsection (1)(b) and (d) does not apply to operating plant if—
 - (a) the operating plant is being operated by an authorised person or instructed person for the electrical part; and
 - (b) a safety observer is being used; and
 - (c) the electrical part is a low voltage overhead insulated electric line.

62A Principal contractor for construction workplace—excavating and underground electrical services

- (1) This section applies to the principal contractor for a construction workplace at which excavation work is to be done.
- (2) Before the work starts, the principal contractor must—
 - (a) find out from appropriate sources what underground electrical services are at or near the location where the work is to be done that could create a risk if contacted or damaged; and
 - (b) obtain prescribed information about each service from an appropriate source; and
 - (c) give the information to each employer or self-employed person who is to do excavation work at or near the location of the service; and
 - (d) ensure the information is recorded in writing.

Maximum penalty—40 penalty units.

- (3) The principal contractor must keep the information recorded until the work ends.

Maximum penalty—20 penalty units.

62C Employer or self-employed person at construction workplace—excavating and underground electrical services

- (1) This section applies if an employer or self-employed person intends to do excavation work at a construction workplace.
- (2) The employer or self-employed person must not start the work unless the principal contractor for the workplace has—
 - (a) advised the employer or self-employed person to the effect that the principal contractor's inquiries have shown that there are no underground electrical services at or near the location where the work is to be done; or
 - (b) given prescribed information about the underground electrical services at the workplace to the employer or self-employed person.
- (3) The employer or self-employed person must—
 - (a) ensure that information obtained under subsection (2) is considered in doing the work; and
 - (b) ensure that any reasonable restrictions contained in the information and to be followed in doing the work are followed in doing the work; and
 - (c) decide on and implement any control measures necessary to prevent a person's exposure to the risk of death, illness or injury from contact with, or damage to, the service the information is about.

62D Employer or self-employed person not at construction workplace—excavating and underground electrical services

- (1) An employer or self-employed person who intends to do excavation work other than at a construction workplace must, before the work starts—

- (a) find out from appropriate sources what underground electrical services are at or near the location where the work is to be done that could create a risk if contacted or damaged; and
 - (b) obtain prescribed information about each service from an appropriate source; and
 - (c) ensure that the information is considered in planning the work; and
 - (d) ensure that the information is recorded in writing.
- (2) The employer or self-employed person must—
- (a) ensure that information obtained under subsection (1) is considered in doing the work; and
 - (b) ensure that any reasonable restrictions contained in the information and to be followed in doing the work are followed in doing the work; and
 - (c) decide on and implement any control measures necessary to prevent a person's exposure to the risk of death, illness or injury from contact with, or damage to, the service the information is about; and
 - (d) keep the information recorded until the work ends.

63 Work involving direct contact with electrical part

- (1) Work may be performed involving a person coming into direct contact with an electrical part if the electrical part is—
- (a) isolated from all sources of electricity; and
 - (b) tested to ensure it is, or otherwise confirmed to be, isolated from all sources of electricity; and
 - (c) if the electrical part is a high voltage electrical part—earthed.
- (2) Subsection (1)(b) does not apply as a requirement if—
- (a) the electrical part can not be directly contacted to prove isolation from all sources of electricity; and
 - (b) there is in place an earthing switch that is able to control the operation of the electrical part and is designed to

operate safely if the electrical part has not been isolated from all sources of electricity; and

- (c) the work is being performed in the business or undertaking of an employer, and the employer has given written instructions to the person performing the work that, if complied with, will be effective to isolate the electrical part from all sources of electricity.

64 Work within exclusion zone for electrical part

- (1) Work may be performed involving a person, operating plant or a vehicle coming within the exclusion zone for the person, operating plant or vehicle for an electrical part, other than by coming into direct contact with the electrical part, if the electrical part is—
 - (a) isolated from all sources of electricity; and
 - (b) tested to ensure it is, or otherwise confirmed to be, isolated from all sources of electricity; and
 - (c) if the electrical part is a high voltage electrical part—earthed.
- (2) However, if it is not practicable for subsection (1)(b) to be complied with, the work may nevertheless be performed if—
 - (a) the work can be performed safely; and
 - (b) if the work is being performed in the business or undertaking of an employer—the employer has given written instructions, either generally or directed at the particular circumstances, about the work to be performed and the precautions to be complied with; and
 - (c) at least 1 of the following applies—
 - (i) suitable barriers or earthed metal shields are installed between the person, operating plant or vehicle and the electrical part;
 - (ii) the work is testing, and the electrical part, or an item of electrical equipment of which the electrical part is a component, is designed in a way requiring the work to be performed while the person, operating plant or vehicle is within the exclusion

- zone for the person, operating plant or vehicle for the electrical part;
- (iii) the work is earthing of the electrical part, or an item of electrical equipment of which the electrical part is a component, and is performed after the electrical part or item of electrical equipment has been isolated and proved to be de-energised.
- (3) Work may be performed involving operating plant coming within the exclusion zone for the operating plant for an electrical part, other than by coming into direct contact with the electrical part, if—
- (a) the operating plant is being used to work on an overhead electric line; and
 - (b) the use of the operating plant is under a documented safe system of work for use of the operating plant within the exclusion zone.

Division 3 Consultation with persons in control of electric lines

64A Requirement to consult

- (1) This section applies if—
- (a) work is to be performed in the conduct of the business or undertaking of an employer or self-employed person; and
 - (b) despite the requirements of section 62, there is a reasonable likelihood the performance of the work could involve—
 - (i) a person coming into direct contact with an overhead electric line; or
 - (ii) operating plant or a vehicle coming into direct contact with an overhead electric line; or
 - (iii) a person coming within the exclusion zone for the person for an overhead electric line; or

Electrical Safety Regulation 2002

- (iv) operating plant or a vehicle coming within the exclusion zone for the operating plant or vehicle for an overhead electric line.
- (2) The employer or self-employed person must give the person in control of the overhead electric line written notice of the employer or self-employed person's intention to perform the work.

Maximum penalty—40 penalty units.

- (3) The person in control of the overhead electric line must, within 7 days after receiving the written notice under subsection (2), give the employer or self-employed person a safety advice about the performance of the work.

Maximum penalty—40 penalty units.

- (4) The employer or self-employed person must not allow the work to be started before the employer or self-employed person has received the safety advice from the person in control of the overhead electric line, unless the employer or self-employed person has a reasonable excuse.

Maximum penalty—40 penalty units.

- (5) In this section—

safety advice, about the performance of work in the conduct of the business or undertaking of an employer or self-employed person, means a written notice advising how, as well as complying with this regulation, the employer or self-employed person can best ensure the electrical safety of persons and property in the performance of the work.

Examples of what might be included in a safety advice—

- advice recommending de-energising the overhead electric line while the work is being performed, and explaining how this can be arranged
- advice recommending relocating the overhead electric line or replacing the overhead electric line with an underground cable, and explaining how this can be arranged
- advice recommending erecting physical barriers to enclose the overhead electric line, and explaining how this can be arranged

Part 5 Electrical installations

Division 1 Performing electrical work

65 Purpose of div 1

To the extent that this division applies, or is capable of applying, to a person who is an employer or self-employed person, this division prescribes a way of discharging the electrical safety obligation of an employer or self-employed person to ensure that the person's business or undertaking is conducted in a way that is electrically safe.

66 Licensed electrical worker to comply with wiring rules

A licensed electrical worker who performs electrical work on an electrical installation must ensure that the electrical installation, to the extent it is affected by the electrical work, is in accordance with the wiring rules.

Maximum penalty—40 penalty units.

67 Employer to ensure electrical installation complies

An employer who employs a licensed electrical worker to perform electrical work on an electrical installation must ensure that the electrical installation, to the extent it is affected by the electrical work, is in accordance with—

- (a) if the electrical installation is to be used for construction work—the wiring rules and AS/NZ 3012 (Electrical installations—Construction and demolition sites); or
- (b) if the electrical installation is not to be used for construction work—the wiring rules.

Maximum penalty—40 penalty units.

67A Self-employed person to ensure electrical installation complies

A self-employed person who is a licensed electrical worker and who performs electrical work on an electrical installation must ensure that the electrical installation, to the extent it is affected by the electrical work, is in accordance with—

- (a) if the electrical installation is to be used for construction work—the wiring rules and AS/NZ 3012; or
- (b) if the electrical installation is not to be used for construction work—the wiring rules.

Maximum penalty—40 penalty units.

68 Work involving water equipment

- (1) A person must not perform work on water equipment unless—

- (a) the person is a licensed electrical worker; and
- (b) the work performed is work that the person would be authorised to perform on the water equipment under the person's electrical work licence if the water equipment were electrical equipment; and
- (c) the water equipment, to the extent it is affected by the work, is in accordance with the wiring rules.

Maximum penalty—40 penalty units.

- (2) An employer or self-employed person whose business or undertaking includes the performance of work on water equipment must ensure that, in the conduct of the business or undertaking, a person does not perform work in contravention of subsection (1).

Maximum penalty—40 penalty units.

- (3) In this section—

designated equipment means any apparatus, appliance, cable, conductor, fitting, insulator, material, meter or wire—

- (a) used for controlling, generating, supplying, transforming or transmitting electricity at extra low voltage; or

(b) operated by electricity at extra low voltage.

water equipment means designated equipment that is in, or that surrounds the water container of, a swimming pool, paddling pool, spa pool, water feature or water tub.

work, on water equipment, does not include—

- (a) the plugging in of a pre-packaged water feature; or
- (b) replacing a component forming part of the water equipment if the water equipment has been designed so that the component is readily and safely able to be replaced by a person without electrical knowledge or skill.

69 Work involving electric motor forming part of vehicle

- (1) A person must not perform work on an electric motor forming part of a vehicle unless—
 - (a) the person is a licensed electrical worker; and
 - (b) the work performed is work that the person would be authorised to perform on the electric motor under the person's electrical work licence if the electric motor were electrical equipment.

Maximum penalty—40 penalty units.

- (2) An employer or self-employed person whose business or undertaking includes the performance of work on an electric motor must ensure that, in the conduct of the business or undertaking, a person does not perform work in contravention of subsection (1).

Maximum penalty—40 penalty units.

- (3) In this section—

electric motor means an electric motor that is electrical equipment within the meaning of section 14(1)⁷ of the Act, but is not electrical equipment under the Act because of the operation of section 14(2) of the Act.

⁷ Section 14 (Meaning of *electrical equipment*) of the Act

vehicle does not include a car or motorbike under the *Transport Operations (Road Use Management) Act 1995*.

work, on an electric motor, means work on the electric motor that would be electrical work if the electric motor were electrical equipment.

Division 2 Defects and earthing

70 Requirement on person in control to fix defect

If an inspector or electricity entity gives written notice to the person in control of electrical equipment of any defect affecting the electrical safety of the electrical equipment, whether or not a serious defect, the person in control must take all reasonable steps to ensure the defect is fixed.

Maximum penalty—40 penalty units.

71 Earthing

- (1) This section applies if a low voltage electrical installation receives electricity distributed by an electricity entity.
- (2) The person in control of the low voltage electrical installation must not knowingly allow the earthing for the installation to be inconsistent with the earthing system requirements the electricity entity has under this regulation.

Maximum penalty for subsection (2)—40 penalty units.

Division 3 Electric lines

72 Service line

- (1) This section applies if an electrical installation receives electricity distributed by an electricity entity.
- (2) The person in control of the electrical installation must maintain the person in control's facilities for—
 - (a) attaching an overhead service line to supply electricity to the electrical installation; or

- (b) the entrance, support, protection and termination of an underground service line to supply electricity to the electrical installation.

Maximum penalty—40 penalty units.

Examples of facilities that may be provided by a person in control—

- a service riser bracket
 - timber backing for the electricity entity's 'J' hook
- (3) However, subsection (2) does not require the person in control of the electrical installation to maintain the insulation of any clamp or apparatus supplied by the person in control for the purposes of any joint needed for consumer terminals.
- (4) The electricity entity must at periodic reasonable intervals inspect and maintain the insulation of the clamp or apparatus mentioned in subsection (3).

Maximum penalty for subsection (4)—40 penalty units.

73 Structure supporting electric line or equipment to comply with wiring rules

- (1) The person in control of an electrical installation must ensure that any structure supporting an electric line or item of electrical equipment forming part of the electrical installation is in accordance with the requirements of—
- (a) the wiring rules; and
 - (b) any direction the chief executive gives for ensuring electrical safety.

Maximum penalty—40 penalty units.

- (2) If there is a conflict between the wiring rules and a direction of the chief executive, the direction prevails.

74 Obligation to preserve insulation of electric line

The person in control of an electrical installation must maintain, to a reasonable extent, the integrity of the insulation of any electric line, or connection to an electric line, that is part of the electrical installation—

- (a) if it is an overhead electric line—near the point of attachment of the electric line to any structure; and
- (b) whether or not it is an overhead electric line—near roofs or structures where it is likely that persons, including, for example, painters and plumbers, could come into contact with the insulated wires or connectors of the line.

Maximum penalty—40 penalty units.

75 Trimming of trees near overhead electric line

- (1) The person in control of an overhead electric line must ensure that trees and other vegetation are trimmed, and other measures taken, to prevent contact with the line that is likely to cause injury from electric shock to any person or damage to property.

Maximum penalty—40 penalty units.

- (2) In this section—

overhead electric line does not include an overhead electric line owned by an electricity entity.

76 Obligation to ensure safety of disconnected overhead electric line

- (1) The person in control of an overhead electric line must take all reasonable steps to ensure that, if the line is disconnected from its electricity supply, the line is—
 - (a) dismantled as soon as practicable after disconnection; or
 - (b) maintained so it is electrically and mechanically safe.

Maximum penalty—40 penalty units.

- (2) In this section—

overhead electric line does not include an overhead electric line owned by an electricity entity.

Division 4 Installation of approved safety switches in domestic residences

77 Definitions for div 4

In this division—

approved safety switch means a residual current device that—

- (a) has a Queensland or external approval; and
- (b) has a rated residual current of not more than 30mA.

chief executive (land) means the chief executive of the department in which the *Land Act 1994* is administered.

combined form means a form that—

- (a) gives transfer and safety switch information and information about a change of ownership required under other Acts; and
- (b) may be given to the chief executive (land) or the registrar.

date of possession, for residential land, means the date the transferee of the land enters into lawful possession of the land.

domestic residence means a building or structure, or a part of a building or structure, that—

- (a) is used, or designed to be used, as a single dwelling; and

Examples for paragraph (a)—

- dwelling house
- flat

- (b) is not used, or designed to be used, for temporary accommodation.

Examples of temporary accommodation for paragraph (b)—

- boarding house
- motel

general purpose socket-outlet means a low voltage socket-outlet that—

- (a) has a rating of 10A; and

- (b) is designed to fit a three-pin flat-pin plug that complies with the relevant standard under part 6 for the type of plug; and
- (c) is used, or intended to be used, or could at some time reasonably be expected to be used, for more than 1 appliance.

registrar see the *Land Title Act 1994*, schedule 2.

residential land means land on which a domestic residence is constructed, and includes an interest in residential land.

transfer and safety switch information see section 79.

transfer date, for residential land, means the date the transferee of the land is entitled to lawful possession of the land.

transferee, of residential land, means the person who, on becoming entitled to possession of the land, may lodge an application for registration—

- (a) under the *Land Act 1994*, as a lessee, or personal representative of a deceased lessee, of the land; or
- (b) under the *Land Title Act 1994*, as an owner, or the personal representative of an owner, of the land.

transferor, of residential land, means—

- (a) if, immediately before the transfer date for the residential land, a mortgagee in possession under the *Property Law Act 1974* is in lawful possession of the land—the mortgagee in possession; or
- (b) otherwise—the person registered, immediately before the transfer date for the land—
 - (i) under the *Land Act 1994*, as a lessee, or personal representative of a deceased lessee, of the land; or
 - (ii) under the *Land Title Act 1994*, as an owner, or the personal representative of an owner, of the land.

78 Notice to transferee about approved safety switch

- (1) The transferor of residential land must, on or before the date of possession for the land, give the transferee of the land

written notice of whether an approved safety switch has been installed for the general purpose socket-outlets installed in the domestic residence on the land.

Maximum penalty—15 penalty units.

- (2) However, subsection (1) does not apply if—
 - (a) the transferor became transferor of the residential land under an agreement to transfer the land; and
 - (b) the date of the agreement is before 1 September 2002.
- (3) The transferor must not state anything in the notice that the transferor knows is false or misleading in a material particular.

Maximum penalty for subsection (3)—15 penalty units.

79 Notice to chief executive about approved safety switch and other matters

- (1) The transferor of residential land must, within 90 days after the date of possession for the land, give the chief executive a written notice stating the following information (*transfer and safety switch information*)—
 - (a) the full names of the transferor and transferee;
 - (b) the addresses of the transferor and transferee immediately after the date of possession for the land;
 - (c) the property details of the land;
 - (d) the current use of the land;
 - (e) if there is an agreement for the transfer of the land—the date of the agreement;
 - (f) the date of possession for the land;
 - (g) whether an approved safety switch has been installed for the general purpose socket-outlets installed in the domestic residence on the land;
 - (h) whether the transferor has given the transferee written notice of whether an approved safety switch has been installed for the general purpose socket-outlets installed in the domestic residence on the land.

Maximum penalty—15 penalty units.

- (2) However, subsection (1) does not apply if—
 - (a) the transferor became transferor of the residential land under an agreement to transfer the land; and
 - (b) the date of the agreement is before 1 September 2002.
- (3) Also, the transferor is not required to comply with subsection (1) if a properly completed combined form, together with an application for registration is given to—
 - (a) for an application for registration under the *Land Act 1994*—the chief executive (land); or
 - (b) for an application for registration under the *Land Title Act 1994*—the registrar.
- (4) If a combined form is given under subsection (3), the chief executive may use only the transfer and safety switch information on the form.

80 Installation of approved safety switch in particular residences

- (1) This section applies if—
 - (a) the date of possession for residential land is on or after 1 September 2002; and
 - (b) a general purpose socket-outlet was installed in the domestic residence on the land before 1 June 1992; and
 - (c) an approved safety switch has not been installed for the general purpose socket-outlet.
- (2) The owner of the land must, within 3 months after the date of possession, have an approved safety switch installed for the general purpose socket-outlet.

Maximum penalty—15 penalty units.

- (3) In this section—

owner, of residential land, means the person registered or entitled to be registered, immediately after the transfer date for the land—

 - (a) under the *Land Act 1994*, as a lessee, or personal representative of a deceased lessee, of the land; or

- (b) under the *Land Title Act 1994*, as an owner, or the personal representative of an owner, of the land.

80A Installation of approved safety switch if residential tenancy agreement entered into or to be entered into

- (1) Subsection (2) applies if—
 - (a) the owner of residential land to which a residential tenancy agreement entered into before 1 March 2006 relates is aware of the residential tenancy agreement; and
 - (b) a general purpose socket-outlet was installed in the domestic residence on the residential land before 1 June 1992; and
 - (c) an approved safety switch is not installed for the general purpose socket-outlet.
- (2) The owner of the residential land must ensure an approved safety switch is installed for the general purpose socket-outlet by the end of 29 February 2008.

Maximum penalty—15 penalty units.

- (3) Subsection (4) applies if—
 - (a) a residential tenancy agreement is entered into for residential land after 28 February 2006 and before 1 March 2008; and
 - (b) the owner of the residential land is aware of the residential tenancy agreement; and
 - (c) a general purpose socket-outlet was installed in the domestic residence on the residential land before 1 June 1992; and
 - (d) when the residential tenancy agreement is entered into an approved safety switch is not installed for the general purpose socket-outlet.
- (4) The owner of the residential land must ensure an approved safety switch is installed for the general purpose socket-outlet by the earlier of the following—
 - (a) 6 months after the agreement was entered into;

Electrical Safety Regulation 2002

(b) the end of 29 February 2008.

Maximum penalty—15 penalty units.

(5) Subsection (6) applies if—

(a) a residential tenancy agreement for residential land is proposed to be entered into on or after 1 March 2008; and

(b) the owner of the residential land is aware of the proposed residential tenancy agreement or that the proposed residential agreement has been entered into; and

(c) a general purpose socket-outlet was installed in the domestic residence on the residential land before 1 June 1992; and

(d) an approved safety switch is not installed for the general purpose socket-outlet.

(6) The owner of the residential land must ensure an approved safety switch is installed for the general purpose socket-outlet as soon as practicable after becoming aware of the proposed residential tenancy agreement or that the proposed residential agreement has been entered into.

Maximum penalty—15 penalty units.

(7) In this section—

owner, of residential land, means the person registered or entitled to be registered, immediately after the transfer date for the land—

(a) under the *Land Act 1994*, as a lessee, or personal representative of a deceased lessee, of the land; or

(b) under the *Land Title Act 1994*, as an owner, or the personal representative of an owner, of the land.

residential tenancy agreement has the meaning given by the *Residential Tenancies Act 1994*.

81 Performing electrical installation work for domestic residences

A licensed electrical worker or a licensed electrical contractor must not perform electrical installation work on an electrical installation installed in a domestic residence unless—

- (a) an approved safety switch has been installed for the general purpose socket-outlets installed in the residence; or
- (b) if an approved safety switch has not been installed for the general purpose socket-outlets installed in the residence—
 - (i) the work is or includes the installation of an approved safety switch for the general purpose socket-outlets installed in the residence; or
 - (ii) the worker reasonably believes installation of an approved safety switch for the general purpose socket-outlets installed in the residence is not required under this regulation; or
 - (iii) the work is the connection of the residence to a source of electricity; or
 - (iv) the work is needed to be performed without delay in an emergency, to prevent an emergency from happening or for safety reasons.

Maximum penalty—40 penalty units.

Division 5 Workplace electrical installations**Subdivision 1 Preliminary****82 Purpose of div 5**

This division prescribes a way of discharging the electrical safety obligation of an employer or self-employed person to ensure that the person's business or undertaking is conducted in a way that is electrically safe.

83 Definitions for div 5

In this division—

amusement device means an amusement device as defined in AS 3533.3.⁸

amusement ride means an amusement ride as defined in AS 3533.3.

amusement work means work, other than work performed by a non-profit organisation, to assemble, operate or disassemble any of the following on the site on which it is used, intended to be used or has been used—

- (a) an amusement device or amusement ride;
- (b) a thing used to provide amusement activities, including side show activities, associated with—
 - (i) carnivals, fairs or shows; or
 - (ii) amusement arcades or similar places;

Example of side show activities—

providing hamburgers, fairy floss or massages in a side show

- (c) a thing used to provide entertainment or advertising activities, in temporary sites, associated with shows, fairs or carnivals.

construction wiring, for a workplace, means temporary electrical wiring by which electricity is supplied by an electricity entity for use in, and for the period of, construction work, within the meaning of the WHS Act, section 14, at the place.

construction work means—

- (a) construction work within the meaning of the WHS Act, section 14, other than amusement work or rural industry work; or
- (b) work done in conjunction with construction work mentioned in paragraph (a).

8 AS 3533 (Amusement rides and devices), part 3 (In-service inspection)

Electrical Safety Regulation 2002

Example of paragraph (b)—

installation of plumbing in a house under construction

cord extension set means an assembly of—

- (a) a plug intended for connection to a socket outlet; and
- (b) a sheathed flexible cord; and
- (c) a cord extension socket.

manufacturing work means the work of assembly, disassembly, fabrication, installation, maintenance, manufacturing, refurbishment or repair, but does not include amusement work, construction work or rural industry work.

Examples—

- installing the interior fittings of a shop
- manufacturing clothes
- repairing leaking pipes

non-profit organisation means an organisation that is not carried on for the profit or gain of its individual members.

Example of entities that may be non-profit organisations—

charities, churches, clubs, environment protection societies

prescribed details, in relation to a tag to be attached to equipment, or a written record to be made in relation to equipment, after it is inspected and tested or reinspected and retested, means the following—

- (a) for all equipment—
 - (i) the date of the testing or retesting; or
 - (ii) the day by which the equipment must be reinspected and retested;
- (b) if the individual who performed the test or retest of the equipment is employed or engaged by a corporation, any of the following—
 - (i) the name of the individual;
 - (ii) the individual's electrical contractor licence number;
 - (iii) the name of the corporation;

Electrical Safety Regulation 2002

- (iv) the corporation's electrical contractor licence number;
- (c) if the individual who performed the test or retest of the equipment is not employed or engaged by a corporation, any of the following—
 - (i) the name of the individual;
 - (ii) the individual's electrical contractor licence number;
 - (iii) the electrical contractor licence number of the individual's employer;
 - (iv) the individual's electrical worker licence number.

rural industry work see section 83A.

safety switch means a type 1 safety switch or a type 2 safety switch.

service work means work that is not amusement work, construction work, manufacturing work, office work or rural industry work.

Examples—

- cleaning a motel
- cooking in a restaurant
- providing health services at a health facility
- selling goods from a shop
- teaching at an education facility
- caring for children at a child care centre

specified electrical equipment means—

- (a) for the performance of amusement work, manufacturing work or rural industry work, the following equipment (other than an amusement device or amusement ride)—
 - (i) a cord extension set with a current rating of not more than 20 amps;
 - (ii) a portable outlet device with a current rating of not more than 20 amps;
 - (iii) electrical equipment, other than a portable safety switch, that—

Electrical Safety Regulation 2002

- (A) has a current rating of not more than 20 amps; and
 - (B) is connected by a flexible cord and plug to low voltage supply; and
- (b) for the performance of office work or service work—
- (i) a cord extension set with a current rating of not more than 20 amps; or
 - (ii) a portable outlet device with a current rating of not more than 20 amps; or
 - (iii) electrical equipment, other than a portable safety switch, that—
 - (A) has a current rating of not more than 20 amps; and
 - (B) is connected by a flexible cord and plug to low voltage supply; and
 - (C) is moved during its normal use for the purpose of its use.

type 1 safety switch means a residual current device, whether or not portable, with a rated residual current of not more than 10mA.

type 2 safety switch means a residual current device, whether or not portable, with a rated residual current of more than 10mA but not more than 30mA.

83A Meaning of *rural industry work*

- (1) ***Rural industry work*** is work—
- (a) in the cultivation of any agricultural crop or product whether or not grown for food; or
 - (b) in the rearing and management of farm animals, for example, livestock, bees or worms; or
 - (c) in the classing, scouring, sorting or pressing of wool; or
 - (d) that is aquaculture; or
 - (e) in flower or vegetable market gardens; or

- (f) at clearing, fencing, trenching, draining or otherwise preparing land for anything stated in paragraph (a), (b), (d) or (e).
- (2) **Rural industry work** includes work that is construction work, manufacturing work or office work performed for the purposes of an activity mentioned in subsection (1) if the work is—
- (a) performed by an employer or self-employed person, including by his or her employee, carrying on the business or undertaking in which the product of the construction work, manufacturing work or office work is to be used; and
- (b) performed on premises on which the product of the construction work, manufacturing work or office work is to be used.

Examples of construction work or manufacturing work for subsection (2)—

- repairing farm machinery, for example, tractors or implements
 - making farm machinery, for example, cattle crushes, spray booms or fruit picking booms
 - building sheds
- (3) **Rural industry work** does not include work to which rural industry work is only incidental.

Examples—

- work in carrying on a farm stay
- work in conducting a tour associated with rural industry work

Subdivision 2 All work

84 Application of sdiv 2

This subdivision applies to an employer or self-employed person if the employer or a worker of the employer, or the self-employed person, performs work, whether or not electrical work, at a workplace.

85 Cord extension sets and flexible cables

- (1) An employer or self-employed person must ensure that any cord extension set or flexible cable at the workplace is—
 - (a) located where it is not likely to suffer damage; or
 - (b) protected against damage.
- (2) In this section—

damage includes damage by liquid.

Subdivision 3 Construction work**86 Application of sdiv 3**

This subdivision applies to the performance of construction work at a workplace.

87 Requirements for construction wiring and electrical equipment

- (1) An employer or self-employed person must ensure that all electrical equipment for the performance of work is in accordance with the requirements of AS/NZS 3012 (Electrical installations—Construction and demolition sites).
- (2) However, the requirement under AS/NZS 3012, clause 3.8.3⁹ that the tag must include the name of the person or company who performed the test does not apply.
- (3) An employer or self-employed person must ensure that, for the purposes of the business or undertaking, electrical equipment mentioned in AS/NZS 3012, clause 3.1¹⁰ is not fitted with a tag that includes the test or retest date for the equipment unless—
 - (a) the equipment is new; or

⁹ AS/NZS 3012 (Electrical installations—Construction and demolition sites), clause 3.8.3 (Compliant equipment)

¹⁰ AS/NZS 3012 (Electrical installations—Construction and demolition sites), clause 3.1 (Application)

- (b) both of the following apply—
 - (i) the equipment has been inspected and tested under that clause by a competent person and found to comply with the requirements of AS/NZS 3012;
 - (ii) the tag includes the day by which the equipment must be reinspected and retested and the information mentioned in subsection (4).
- (4) For subsection (3)(b)(ii)—
 - (a) if the individual who performed the test or retest is employed or engaged by a corporation—the information is any of the following—
 - (i) the name of the individual;
 - (ii) the individual's electrical contractor licence number;
 - (iii) the name of the corporation;
 - (iv) the corporation's electrical contractor licence number; or
 - (b) if paragraph (a) does not apply—the information is any of the following—
 - (i) the name of the individual;
 - (ii) the individual's electrical contractor licence number;
 - (iii) the electrical contractor licence number of the individual's employer;
 - (iv) the individual's electrical worker licence number.
- (5) An employer or self-employed person whose business or undertaking is being conducted at a construction workplace and who is the principal contractor for the construction workplace must ensure that all construction wiring at the workplace is in accordance with the requirements of AS/NZS 3012 (Electrical installations—Construction and demolition sites).

(6) In this section—

competent person see AS/NZS 3012, clause 1.4.7.¹¹

Subdivision 4 Manufacturing work

88 Application of sdiv 4

This subdivision applies to the performance of manufacturing work at a workplace.

89 Double adaptors and piggyback plugs prohibited

- (1) An employer or self-employed person must not use a double adaptor or piggyback plug.
- (2) An employer must ensure the employer's workers do not use a double adaptor or piggyback plug.

90 Specified electrical equipment

- (1) An employer or self-employed person must ensure that specified electrical equipment of the employer or self-employed person at the workplace is not used to perform work unless—
 - (a) it is inspected and tested by a competent person—
 - (i) if the equipment is double insulated—at least once every year; or
 - (ii) if the equipment is not double insulated—at least once every 6 months; and
 - (b) either—
 - (i) if the specified electrical equipment is connected to a socket-outlet that is in a permanent workplace under the control of the employer or self-employed person—

¹¹ AS/NZS 3012 (Electrical installations—Construction and demolition sites), clause 1.4.7 (Competent person)

Electrical Safety Regulation 2002

- (A) until the end of 29 February 2008—the specified electrical equipment is connected to a type 1 safety switch or type 2 safety switch; or
 - (B) on or after 1 March 2008—the specified electrical equipment is connected to a socket-outlet for which a type 1 safety switch, or type 2 safety switch, that is not portable, is installed; or
- (ii) if the specified electrical equipment is connected to a socket-outlet that is not in a permanent workplace under the control of the employer or self-employed person—the specified electrical equipment is connected to a type 1 safety switch or type 2 safety switch.

Example of a workplace that is not under the control of the employer or self-employed person—

the premises of a customer of the employer or self-employed person visited by a service technician of the employer or self-employed person

Examples of specified electrical equipment used to perform manufacturing work—

- a hand held grinder plugged into a socket-outlet
- a hand held electric drill plugged into a socket-outlet that is used for drilling holes in steelwork in a light engineering workshop

(1A) However—

- (a) subsection (1)(b)(i)(B) does not apply if the employer or self-employed person is exempted under section 90B; and
 - (b) subsection (1)(b)(i) and (ii) do not apply to a socket-outlet that is—
 - (i) more than 2.3m above the floor; and
 - (ii) provided for the purpose of supplying electricity to a luminaire or to electrical equipment with a power rating of not more than 150W.
- (2) If after inspecting and testing the electrical equipment under subsection (1)(a), a competent person decides the equipment is safe to use, the employer or self-employed person must

ensure the competent person immediately attaches a durable tag to the equipment that shows the prescribed details.

- (3) If after inspecting and testing the electrical equipment under subsection (1)(a), a competent person decides the equipment is not safe to use, the employer or self-employed person must ensure—
 - (a) the competent person immediately attaches a durable tag to the equipment that warns people not to use the equipment; and
 - (b) the equipment is immediately withdrawn from use.
- (4) An employer or self-employed person must ensure that, for the purposes of the business or undertaking, a tag is not attached to specified electrical equipment under subsection (2) unless—
 - (a) the equipment is new; or
 - (b) both of the following apply—
 - (i) the equipment has been inspected and tested by a competent person;
 - (ii) the tag was attached by the competent person.

90A Manufacturing work—safety switch

- (1) This section applies if—
 - (a) manufacturing work is the primary work performed at the workplace; and
 - (b) a socket-outlet with a current rating of not more than 20 amps is installed and supplies electricity to the workplace; and
 - (c) the socket-outlet is—
 - (i) not more than 2.3m above the floor; and
 - (ii) not provided for the purpose of supplying electricity to a luminaire or to electrical equipment with a power rating of not more than 150W.
- (2) Subsection (3) applies if the manufacturing work is performed before 1 March 2008.

- (3) The employer or self-employed person must have a type 1 safety switch, or type 2 safety switch, that is not portable, installed for the socket-outlet before 1 March 2008.

Maximum penalty—15 penalty units.

- (4) Subsection (5) applies if the manufacturing work is to be performed on or after 1 March 2008.

- (5) Before performing the manufacturing work, the employer or self-employed person must have a type 1 safety switch, or type 2 safety switch, that is not portable, installed for the socket-outlet.

Maximum penalty—15 penalty units.

- (6) Subsection (3) or (5) does not apply if the employer or self-employed person is exempted under section 90B.

90B Exemption for safety switches

An employer or self-employed person is exempt from complying with section 90(1)(b)(i)(B) or 90A(3) or (5) if—

- (a) the employer or self-employed person is not the person in control of the electrical equipment to which the safety switch is to be installed to comply with the section; and
- (b) the employer or self-employed person has been unable to obtain permission from the person in control of the electrical equipment for the installation of the safety switch; and
- (c) for an exemption from complying with section 90(1)(b)(i)(B)—the specified electrical equipment is connected to a type 1 safety switch or type 2 safety switch.

91 Safety switches, including portable safety switches

- (1) An employer or self-employed person must not use, or allow to be used, a safety switch unless it complies with AS/NZS 3760 (In-service safety inspection and testing of electrical equipment) when tested.

- (2) An employer or self-employed person must ensure that each safety switch, other than a portable safety switch, the employer or self-employed person has at the workplace—
 - (a) is tested by a competent person in accordance with AS/NZS 3760 immediately after it is connected; and
 - (b) is tested in accordance with, and at the intervals stated in, AS/NZS 3760.
- (3) An employer or self-employed person must ensure that each portable safety switch the employer or self-employed person has at the workplace—
 - (a) is tested by pushing the test button on the safety switch immediately after it is connected; and
 - (b) is tested in accordance with, and at the intervals stated in, AS/NZS 3760.
- (4) If a safety switch is not working properly, the employer or self-employed person must ensure—
 - (a) a durable tag is immediately attached to the safety switch that warns people not to use the safety switch; and
 - (b) the safety switch is immediately withdrawn from use.

Subdivision 5 Service work or office work

92 Application of sdiv 5

This subdivision applies to the performance of service work or office work at a workplace.

93 Specified electrical equipment

- (1) An employer or self-employed person must ensure that specified electrical equipment of the employer or self-employed person at the workplace is not used to perform work unless—
 - (a) it is inspected and tested by a competent person—

Electrical Safety Regulation 2002

- (i) if the equipment is used only for office work—at least once every 5 years; or
- (ii) otherwise—at least once every year; or
- (b) it is connected to a type 1 safety switch or a type 2 safety switch.

Examples of specified electrical equipment used to perform service work—

- a portable vacuum cleaner used in a hotel
- a hand held blow dryer used in a hairdressing salon

Example of specified electrical equipment used to perform office work—

a powerboard or extension lead used to supply power to office equipment

- (2) If after inspecting and testing the electrical equipment under subsection (1)(a), a competent person decides the equipment is safe to use, the employer or self-employed person must ensure the competent person immediately attaches a durable tag to the equipment that shows the prescribed details.
- (3) If after inspecting and testing the electrical equipment under subsection (1)(a), a competent person decides the equipment is not safe to use, the employer or self-employed person must ensure—
 - (a) the competent person immediately attaches a durable tag to the equipment that warns people not to use the equipment; and
 - (b) the equipment is immediately withdrawn from use.
- (4) An employer or self-employed person must ensure that, for the purposes of the business or undertaking, a tag is not attached to specified electrical equipment under subsection (2) unless—
 - (a) the equipment is new; or
 - (b) both of the following apply—
 - (i) the equipment has been inspected and tested by a competent person;
 - (ii) the tag was attached by the competent person.

94 Safety switches, including portable safety switches

- (1) An employer or self-employed person must not use, or allow to be used, a safety switch unless it complies with AS/NZS 3760 (In-service safety inspection and testing of electrical equipment) when tested.
- (2) An employer or self-employed person must ensure that each safety switch, other than a portable safety switch, the employer or self-employed person has at the workplace—
 - (a) is tested by a competent person in accordance with AS/NZS 3760 immediately after it is connected; and
 - (b) is tested in accordance with, and at the intervals stated in, AS/NZS 3760.
- (3) An employer or self-employed person must ensure that each portable safety switch the employer or self-employed person has at the workplace—
 - (a) is tested by pushing the test button on the safety switch immediately after it is connected; and
 - (b) is tested in accordance with, and at the intervals stated in, AS/NZS 3760.
- (4) If a safety switch is not working properly, the employer or self-employed person must ensure—
 - (a) a durable tag is immediately attached to the safety switch that warns people not to use the safety switch; and
 - (b) the safety switch is immediately withdrawn from use.

Subdivision 6 Amusement work**94A Application of sdiv 6**

This subdivision applies to the performance of amusement work at a workplace.

94B Double adaptors and piggyback plugs prohibited

- (1) An employer or self-employed person must not use a double adaptor or piggyback plug.
- (2) An employer must ensure the employer's workers do not use a double adaptor or piggyback plug.

94C Specified electrical equipment

- (1) An employer or self-employed person must ensure that specified electrical equipment of the employer or self-employed person at the workplace is not used to perform work unless—
 - (a) it is inspected and tested by a competent person—
 - (i) if the equipment is double insulated—at least once every year; or
 - (ii) if the equipment is not double insulated—at least once every 6 months; and
 - (b) it is connected to a type 1 safety switch or type 2 safety switch.
- (2) If after inspecting and testing the electrical equipment under subsection (1)(a) a competent person decides the equipment is safe to use, the employer or self-employed person must ensure the competent person immediately attaches a durable tag to the equipment that shows the prescribed details
- (3) If after inspecting and testing the electrical equipment under subsection (1)(a) a competent person decides the equipment is not safe to use, the employer or self-employed person must ensure—
 - (a) the competent person immediately attaches a durable tag to the equipment that warns people not to use the equipment; and
 - (b) the equipment is immediately withdrawn from use.
- (4) An employer or self-employed person must ensure that, for the purposes of the business or undertaking, a tag is not attached to specified electrical equipment under subsection (2) unless—

- (a) the equipment is new; or
- (b) both of the following apply—
 - (i) the equipment has been inspected and tested by a competent person;
 - (ii) the tag was attached by the competent person.

94D Amusement devices and amusement rides

- (1) An employer or self-employed person must ensure that all or part of an amusement device or amusement ride that is electrical equipment connected to the electricity supply by a plug, of the employer or self-employed person at the workplace is not used to perform work unless—
 - (a) it is inspected and tested by a competent person—
 - (i) each time it is assembled on the site where it is intended to be used; and
 - (ii) in any event at least once every 6 months; and
 - (b) for a device or ride with a current rating of not more than 20 amps—it is connected to a type 1 safety switch or type 2 safety switch.
- (2) An inspection and test under subsection (1)(a) must include the competent person—
 - (a) deciding the safety of earthing, insulation and connections; and
 - (b) deciding whether any safety switch complies with AS/NZS 3760 when tested; and
 - (c) making a visual examination to decide the safety of the items of electrical equipment of the device or ride, including cabling, plugs, sockets, light fittings, enclosures and motors.
- (3) If after inspecting and testing the electrical equipment under subsection (1)(a) a competent person decides the equipment is safe to use, the employer or self-employed person must ensure the competent person immediately makes a written record of—

- (a) details of the test; and
 - (b) the prescribed details.
- (4) If after inspecting and testing the electrical equipment under subsection (1)(a) a competent person decides the equipment is not safe to use, the employer or self-employed person must ensure—
- (a) the competent person immediately—
 - (i) attaches a durable, conspicuous sign to the equipment that warns people not to use the equipment; and
 - (ii) makes a written record of details of the test; and
 - (b) the equipment is immediately withdrawn from use.
- (5) An employer or self-employed person must ensure that a written record is not made, with the authority of the employer or self-employed person, of the day by which the equipment must be reinspected and retested unless the equipment has been inspected and tested by a competent person.

94E Safety switches, including portable safety switches

- (1) An employer or self-employed person must not use, or allow to be used, a safety switch unless it complies with AS/NZS 3760 when tested.
- (2) An employer or self-employed person must ensure that each safety switch, other than a portable safety switch, the employer or self-employed person has at the workplace—
 - (a) is tested by a competent person in accordance with AS/NZS 3760 immediately after it is connected; and
 - (b) is tested in accordance with, and at the intervals stated in, AS/NZS 3760.
- (3) An employer or self-employed person must ensure that each portable safety switch the employer or self-employed person has at the workplace—
 - (a) is tested by pushing the test button on the safety switch immediately after it is connected; and

- (b) is tested in accordance with, and at the intervals stated in, AS/NZS 3760.
- (4) If a safety switch is not working properly, the employer or self-employed person must ensure—
 - (a) a durable tag is immediately attached to the safety switch that warns people not to use the safety switch; and
 - (b) the safety switch is immediately withdrawn from use.

Subdivision 7 Rural industry work

94F Application of sdiv 7

This subdivision applies to the performance of rural industry work at a workplace.

94G Requirements for rural industry work

- (1) An employer or self-employed person must ensure that—
 - (a) specified electrical equipment used by the employer or self-employed person is visually inspected for electrical safety defects before it is connected to a socket-outlet; and
 - (b) if rural industry work is proposed to be performed, the proposed work is assessed to decide whether it involves a stated electrical risk factor; and
 - (c) if the proposed work involves a stated electrical risk factor, control measures are implemented to prevent the electrical risk from the stated electrical risk factor; and
 - (d) if specified electrical equipment is used by the employer or self-employed person that involves a stated electrical risk factor, the specified electrical equipment is—
 - (i) connected to a type 1 safety switch or type 2 safety switch; or
 - (ii) inspected and tested at least annually by a competent person and complies with AS/NZS 3760 when tested; and

Electrical Safety Regulation 2002

- (e) control measures are implemented for the risk of electric shock or burns from electrical welding work performed in the employer or self-employed person's business or undertaking, including the wearing of protective clothing, gloves and footwear.
- (2) If after inspecting and testing the electrical equipment under subsection (1)(d)(ii) a competent person decides the equipment is safe to use, the employer or self-employed person must ensure the competent person immediately attaches a durable tag to the equipment that shows the prescribed details.
 - (3) If after inspecting and testing the electrical equipment under subsection (1)(d)(ii) a competent person decides the equipment is not safe to use, the employer or self-employed person must ensure—
 - (a) the competent person immediately attaches a durable tag to the equipment that warns people not to use the equipment; and
 - (b) the equipment is immediately withdrawn from use.
 - (4) An employer or self-employed person must ensure that, for the purposes of the business or undertaking, a tag is not attached to specified electrical equipment under subsection (2) unless—
 - (a) the equipment is new; or
 - (b) both of the following apply—
 - (i) the equipment has been inspected and tested by a competent person;
 - (ii) the tag was attached by the competent person.
 - (5) In this section—

personally supported electrical equipment includes hand held, or carried, electrical equipment, for example, a back pack type vacuum cleaner.

stated electrical risk factor means any of the following—

 - (a) use of plug-in electrical equipment in an unroofed area or wet area, for example, a hose down area;

- (b) use of personally supported electrical equipment if the electrical supply cord is subject to flexing while the equipment is being used;
- (c) use of plug-in electrical equipment that is exposed to environmental factors that subject the equipment to abnormal wear or deterioration.

Example of environmental factors that subject equipment to abnormal wear or deterioration—

- corrosive or other damaging dusts, for example, metal dust
- corrosive chemicals in the air

Part 6 Electrical equipment

Division 1 Preliminary

95 Definitions for pt 6

In this part—

existing type see section 106.

external approval see section 99.

externally approved see section 99.

new type see section 106.

nonprescribed electrical equipment means electrical equipment of a type that is not a type of electrical equipment of a prescribed class.

prescribed class, of electrical equipment, see section 96.

Queensland approval see section 98.

Queensland approved see section 98.

relevant standard, for a type of electrical equipment of a prescribed class of electrical equipment, see section 97.

second-hand electrical equipment means electrical equipment that has previously been sold, other than by wholesale.

sell includes—

- (a) sell by wholesale, retail or auction; and
- (b) supply in trade or commerce or under an arrangement; and
- (c) agree, attempt or offer to sell; and
- (d) keep or expose for sale; and
- (e) cause or permit to be sold.

type, of electrical equipment of a prescribed class of electrical equipment, see section 96.

type approval certificate, for a type of electrical equipment, means a certificate issued by the chief executive evidencing the approval of the type of electrical equipment under this part.

type approval holder, for a type of electrical equipment, means the holder of a type approval certificate for the type of electrical equipment.

type approval number, for an approval of a type of electrical equipment, see section 102.

96 Meanings of *prescribed class* and *type*

- (1) Schedule 3 lists classes of electrical equipment.
- (2) Each class of electrical equipment listed is a *prescribed class* of electrical equipment.
- (3) A particular type of electrical equipment is a *type* of electrical equipment of a prescribed class of electrical equipment if the type matches the description given in the defining standard to the prescribed class.
- (4) In this section—

defining standard means AS/NZS 4417 (Marking of electrical products to indicate compliance with regulations), part 2 (Specific requirements for electrical safety regulatory applications).

97 Meaning of *relevant standard*

- (1) A standard is a *relevant standard* for a type of electrical equipment of a prescribed class of electrical equipment if—
 - (a) it is the standard shown in schedule 3 as the relevant standard for the prescribed class, and the standard can be readily applied to the type; or
 - (b) if the standard mentioned in paragraph (a) can not be readily applied to the type—it is a standard accepted by the chief executive as a standard that can be readily applied to the type; or
 - (c) if there is no standard under paragraph (a) that can be readily applied to the type, and there is no standard under paragraph (b) accepted by the chief executive as a standard that can be readily applied to the type—the standard identified by the chief executive as the standard to be applied to the type.
- (2) The acceptance of a standard under subsection (1)(b), or the identification of a standard under subsection (1)(c), has effect subject to compliance with any requirements stated by the chief executive as part of the chief executive's acceptance or identification of the standard.

98 Queensland approvals

- (1) A type of electrical equipment is *Queensland approved* if—
 - (a) it is a type of electrical equipment of a prescribed class of electrical equipment; and
 - (b) the type has been approved under this part.
- (2) An item of electrical equipment has a *Queensland approval* if the item is of a type of electrical equipment that is Queensland approved.

99 External approvals

- (1) A type of electrical equipment is *externally approved* if—
 - (a) it is a type of electrical equipment of a prescribed class of electrical equipment; and

- (b) the type has been registered, certified or otherwise approved by an external approvals entity to comply with standards required to permit the type of electrical equipment to be offered for sale in the entity's jurisdiction.
- (2) An item of electrical equipment has an *external approval* if the item is of a type of electrical equipment that is externally approved.

Division 2 Restriction on hire or sale of particular items of electrical equipment

100 Hire or sale of electrical equipment of prescribed class

- (1) A person must not hire or sell an item of electrical equipment of a type of electrical equipment of a prescribed class of electrical equipment unless—
 - (a) for a sale of an item—the item has a Queensland approval or an external approval; and
 - (b) the item is marked—
 - (i) for an item with a Queensland approval—as required under this part; or
 - (ii) for an item with an external approval—as required by law governing the marking of the item in the external approvals entity's jurisdiction; or
 - (iii) with a regulatory compliance mark; and
 - (c) the item is of a type of electrical equipment of a prescribed class of electrical equipment that complies with the safety requirements, electrical or otherwise, of the relevant standard for the type as in force when the Queensland approval or external approval was granted; and
 - (d) if the item has a Queensland approval that is currently extended under section 103A—the item was

manufactured before the application for the extension was made.

Maximum penalty—40 penalty units.

- (2) This section does not apply to the sale of second-hand electrical equipment.
- (3) In this section—

regulatory compliance mark means a compliance mark for an item of electrical equipment complying with AS/NZS 4417 (Marking of electrical products to indicate compliance with regulations) that is used to indicate that the item complies with this regulation.

Division 3 Queensland approvals of types of electrical equipment of prescribed classes

101 Application for approval of type of electrical equipment

- (1) A person may apply to the chief executive for approval of a type of electrical equipment of a prescribed class of electrical equipment.
- (2) The application for approval must—
 - (a) be made in the approved form; and
 - (b) be accompanied by—
 - (i) a test report issued by an approved testing entity stating—
 - (A) that an item of electrical equipment of the type the subject of the application has been tested and examined in accordance with the safety requirements, electrical or otherwise, of the relevant standard for the type as in force when the item was manufactured or the test report was issued; and
 - (B) the results of the test or examination; and
 - (ii) the fee for the application; and

- (iii) if required by the chief executive—an item of electrical equipment of the type the subject of the application; and
 - (iv) any other relevant information the chief executive requires about the construction, operation or safety of the type of electrical equipment.
- (3) The application must include a declaration by the applicant that an item of electrical equipment of the type the subject of the application has been tested and examined by an approved testing entity in accordance with the relevant standard for the type.

102 Approval of type of electrical equipment

- (1) The chief executive may approve the type of electrical equipment the subject of an application for approval if the type of electrical equipment complies with the safety requirements, electrical or otherwise, of the relevant standard for the type of electrical equipment as in force—
 - (a) when the item tested or examined under section 101 for the application was manufactured; or
 - (b) when the test report for the item was issued.
- (2) The chief executive must approve the type of electrical equipment by—
 - (a) issuing the applicant with a type approval certificate for the type of electrical equipment; and
 - (b) giving the type of electrical equipment an identification number (a *type approval number*); and
 - (c) giving the applicant written notice of any conditions of the approval.
- (2A) The approval may be on conditions.
- (2B) A type approval holder for a type of electrical equipment must comply with any conditions of the approval.

Maximum penalty—40 penalty unit.

- (3) If the chief executive refuses to approve the type of electrical equipment, the chief executive must give the applicant an information notice for the decision to refuse.

103 Term of approval

Unless it is cancelled earlier, the approval of a type of electrical equipment is for a period of up to 5 years, stated in the approval, or if no period is stated, 5 years.

103A Extension of term of approval by up to 1 year

- (1) A type approval holder for a type of electrical equipment may apply to the chief executive for an extension of the term of the approval for a period of up to 1 year stated in the application.
- (2) The application must—
 - (a) be in the approved form and accompanied by the fee for the application; and
 - (b) relate only to items manufactured before the application was made.
- (3) The chief executive may, by written notice, require the applicant to give the chief executive within a stated reasonable time the additional information the chief executive reasonably requires to consider the application.
- (4) If the applicant does not give the chief executive the additional information within the time stated in the notice, the application is taken to have been refused.
- (5) The chief executive may extend the term only if the chief executive is satisfied that, at the time the application is made, the type of electrical equipment—
 - (a) is for sale; and
 - (b) is not being manufactured.
- (6) The extension may be on conditions.
- (7) A person granted an extension of an approval under subsection (5) must comply with any conditions of the extension.

Maximum penalty—40 penalty units.

- (8) The chief executive must give the applicant written notice of the following within 3 months after the relevant date—
- (a) the grant or refusal of the extension;
 - (b) if the extension is granted—any conditions of the extension;
 - (c) if the extension is refused—an information notice for the decision to refuse.
- (9) If the chief executive does not give the notice within 3 months after the relevant date, the application is taken to have been refused.
- (10) If the approval will expire before the relevant date, the term of the approval is extended until whichever of the following happens first—
- (a) the chief executive gives the notice mentioned in subsection (8);
 - (b) the application is taken to have been refused under subsection (9).
- (11) In this section—
- relevant date*** means—
- (a) the date the chief executive receives an application for an extension of a type approval for a type of electrical equipment; or
 - (b) if the chief executive makes a request for additional information in relation to an application for an extension of a type approval for a type of electrical equipment—the date the chief executive makes the request.

103B Renewal of approval

- (1) A type approval holder whose approval for a type of electrical equipment has not been extended under section 103A may apply to the chief executive to renew the approval for a period of up to 5 years stated in the application.
- (2) The application must be in the approved form and accompanied by the fee for the application.

Electrical Safety Regulation 2002

- (3) The chief executive may, by written notice, require the applicant to give the chief executive within a stated reasonable time the additional information the chief executive reasonably requires to consider the application.
- (4) If the applicant does not give the chief executive the additional information within the time stated in the notice, the application is taken to have been refused.
- (5) The chief executive may renew the approval only if the chief executive is satisfied that, at the time the application is made, the type of electrical equipment—
 - (a) is for sale or is intended for sale; or
 - (b) is being manufactured in accordance with the approval.
- (6) The renewal may be on conditions.
- (7) A person granted a renewal of an approval under subsection (5) must comply with any conditions of the renewal.

Maximum penalty—40 penalty units.
- (8) The chief executive must give the applicant written notice of the following within 3 months after the relevant date—
 - (a) the grant or refusal of the renewal;
 - (b) if the renewal is granted—any conditions of the renewal;
 - (c) if the renewal is refused—an information notice for the decision to refuse.
- (9) If the chief executive does not give the notice within 3 months after the relevant date, the application is taken to have been refused.
- (10) If the approval will expire before the relevant date, the term of the approval is extended until whichever of the following happens first—
 - (a) the chief executive gives the notice mentioned in subsection (8);
 - (b) the application is taken to have been refused under subsection (9).
- (11) In this section—

relevant date means—

- (a) the date the chief executive receives an application for a renewal of a type approval for a type of electrical equipment; or
- (b) if the chief executive makes a request for additional information in relation to an application for a renewal of a type approval for a type of electrical equipment—the date the chief executive makes the request.

104 Register of approved types of electrical equipment

- (1) The chief executive must keep a register of approved types of electrical equipment.
- (2) The register must include particulars of—
 - (a) type approval certificates, including—
 - (i) the name and address of each type approval holder; and
 - (ii) the expiry day of each approval; and
 - (b) transfers and cancellations of approvals.
- (3) The chief executive may keep the register in the form, whether or not documentary form, the chief executive considers appropriate.

Division 4 Changes to approvals

105 Changing name and address

- (1) If the name or address of a type approval holder for a type of electrical equipment changes, the holder must give written notice of the new name or address to the chief executive within 14 days after the change.

Maximum penalty—20 penalty units.

- (2) The chief executive must enter details of the new name or address in the register of approved types of electrical equipment.

106 Application to change approval to include new type

- (1) A type approval holder for a type of electrical equipment may apply to the chief executive to change the approval of the type of electrical equipment (the *existing type*) to include an approval of another type of electrical equipment (the *new type*) that is not substantially different from the existing type.
- (2) The application to change the approval of the existing type to include an approval of the new type must—
 - (a) be made in the approved form; and
 - (b) be accompanied by—
 - (i) if required by the chief executive, a test report issued by an approved testing entity stating—
 - (A) that an item of electrical equipment of the new type has been tested or examined in accordance with the safety requirements, electrical or otherwise, of the relevant standard for the existing type as in force when the item was manufactured or the test report was issued; and
 - (B) the results of the test or examination; and
 - (ii) information required by the chief executive to decide if the new type complies with the relevant standard for the existing type; and
 - (iii) the fee for the application; and
 - (iv) if required by the chief executive—an item of electrical equipment of the new type.

107 Changing approval of type of electrical equipment to include new type

- (1) The chief executive may change the approval of the existing type by including approval of the new type in the approval of the existing type if the new type complies with the electrical safety requirements of the relevant standard for the existing type.

- (2) In changing the approval, the chief executive must issue the type approval holder a certificate to be attached to the type approval certificate for the existing type.
- (3) If the chief executive refuses to change the approval, the chief executive must give the type approval holder an information notice for the decision to refuse.

Division 5 Transfer and cancellation of approvals

108 Transfer of approval of type of electrical equipment

- (1) A proposed transferee of the approval of a type of electrical equipment may apply to the chief executive for approval of the transfer.
- (2) The chief executive may approve the transfer if the application—
 - (a) is made in the approved form; and
 - (b) is accompanied by—
 - (i) the type approval certificate for the type of electrical equipment; and
 - (ii) the fee for the application; and
 - (iii) the type approval holder's written agreement to the transfer.
- (3) The chief executive may approve the transfer even if subsection (2)(b)(i) or (iii) is not complied with if the chief executive is satisfied that the type approval holder agrees to the transfer.
- (4) If the chief executive refuses to approve the transfer, the chief executive must give the proposed transferee an information notice for the decision to refuse.
- (5) If the chief executive approves the transfer, the chief executive must—

- (a) issue to the proposed transferee a new type approval certificate for the type of electrical equipment; and
- (b) cancel the old type approval certificate.

109 Cancellation of approval of type of electrical equipment

- (1) The chief executive may cancel the approval of a type of electrical equipment if—
 - (a) an item of electrical equipment of the type does not comply with the safety requirements, electrical or otherwise, of the relevant standard for the type; or
 - (b) an item of electrical equipment of the type is, or is likely to be or to become, dangerous in normal use; or
 - (c) the approval was obtained by incorrect or misleading information; or
 - (d) an item of electrical equipment of the type, or purportedly of the type, is found, on examination by the chief executive, to be substantially different from the type as described in—
 - (i) the type approval certificate for the type; or
 - (ii) a test report forming the basis for the approval of the type; or
 - (e) the type approval holder for the type of electrical equipment contravenes the Act in relation to the approval; or
 - (f) the type approval holder for the type of electrical equipment does not pay a fee required under this regulation to be paid in relation to the approval; or
 - (g) the type approval holder for the type of electrical equipment asks for the cancellation.
- (2) If the chief executive cancels the approval of a type of electrical equipment, other than at the type approval holder's request, the chief executive must notify the cancellation by gazette notice stating the day of cancellation.

110 Procedure before cancellation

- (1) If the chief executive considers a ground exists to cancel the approval of a type of electrical equipment, other than that the type approval holder has asked for the cancellation, the chief executive must, before taking the action, give the type approval holder written notice—
 - (a) stating that the chief executive is considering cancelling the approval; and
 - (b) stating each ground for the proposed cancellation; and
 - (c) outlining the facts and circumstances forming the basis for each ground; and
 - (d) inviting the type approval holder to show, within a stated time of at least 28 days, why the approval should not be cancelled.
- (2) If, after considering all written representations made by the type approval holder within the stated time, the chief executive still considers a ground exists to cancel the approval, the chief executive may cancel the approval.
- (3) If the chief executive cancels the approval, the chief executive must give the type approval holder an information notice for the decision to cancel the approval.

111 Type approval holder to return type approval certificate for cancelled approval

Within 14 days of receiving notice of cancellation of approval of a type of electrical equipment, the type approval holder for the type of electrical equipment must give the chief executive the type approval certificate for the type unless the type approval holder has a reasonable excuse.

Maximum penalty—10 penalty units.

Division 6 Marking of equipment of approved type

112 Marking of item of electrical equipment of approved type

An item of electrical equipment of a type of electrical equipment approved under this part is marked as required under this part if it is marked with—

- (a) the type approval number for the approval of the type; or
- (b) another mark approved by the chief executive.

113 Approval by the chief executive not to mark item of electrical equipment

- (1) This section applies if the chief executive considers that any item of electrical equipment of a type approved under this part is too small to be marked as otherwise required under this part or, for another reason, should not be marked.
- (2) The chief executive may, by written notice given to the type approval holder for the type of electrical equipment, direct that each item of electrical equipment of the type is adequately marked under this part if the container for each item of the type—
 - (a) is marked with—
 - (i) the type approval number for the approval of the type; or
 - (ii) another mark approved by the chief executive; and
 - (b) states the nature of the item of electrical equipment.

Division 7 Chief executive may require testing of item of electrical equipment of approved type

114 Chief executive may require item of electrical equipment of approved type to be submitted

If the chief executive considers it necessary or appropriate for the maintenance of electrical safety, the chief executive may decide to have an item of electrical equipment of a type approved under this part tested and examined for compliance with the relevant standard for the type.

115 Procedure for obtaining item of electrical equipment for testing

- (1) If the chief executive decides to have an item of electrical equipment of a type approved under this part tested and examined, the chief executive may—
 - (a) by written notice, require the type approval holder for the type of electrical equipment to give the chief executive items of electrical equipment of the type for testing and examining within a stated reasonable time; or
 - (b) buy, for testing and examining, items of electrical equipment of the type at any place where they are offered for sale; or
 - (c) require an inspector to select, for testing and examining, items of electrical equipment of the type from a place where the type approval holder for the type of electrical equipment has them stored and give them to the chief executive within a stated reasonable time.
- (2) If the chief executive makes a requirement under subsection (1)(a), the type approval holder must take all steps that are reasonable in the circumstances to ensure that the requirement is complied with.

Maximum penalty—40 penalty units.

- (3) If the chief executive makes a requirement under subsection (1)(c), the type approval holder must take all steps that are

reasonable in the circumstances to ensure the inspector is able to comply with the requirement.

Maximum penalty for subsection (3)—40 penalty units.

116 Identification of item of electrical equipment to be tested

Before the chief executive gives an item of electrical equipment of a type approved under this part to an approved testing entity for testing and examining, the chief executive must—

- (a) give the type approval holder for the type an opportunity to place an identifying mark on the item; and
- (b) advise the approved testing entity of the mark.

117 Cost of testing and examining and liability for damage

- (1) If an item of electrical equipment of a type approved under this part is tested and examined under this division and is found to comply substantially with the relevant standard for the type, the chief executive must bear the cost of the testing and examination and compensate the type approval holder for the type for any damage done to the item.
- (2) An amount for which a type approval holder is entitled to be compensated under subsection (1) may be recovered from the chief executive as a debt owing by the State to the type approval holder.
- (3) If an item of electrical equipment of a type approved under this part is tested and examined under this division and is found not to comply substantially with the relevant standard for the type, the type approval holder for the type—
 - (a) must reimburse the chief executive for all costs incurred in obtaining and having the item of electrical equipment tested and examined; and
 - (b) is not entitled to compensation for damage necessarily caused to the item to enable it to be properly tested and examined.

- (4) An amount the chief executive is entitled to be reimbursed under subsection (3) may be recovered by the chief executive as a debt owing to the State.

118 Return of item of electrical equipment given to chief executive

- (1) This section applies if, at the chief executive's request, a person gives the chief executive free of charge an item of electrical equipment—
 - (a) for testing and examination under this division; or
 - (b) with an application under this part.
- (2) The chief executive must notify the person the item of electrical equipment is available for collection by the person at a stated place as soon as practicable after—
 - (a) for an item of electrical equipment provided for testing or examination—
 - (i) if the chief executive believes, on reasonable grounds, that the item is required as evidence in a prosecution for an offence—the prosecution and any appeal from the prosecution; or
 - (ii) if subparagraph (i) does not apply—the testing and examination; or
 - (b) if the item is given with an application under this part—the chief executive decides the application.
- (3) Despite subsection (2)(a)(i), the chief executive must notify the person immediately after the earlier of the following—
 - (a) the chief executive decides the item of electrical equipment is not required as evidence;
 - (b) a prosecution for an offence involving the item of electrical equipment is not started within 6 months from when the notice would have been given if subsection (2)(a)(i) had not applied.
- (4) If, at the end of 6 months after the giving of notice, the item of electrical equipment has not been collected, the chief executive may dispose of the item as the chief executive

considers appropriate and the person is not entitled to claim for the item or any loss or damage to it.

- (5) Subsection (2) does not apply if the item of electrical equipment was necessarily destroyed by testing.

Division 8 Nonprescribed electrical equipment

119 Chief executive may put into effect program for certification

- (1) The chief executive may put into effect a program for the issue of, including charging of fees for, certificates for nonprescribed electrical equipment of its suitability for connection to electricity supply.
- (2) A program under subsection (1) can not require a person to take part in the program.

120 Sale of particular nonprescribed electrical equipment prohibited

A person must not sell an item of nonprescribed electrical equipment to which the safety criteria in AS/NZS 3820 (Essential safety requirements for low voltage electrical equipment) apply unless the item of electrical equipment complies with the safety criteria as in force at the later of the following—

- (a) on 5 October 1998;
- (b) when the item was manufactured or imported.

Maximum penalty—40 penalty units.

Division 9 Prohibition of hire or sale of particular electrical equipment

121 Chief executive may prohibit the hire, sale or use of electrical equipment on safety grounds

- (1) The chief executive may, by gazette notice, prohibit the hire, sale or use of an item of electrical equipment, or items of electrical equipment of a particular type, if the chief executive believes on reasonable grounds that the item or type does not comply with the safety criteria in AS/NZS 3820 (Essential safety requirements for low voltage electrical equipment).
- (2) The prohibition remains in force for the time stated in the prohibition or, if no time is stated, without limit of time.
- (3) As well as notifying the prohibition in the gazette, the chief executive must give an information notice for the decision to prohibit the hire, sale or use of the item or type of electrical equipment to each person the chief executive knows to be, or to be likely to be, a hirer or seller of the item or type.
- (4) A person must not contravene the prohibition, unless the person has a reasonable excuse.
Maximum penalty—40 penalty units.
- (5) Unless a court otherwise decides in the circumstances of a particular case, it is not a reasonable excuse for a contravention of the prohibition that the person did not receive an information notice under subsection (3).

Division 10 Second-hand electrical equipment

122 Limitation on sale of second-hand electrical equipment

- (1) This section applies to a person if the person conducts a business or undertaking that includes selling items of second-hand electrical equipment.
- (2) A person to whom this section applies must not sell an item of second-hand electrical equipment unless the person gives the

purchaser of the item information about whether the item has been tested and found to be electrically safe.

Maximum penalty—40 penalty units.

- (3) A person to whom this section applies must not sell an item of second-hand electrical equipment if—
- (a) the item is of a type of a prescribed class of electrical equipment; and
 - (b) none of the following apply—
 - (i) the item has or had a Queensland approval, and is marked as required under this part;
 - (ii) the item has or had an external approval, and is marked as required by the law governing the marking of the item in the external approvals entity's jurisdiction;
 - (iii) the item is marked with a regulatory compliance mark.

Maximum penalty for subsection (3)—40 penalty units.

123 Limitation on offering second-hand electrical equipment for sale

- (1) A person who offers for sale to another person (the *proposed purchaser*) an item of second-hand electrical equipment must also give the proposed purchaser information to the effect that the item has not been tested and found to be electrically safe.

Maximum penalty—40 penalty units.

- (2) However, if the item has been tested by a licensed electrical worker who is qualified to test the item and has been found to be electrically safe, the proposed purchaser may instead be given the information about the test.
- (3) A person is not required to comply with subsection (1) if the proposed purchaser conducts a business or undertaking that includes dealing in, repairing or reconditioning items of second-hand electrical equipment.

Division 11 Labelling and inspection of electrical equipment

124 Labelling faulty portable electrical equipment

- (1) This section applies if a person acting under the authority of a distribution entity finds, at a place occupied by a consumer, an item of portable electrical equipment that has a serious defect.
- (2) The distribution entity must ensure that a label is attached to the item of electrical equipment stating that the item is electrically unsafe.

Maximum penalty—40 penalty units.

- (3) A person must not take the label off the item of electrical equipment or connect a source of electricity to the item unless the item—
 - (a) is repaired by a licensed electrical worker qualified to repair it; or
 - (b) is repaired by a person who, because of the operation of section 18(2)(d)¹² of the Act, is not performing electrical work in repairing the equipment.

Maximum penalty for subsection (3)—40 penalty units.

Division 12 Hire electrical equipment

125 Purpose of div 12

This division prescribes a way of discharging the electrical safety obligation of an employer or self-employed person to ensure that the person's business or undertaking is conducted in a way that is electrically safe.

126 Hiring electrical equipment

- (1) An employer or self-employed person must not hire out to another person an item of electrical equipment belonging to

12 Section 18 (Meaning of *electrical work*) of the Act

Electrical Safety Regulation 2002

the employer or self-employed person unless the employer or self-employed person ensures that—

- (a) either—
 - (i) a competent person inspects and tests the equipment before each hiring; or
 - (ii) the item has a safety switch that can not be disconnected, deactivated or removed during the item's operation; and
- (b) the item is inspected, tested and tagged by a competent person at least once every 6 months; and
- (c) if the item has a safety switch under paragraph (a)(ii), the safety switch—
 - (i) is inspected, tested and tagged by a competent person at least once every 6 months; and
 - (ii) complies with AS/NZS 3760 (In-service safety inspection and testing of electrical equipment) when tested.

Maximum penalty—40 penalty units.

- (1A) However, subsection (1)(b) does not apply if the item is domestic electrical equipment that is hired for use in a domestic situation.

Example of domestic electrical equipment hired for use in a domestic situation—

refrigerator, television or computer hired for use in a dwelling house or flat

Example of domestic electrical equipment not hired for use in a domestic situation—

refrigerator hired for use in a mechanic's workshop

- (2) For subsection (1)(a)(i), if because of the way in which the item of electrical equipment is designed, the item can not be tested without dismantling it, the item must be tested to the extent that it can be tested without dismantling it.
- (3) If, after inspecting and testing an item of electrical equipment under subsection (1)(b), a competent person decides the item is safe to use, the employer or self-employed person must ensure the competent person immediately attaches a durable

tag to the item that shows the day by which the item must be reinspected and retested.

Maximum penalty—40 penalty units.

- (4) If the competent person decides the item of electrical equipment is not safe to use, the employer or self-employed person must ensure that—
- (a) the competent person immediately attaches a durable tag to the item warning people not to use the item; and
 - (b) the item is immediately withdrawn from use.

Maximum penalty—40 penalty units.

- (5) The employer or self-employed person must keep records of the tests performed under subsection (1)(b) or (c)(i) for at least 5 years.

Maximum penalty for subsection (5)—20 penalty units.

- (6) In this section—

domestic electrical equipment means computer equipment, browngoods or whitegoods.

Division 13 Miscellaneous

126A Refund of fees

- (1) This section applies if an application mentioned in schedule 7,¹³ item 9, 11 or 13 is—
- (a) refused by the chief executive; or
 - (b) withdrawn before it is decided.
- (2) The amount stated in schedule 7 as the administration component of the fee paid for the application must be refunded.

Part 7 **Works of an electricity entity**

Division 1 **Compliance with part**

127 **Purpose of pt 7**

To the extent that this part applies, or is capable of applying, to an electricity entity, this part prescribes a way of discharging the electrical safety obligation of an electricity entity to ensure that its works—

- (a) are electrically safe; and
- (b) are operated in a way that is electrically safe.

128 **Compliance with this part**

A person, including an electricity entity, who designs, builds, maintains or operates works of an electricity entity must ensure that the requirements of this part for the works of an electricity entity are complied with.

Maximum penalty—40 penalty units.

Division 2 **Earthing and protection**

129 **Systems of earthing**

- (1) The works of an electricity entity must incorporate an earthing and protection system, to a recognised electricity supply industry standard, capable of ensuring the following—
 - (a) reliable passage of fault current;
 - (b) reliable passage of single wire earth return load currents to ground or source;
 - (c) reliable operation of circuit protection devices;
 - (d) safe step, touch and transfer potentials for all electrical equipment;

- (e) appropriate coordination with the earthing and protection systems of other electricity entities;
 - (f) protection against likely mechanical damage, inadvertent interference and chemical deterioration;
 - (g) mechanical stability and integrity of connections.
- (2) Without limiting subsection (1), the following specific requirements apply for the works of an electricity entity—
- (a) to stop, as far as practicable, a person suffering electric shock—
 - (i) if the multiple earthed neutral system of earthing is used—the neutral conductor of the system must be effectively earthed; and
 - (ii) each non current carrying exposed conductive part of an electric line or generating plant must be effectively earthed;
 - (b) each non current carrying exposed conductive part of a substation must be effectively earthed;
 - (c) a system of earthing must be tested as soon as practicable after its installation to prove its effectiveness;
 - (d) a high voltage electric line must be protected by a suitable fuse, circuit-breaker or equivalent device.
- (3) Earthing is not required under subsection (2)(a)(ii) or (b) in circumstances where the electricity entity, in accordance with a recognised practice in the electricity industry, considers that for safety reasons earthing is not appropriate.

130 Connection of high voltage circuit to earth

- (1) Each distinct high voltage system included in the works of an electricity entity must be connected to earth by direct connection or through a resistance or a reactance.
- (2) All reasonable precautions must be taken to ensure that, for the circumstances in which the system is to operate, fuses or circuit-breakers in the system will operate during fault conditions.

131 Performance and other requirements for works

The following requirements apply for the works of an electricity entity—

- (a) the works must be able to perform under the service conditions and the physical environment in which the works operate;
- (b) the works must have enough thermal capacity to pass the electrical load for which they are designed, without reduction of electrical or mechanical properties to a level below that at which safe operational performance can be provided;
- (c) to the greatest practicable extent, the works must have enough capacity to pass short circuit currents to allow protective devices to operate correctly;
- (d) the works must have enough mechanical strength to withstand anticipated mechanical stresses caused by environmental, construction or electrical service conditions;
- (e) the works must be—
 - (i) designed and constructed to restrict unauthorised access by a person to live exposed parts; and
 - (ii) operated in a way that restricts unauthorised access by a person to live exposed parts;
- (f) design, construction, operation and maintenance records necessary for the electrical safety of the works must be kept in an accessible form;
- (g) parts of the works whose identity or purpose is not obvious must be clearly identified by labels, and the labels must be updated as soon as possible after any change is made to the works;
- (h) electrical equipment intended to form part of the works of an electricity entity must undergo commissioning tests and inspection to verify that the electrical equipment is suitable for service and can be operated safely when initially installed or altered.

132 Insulation of stay wire

If a stay wire attached to a pole or structure supporting an overhead electric line forming part of the works of an electricity entity does not form part of an earthing system, the wire must be insulated to prevent, as far as practicable, any person suffering an electric shock.

133 Protection of earth conductors

To prevent, as far as practicable, any person suffering an electric shock, earthing conductors installed on the outside of a pole or structure supporting an overhead electric line forming part of the works of an electricity entity must be, from ground level to a height of at least 2.4m—

- (a) insulated or suitably covered by a nonconductive material; and
- (b) protected from mechanical damage.

Division 3 Substations**134 Substation requirements**

The following requirements apply for a substation forming part of the works of an electricity entity—

- (a) there must be safe access to, and exit from, the substation;
- (b) a building or enclosure forming part of the substation must be secure, and all reasonable care must be taken to stop unauthorised access to the building or enclosure;
- (c) electrical equipment forming part of the substation must meet applicable standards for electrical safety of persons and property;
- (d) the substation must have appropriate signs, labels, warning notices and barriers.

Division 4 Electric lines and control cables

134A Application of div 4

This division does not apply to electric lines and control cables that are part of a substation that is part of the works of an electricity entity.

135 Measurement of vertical and horizontal distances

For this division—

- (a) the vertical distance of a conductor from the ground is the length of a vertical line between the conductor and the ground; and
- (b) the vertical distance of a conductor from a structure that is immediately below the conductor is the length of a vertical line between the conductor and the point on the structure immediately below the conductor; and
- (c) the vertical distance of a conductor from a structure that is not immediately below the conductor is the length of a vertical line between the conductor and the horizontal projection of the nearest point on the structure to the conductor; and
- (d) the horizontal distance of a conductor from a structure is the length of a horizontal line from the conductor to the nearest point on the structure; and
- (e) the horizontal distance of a conductor from a verandah, balcony, road cutting, embankment or other similar thing is the length of a horizontal line from the conductor to the vertical projection of the nearest point on the verandah, balcony, road cutting, embankment or other similar thing; and
- (f) the horizontal distance of a conductor from a structure that is not immediately below the conductor is the length of a horizontal line from the conductor to the vertical projection of the nearest point on the structure.

136 Electric lines and control cables

The following requirements apply for electric lines and control cables forming part of the works of an electricity entity—

- (a) the lines and cables must be designed and constructed to ensure that applicable safety clearance requirements for clearance to the ground, buildings and other structures, and to other conductors, are complied with, and are appropriate having regard to environmental, construction and electric service conditions;
- (b) underground cables are installed in a way that takes account of local environmental and service conditions, the location of other public utility provider services and the risk of damage from excavation;
- (c) if an underground cable is located above the surface of the ground at a particular place and is accessible to the public, it must be mechanically protected from the point at which it leaves the ground up to a height of 2400mm above any surface near the place on which a person is able to stand;
- (d) a low voltage overhead service must be an insulated cable or a neutral screened cable.

137 Clearance from exposed conductive parts and separation of conductors in same circuit

Exposed conductors in the same circuit of an overhead electric line forming part of the works of an electricity entity must be separated so that, as far as practicable, a conductor does not come in contact with or within arcing distance of—

- (a) another conductor; or
- (b) an earthed exposed conductive part; or
- (c) a stay wire forming part of the overhead electric line.

138 Location of overhead circuit in relation to another overhead circuit

- (1) If the overhead circuits of electric lines forming part of the works of 1 or more electricity entities include different overhead circuits of electric lines that are adjacent, or that cross, and that are on 1 structure, the circuits must be placed as follows—
 - (a) 2 or more low voltage circuits must be placed 1 above the other or side by side;
 - (b) 2 or more high voltage circuits must be placed 1 above the other or side by side;
 - (c) low voltage circuits must be placed below high voltage circuits;
 - (d) if 2 or more high voltage circuits are placed 1 above the other, any lower voltage circuit must be placed below any higher voltage circuit.
- (2) Subsection (1)(c) does not apply to conductors erected on a pole transformer substation.
- (3) Subsection (1)(d) does not apply if an electricity entity considers that exceptional circumstances apply, and that failure to comply with the requirement would not create an unsafe or hazardous situation.

139 Clearance of overhead electric lines from ground

- (1) An electricity entity must ensure the distance from the conductors of its overhead electric lines to the ground is in accordance with—
 - (a) for an overhead electric line, including a high voltage overhead service line—schedule 4, parts 1 and 3; and
 - (b) for a low voltage overhead service line—schedule 5, part 1.
- (2) Subsection (1) does not apply to electric cables known as aerial bundled cables installed with a clearance from the ground decided by the electricity entity to be a safe clearance considering the nature of the cables and their location.

140 Clearance of overhead electric lines from structures

- (1) An electricity entity must ensure the distance from the conductors of its overhead electric lines to a structure is in accordance with—
 - (a) for an overhead electric line, including a high voltage overhead service line—schedule 4, parts 2 and 4; and
 - (b) for a low voltage overhead service line—schedule 5, part 2.
- (2) Subsection (1) does not apply to electric cables known as aerial bundled cables installed with a clearance from a structure decided by the electricity entity to be a safe clearance considering the nature of the cables and their location.

141 Building or adding to structure near electric line

- (1) This section applies if—
 - (a) a person proposes to perform work; and
 - (b) the work is 1 or more of the following—
 - (i) the construction of a building or other structure or of a change to a building or other structure;
 - (ii) the performance of other work in relation to a building or other structure; and
 - (c) the proposed work is likely to involve a building or other structure coming within the clearance requirements under this division for an overhead or underground electric line.
- (2) The person must give written notice in a form approved by the electricity entity whose works include the electric line before the work starts.

Maximum penalty—40 penalty units.
- (3) On receiving the notice, the electricity entity must—
 - (a) take action it considers necessary to protect its works while the work is being performed and to ensure the

- requirements of part 4¹⁴ for exclusion zones will be complied with while the work is being performed; and
- (b) relocate or change the electric line so that after the work is completed—
 - (i) the requirements of this regulation for clearances will be complied with; and
 - (ii) the electric line will be accessible to the electricity entity's employees for the line's operation and maintenance.
 - (4) Unless otherwise agreed between the electricity entity and the person—
 - (a) the person must pay the costs reasonably incurred by the electricity entity acting under subsection (3); and
 - (b) the costs are a debt payable by the person to the electricity entity.

142 Clearance of stay wires and control cables over road

An electricity entity's overhead stay wire or overhead control cable crossing the carriageway of a road must have clearance from the ground of at least 5.5m at the centre line of the carriageway and at least 4.9m at the kerb line of the road.

143 Connection to consumer's premises

- (1) An electricity entity, in supplying electricity to a consumer, must decide the position of its fuses, circuit-breakers, disconnection links and other apparatus in accordance with recognised practice in the electricity industry.
- (2) A consumer must provide suitable means for the connection of the consumer's electrical installation to a service line.

Division 5 Termination requirements for low voltage overhead service lines

144 Termination of low voltage overhead service line

- (1) An electricity entity must ensure a low voltage overhead service line is—
 - (a) secured to a consumer's premises, including poles on the premises; and
 - (b) insulated continuously; and
 - (c) not readily accessible to persons.
- (2) An electricity entity must ensure a metallic pin, eye bolt or other similar fixture installed by or for it on a consumer's premises to support an active conductor of a low voltage overhead service line is effectively earthed.
- (3) The earthing must be by direct connection to the neutral conductor of the service line, at the point of support, by a conductor having an appropriate cross-sectional area.
- (4) Earthing under subsections (2) and (3) is not required if—
 - (a) the low voltage overhead service line is a neutral screened cable and the service fuse is mounted on the electricity entity's pole; or
 - (b) no part of the metallic pin, eye bolt or other similar fixture, or of a metal bracket or riser supporting it, is within 25mm of other metal work on a building, pole or other structure.

Division 6 Service lines generally

145 Fuses and disconnectors for service line

- (1) An electricity entity must provide a fuse or circuit-breaker for each active conductor of a low voltage service line that provides fault current protection for a consumer's electrical installation unless—

- (a) electricity to the consumer's electrical installation is supplied direct from a transformer; and
 - (b) the electricity entity is satisfied that the fuse or circuit-breaker of the transformer provides enough protection for the consumer's electrical installation; and
 - (c) the electricity entity uses the fuse or circuit-breaker of the transformer instead of a fuse or circuit-breaker in the low voltage service line.
- (2) However, if, under subsection (1), the electricity entity uses the fuse or circuit-breaker of the transformer instead of a fuse or circuit-breaker in the low voltage service line, the electricity entity must install isolating links in the electric line supplying the consumer's electrical installation if another consumer's electrical installation is also supplied from the transformer.
- (3) Also, if the electricity entity is not satisfied the fuse or circuit-breaker of the transformer provides enough protection for the consumer's electrical installation, the electricity entity must provide suitable protection on the low voltage side of the transformer.
- (4) Subsection (3) does not apply if the electricity entity is satisfied that suitable protection is provided in the consumer's electrical installation.

146 Disused service lines to be disconnected

An electricity entity must ensure that a service line for a consumer's premises is disconnected and sufficiently isolated from any electric line forming part of its works if—

- (a) the supply of electricity to the consumer's premises has been disconnected; and
- (b) the electricity entity has taken away any of its meters, control apparatus or other electrical equipment from the premises.

Division 7 Maintenance of works

147 Inspection and maintenance of integrity of insulation

- (1) An electricity entity must ensure the integrity of the insulation of the relevant part of the electrical entity's works is inspected and maintained.
- (2) An electricity entity must ensure the integrity of insulation for the clamp or other apparatus at the point where consumer mains are connected to the electricity entity's service line is inspected and maintained.
- (3) Inspection and maintenance under subsection (1) or (2) must be performed at periodic reasonable intervals.
- (4) In this section—

relevant part of an electrical entity's works means the part of an electric line forming part of the works that—

- (a) is adjacent to a roof or structure; and
- (b) in a position where it is likely that a person could come into contact with the line.

Example of a person who is likely to come into contact with the line—

a painter or plumber

148 Trimming of trees near overhead electric line

An electricity entity must ensure that trees and other vegetation are trimmed, and other measures taken, to prevent contact with an overhead electric line forming part of its works that is likely to cause injury from electric shock to any person or damage to property.

Part 8 Electricity supply

Division 1 Connection to source of electricity

149 Electrical installation with serious defect not to be connected to electricity source

- (1) If an electrical installation has a serious defect, a person must not connect the installation to a source of electricity for use for its intended purpose.

Maximum penalty—40 penalty units.

- (2) Subsection (1) does not apply to a distribution entity unless the serious defect in the electrical installation is located in a consumer main switchboard or between a consumer main switchboard and the works of the distribution entity.

150 Electrical installation not to be connected to electricity source if work not tested

- (1) A person must not connect an electrical installation on which electrical work has been performed to a source of electricity unless—

- (a) the person who performed the electrical work was authorised under the Act to perform it; and
- (b) the electrical installation, to the extent it is affected by the electrical work, has been tested to ensure it is electrically safe and is in accordance with the requirements of the wiring rules and any other standard applying under this regulation to the electrical installation.

Maximum penalty—40 penalty units.

- (2) Subsection (1) does not apply to an electrical installation's first connection to a source of electricity.

151 Electrical installation not to be initially connected to electricity source without examination and testing

- (1) A person must not connect an electrical installation to a source of electricity supplied by a distribution entity for the first time unless the distribution entity has—
 - (a) examined the consumer mains and main switchboard for the electrical installation and confirmed there are no serious defects; and
 - (b) carried out tests to ensure the consumer mains and main switchboard are electrically safe.

Maximum penalty—40 penalty units.

- (2) The distribution entity may charge a consumer for an examination or test performed under subsection (1) only if, at the consumer's request, the examination or test is performed outside normal working hours.

152 Reconnection of electrical installation to electricity source

- (1) A person must not reconnect an electrical installation to a source of electricity supplied by a distribution entity unless the person is authorised to do so under subsection (2) or (3).

Maximum penalty—40 penalty units.

- (2) A distribution entity is authorised to reconnect an electrical installation to a source of electricity if—
 - (a) the distribution entity first performs a visual examination of the electrical installation and finds there to be no serious defects; or
 - (b) the distribution entity does not first perform a visual examination of the electrical installation, but the following circumstances apply—
 - (i) the electrical installation was disconnected by the distribution entity because of debt;
 - (ii) the electrical installation has been disconnected for less than 1 month;
 - (iii) the reconnection is for the purpose of supplying the same consumer.

- (3) A licensed electrical contractor is authorised to reconnect a part of an electrical installation to a source of electricity if the contractor has rectified a serious defect that has caused a distribution entity or inspector to leave the part disconnected.
- (4) A distribution entity must keep a record, for at least 5 years, of all electrical installations that have been disconnected from a source of electricity supplied by the distribution entity and which, in the absence of authorisation under subsection (2) or (3), must not be reconnected.

Maximum penalty—20 penalty units.

- (5) A distribution entity may charge a consumer for an examination performed under subsection (2)(a) only if, at the consumer's request, the examination is performed outside normal working hours.
- (6) This section does not apply to reconnection in the ordinary course of disconnection and reconnection in the performance of electrical work.

153 High voltage or hazardous area electrical installation not to be connected to electricity source without inspection

- (1) A person must not connect or reconnect a high voltage electrical installation, or an electrical installation located in a hazardous area, to a source of electricity after electrical installation work or electric line work (the *electrical work*) has been performed on the electrical installation unless—
 - (a) the electrical work has been inspected by an accredited auditor; and
 - (b) the accredited auditor has confirmed that the electrical installation, to the extent it is affected by the electrical work, has been tested to ensure it is electrically safe and is in accordance with the requirements of the wiring rules and any other standard applying under this regulation to the electrical installation.

Maximum penalty—40 penalty units.

- (2) A person must not, at a particular place, connect a high voltage electrical installation, or an electrical installation

located in a hazardous area, to a source of electricity for the first time at the place unless—

- (a) the electrical installation has been inspected by an accredited auditor; and
- (b) the accredited auditor has confirmed that the electrical installation has been tested to ensure it is electrically safe and is in accordance with the requirements of the wiring rules and any other standard applying under this regulation to the electrical installation.

Maximum penalty—40 penalty units.

- (3) This section applies in addition to other provisions of this division about the connection or reconnection of an electrical installation to a source of electricity.

154 Licensed electrical contractor not to connect electricity source without being satisfied of compliance with Act and regulation

A licensed electrical contractor must not connect an electrical installation on which electrical work has been performed to a source of electricity unless the contractor is satisfied that the Act and this regulation have been complied with in relation to the electrical installation to the extent it is affected by the electrical work.

Maximum penalty—40 penalty units.

155 Disconnection and reconnection of low voltage electrical installation

- (1) This section applies to person who—
 - (a) is a licensed electrical contractor, or a licensed electrical worker who holds an electrical mechanic licence and is employed by a licensed electrical contractor; and
 - (b) either—
 - (i) performs electrical installation work on a consumer's consumer terminals, main switchboard or consumer mains; or

- (ii) isolates electricity supply to eliminate an exclusion zone that would otherwise exist.
- (2) Despite anything else in this division, the person may, in accordance with recognised electricity industry practice, de-energise and re-energise the consumer's electrical installation by—
 - (a) removing and replacing a fuse wedge from a service fuse; or
 - (b) switching off and on a circuit-breaker installed as a service line disconnecter.
- (3) Whether or not the person has performed electrical work, the person must test to confirm the electrical installation is safe to connect to the source of electricity before connecting the installation to a source of electricity.

Maximum penalty for subsection (3)—40 penalty units.

Division 2 Private generating plant

156 Generating plant for emergency supply

- (1) This section applies to a person if—
 - (a) private generating plant is installed at the person's premises as part of the person's electrical installation; and
 - (b) the private generating plant is intended to provide a supply of electricity to the person's electrical installation, or to the person's electrical installation and the electrical installation of another person, during an interruption of the supply of electricity from a distribution entity.
- (2) The person must ensure that, when the private generating plant is operating to give emergency supply, there is effective isolation between—
 - (a) all active conductors of the part of the electrical installation or electrical installations to which the private generating plant is connected; and

- (b) any part of the electrical installation or electrical installations still connected to the supply from the distribution entity.

Maximum penalty—40 penalty units.

- (3) The person must ensure the installation of the private generating plant is in accordance with the requirements of the wiring rules.

Maximum penalty for subsection (3)—40 penalty units.

157 Generating plant for interconnection to works of electricity entity

- (1) This section applies to a person if—
 - (a) private generating plant is installed at the person's premises as part of the person's electrical installation; and
 - (b) the private generating plant is intended to interconnect with the works of an electricity entity.
- (2) The person must comply with the electricity entity's conditions for ensuring safe and stable parallel operation of the private generating plant with the works of the electricity entity.

Maximum penalty for subsection (2)—40 penalty units.

Division 3 Testing

158 Notice by licensed electrical contractor of test

- (1) This section applies if, under this part—
 - (a) a licensed electrical contractor is required to test electrical work performed on an electrical installation; and
 - (b) part of the electrical installation is required to be examined or tested by the distribution entity that supplies or is to supply electricity to the electrical installation.

- (2) The licensed electrical contractor must give the distribution entity a notice complying with subsection (3).

Maximum penalty—40 penalty units.

- (3) The notice must state that—
- (a) the tests required to be carried out by the licensed electrical contractor will be carried out in the way required under this part; and
 - (b) the electrical installation will be electrically safe by the date stated on the notice; and
 - (c) the electrical installation will be ready for connection by the date stated on the notice.

159 Certificate of testing and compliance

- (1) A licensed electrical contractor who connects an electrical installation on which electrical work has been performed to a source of electricity must, as soon as practicable after the connection, give the person for whom the work was performed a certificate, complying with this section, about the testing of the electrical installation required under this part.

Maximum penalty—40 penalty units.

- (2) The certificate must state the following—
- (a) the name and address of the person for whom the work was performed;
 - (b) the electrical installation tested;
 - (c) the day the electrical installation was tested;
 - (d) the number of the electrical contractor licence under which the electrical installation was tested.
- (3) The certificate must certify that the electrical installation, to the extent it is affected by the electrical work, has been tested to ensure it is electrically safe and is in accordance with the requirements of the wiring rules and any other standard applying under this regulation to the electrical installation.

- (4) A licensed electrical contractor must keep a copy of a certificate given under this section for at least 5 years after the certificate is given.

Maximum penalty for subsection (4)—20 penalty units.

160 Performance of examination or test

A distribution entity that carries out an examination or test required under this part in relation to an electrical installation must examine or test to ensure that the electrical installation, to the extent of the required examination or test, is electrically safe.

Maximum penalty—40 penalty units.

161 Reasons to be given for not connecting to source of electricity after examination

If, after performing an examination or test, a distribution entity does not connect or reconnect a consumer's electrical installation on which electrical work has been performed to a source of electricity, the distribution entity must give the consumer a written report stating the reasons for not connecting or reconnecting the installation.

Maximum penalty—40 penalty units.

162 Keeping copy of report

The employer of a person who, under this part, performs an examination, inspection or test, must keep a copy of the report of the examination, inspection or test for at least 5 years after the report is made.

Maximum penalty—20 penalty units.

Division 4 Requests and advice to distribution entities

163 Request to distribution entity for examination of electrical work

- (1) This section applies if, under this part, electrical work must be examined or tested by a distribution entity before an electrical installation is connected or reconnected to a source of electricity.
- (2) The person who performed the electrical work must, as soon as practicable after the completion of the electrical work, ask the distribution entity that supplies or is to supply electricity to the electrical installation for the work to be examined or tested.

Maximum penalty—40 penalty units.

- (3) The person must make the request in a way approved by the distribution entity.
- (4) In making the request, the person must certify that the electrical work has been completed and that the electrical installation is in accordance with the requirements of this regulation.

164 Telling distribution entity of need for change to metering

- (1) This section applies if, because of the performance of electrical work on an electrical installation, there is a need to install or change metering, control apparatus or other ancillary equipment forming part of the works of a distribution entity.
- (2) The person who performed the electrical work must, as soon as practicable after the completion of the electrical work, tell the distribution entity of the need for the installation or change.

Maximum penalty—40 penalty units.

- (3) The person must advise the distribution entity in a way approved by the distribution entity.
- (4) In giving the advice, the person must certify that the electrical work has been completed.

Part 9 Safety management systems

Division 1 Prescribed electricity entities

165 Prescribed electricity entities

For part 5¹⁵ of the Act, an electricity entity is a prescribed electricity entity if—

- (a) it is named in schedule 6, part 1, and 2 years have elapsed after the commencement of this section; or
- (b) it is named in schedule 6, part 2, and both of the following apply—
 - (i) 2 years have elapsed after the commencement of this section;
 - (ii) 3 months have elapsed after the entity's name was included in schedule 6, part 2.

Division 2 Requirements for safety management systems

166 Safety management system requirements

- (1) This section prescribes requirements for safety management systems.
- (2) A safety management system must contain details of the following—
 - (a) the system's safety objectives;
 - (b) the systems and procedures by which the objectives are to be achieved;
 - (c) the performance criteria to be met;
 - (d) the way in which adherence to the performance criteria is to be maintained.

15 Part 5 (Safety management systems for electricity entities) of the Act

- (3) When a prescribed electricity entity's safety management system is first put into effect or is modified, the entity must give the chief executive—
 - (a) a copy of the safety management system in its current form; and
 - (b) a certificate in the approved form from an accredited auditor that verifies that the safety management system has been assessed and validated to ensure that the system comprehensively identifies and addresses the hazards and risks associated with the design, construction, operation and maintenance of the entity's works.
- (4) A prescribed electricity entity's safety management system must provide that, when the entity gives the chief executive a copy of its safety management system under subsection (3)(a) and a certificate under subsection (3)(b), the entity must give the chief executive any information the chief executive reasonably requires to ensure that the design, construction, operation and maintenance of the entity's works is in accordance with the requirements of the Act.
- (5) A prescribed electricity entity's safety management system must provide for—
 - (a) the auditing by an accredited auditor, at least once every year and at the expense of the prescribed electricity entity, of how the entity is giving effect to the safety management system; and
 - (b) submission to the chief executive of an annual audit plan for the auditing mentioned in paragraph (a); and
 - (c) submission to the chief executive, after each annual audit, of a certificate of the accredited auditor who conducts the auditing mentioned in paragraph (a), stating the current level of compliance of the prescribed electricity entity with its safety management system; and
 - (d) the giving to the chief executive, after the chief executive's consideration of an annual audit plan under paragraph (b) or of a certificate of an accredited auditor under paragraph (c), of the further information the chief

executive reasonably requires about the entity's safety management system and how the entity is giving effect to the system.

- (6) A prescribed electricity entity's safety management system must also provide for—
- (a) the making of modifications to the safety management system in accordance with the reasonable requirements of the chief executive; and
 - (b) if reasonably required by the chief executive, the auditing by an accredited auditor, in addition to the auditing provided for under subsection (5) and at the expense of the prescribed electricity entity, of how the entity is giving effect to the safety management system.

Part 10 Accredited auditors

167 Appointment

- (1) An application for appointment as an accredited auditor under part 10, division 2¹⁶ of the Act must be—
- (a) made in the approved form; and
 - (b) if a fixed fee applies—accompanied by the fixed fee; and
 - (c) supported by enough information to allow the chief executive to decide the application.
- (2) An application for a renewal of a person's appointment as an accredited auditor must be—
- (a) made in the approved form; and
 - (b) if a fixed fee applies—accompanied by the fixed fee; and

16 Part 10 (Inspectors and accredited auditors), division 2 (Accredited auditors) of the Act

- (c) supported by enough information to allow the chief executive to decide the application; and
- (d) be received by the chief executive at least 14 days before the appointment ends.

168 Refund of part of fee

- (1) If the chief executive does not approve an application under this part, or if the application is withdrawn before it is decided, the appointment administration part of any fixed fee paid with the application must be refunded.
- (2) In this section—

appointment administration part, of a fixed fee, means the amount stated in schedule 7 as the cost of administering an appointment as an accredited auditor.

169 Term of office as accredited auditor

A person's term of office as an accredited auditor is—

- (a) 5 years; or
- (b) a shorter time provided for by the chief executive in the person's appointment.

Part 11 Cathodic protection systems

Division 1 Preliminary

170 Definitions for pt 11

In this part—

cathodically protected structure means a structure protected by a cathodic protection system.

cathodic protection standard means AS/NZS 2832.1 (Cathodic protection of metals—Pipes and cables).

foreign structure, for a cathodic protection system, means a structure that is buried or submerged and that may be subject to interference arising from the cathodic protection system.

foreign structure owner, for a cathodic protection system, means a person who owns a foreign structure for the cathodic protection system.

impressed current cathodic protection system means a cathodic protection system in which the current flowing between the structure protected by the cathodic protection system and the anode is supplied by an external source.

maximum operating current, for a cathodic protection system, means the maximum value of the fixed, manually variable or automatically variable current at which the cathodic protection system operates, other than during short term testing of the cathodic protection system.

registered system means a registrable system registered under this part.

registrable system means an impressed current cathodic protection system the converter of which is capable of delivering a current greater than 0.25A.

short term testing, of a cathodic protection system, means testing of less than a total of 30 minutes in any 7 consecutive days.

171 Electrical terms apply for direct current

In this part, electrical values are the values as they apply for direct current.

Examples—

- 500mV means 500mV d.c.
- 50V means 50V d.c.

172 Exclusion from application

Unless otherwise stated in this part, this part does not apply to a cathodic protection system installed on—

- (a) a floating mobile structure; or

- (b) fishing equipment; or
- (c) a fixed off shore structure not connected with land above sea level; or
- (d) an internal surface of an apparatus, structure or item of equipment to which AS 2832.4 (Cathodic protection of metals—Internal surfaces) applies.

Division 2 Installation and design

173 Installation of cathodic protection system only if preliminary steps taken

- (1) A person must not start to install a cathodic protection system unless the person has complied with subsection (2).

Maximum penalty—40 penalty units.

- (2) At least 60 days before starting installation, the person must—
 - (a) advise all relevant persons for the proposed cathodic protection system of the proposal to install the system; and
 - (b) allow the relevant persons to examine the proposal.

- (3) In this section—

relevant person, for a proposed cathodic protection system, means a person who will, if the system is installed, become a foreign structure owner for the system.

174 Correct design and installation of cathodic protection system

A person who owns a cathodic protection system must ensure that the system is designed and installed in accordance with the requirements of the cathodic protection standard.

Maximum penalty—40 penalty units.

Division 3 Operating requirements

175 Operation of cathodic protection system only on conditions

- (1) The owner of a cathodic protection system must not operate the system unless—
 - (a) the system has been tested in accordance with the testing requirements of this part; and
 - (b) each foreign structure owner for the system has stated either that interference mitigation is satisfactory or that it is not required; and
 - (c) the system is operated in accordance with the requirements of the cathodic protection standard; and
 - (d) if the system is a registrable system—the system is currently registered under this part, and is operated in accordance with the requirements of the conditions of its registration.

Maximum penalty—40 penalty units.

- (2) Despite subsection (1)(b), (c) and (d), a person may operate a cathodic protection system for a reasonable period to perform tests in accordance with the testing requirements of this part.

Division 4 Testing requirements

176 Tests before registration or operation of system

- (1) An owner of a cathodic protection system that is a registrable system must perform tests in accordance with this section within 90 days, or the longer period the chief executive allows, before applying for registration of the system.

Maximum penalty—40 penalty units.

- (2) An owner of a cathodic protection system that is not a registrable system must perform tests in accordance with this section within 90 days before starting to operate the system, other than for the tests.

Maximum penalty—40 penalty units.

- (3) The tests are—
- (a) interference tests on all foreign structures for the system; and
 - (b) if the system has an anode immersed in water or a marine environment—tests to ensure the potential difference between any 2 accessible points spaced 1m apart in the water or marine environment are not more than 3V when the system is energised.
- (4) The tests must be based on the maximum value of the current at which the cathodic protection system will operate at all times, other than during short term testing of the cathodic protection system in which currents of greater values are permitted.
- (5) The owner of the cathodic protection system must make all the arrangements for the tests, provide all the facilities and equipment for the tests and bear all the costs associated with the tests.
- (6) Without limiting subsection (5), for the performance of an interference test mentioned in subsection (3)(a), the owner must—
- (a) arrange with all foreign structure owners a mutually acceptable time for performing the test; and
 - (b) allow the foreign structure owners to observe the performance of the test.

177 Further tests during period of registration of system

- (1) This section applies to a cathodic protection system that is a registered system.
- (2) The owner of the system must perform interference tests on all foreign structures for the system—

- (a) when an anode forming part of the system is replaced; and
- (b) if required by the chief executive—when the system, or its method of operation, is changed.

Maximum penalty—40 penalty units.

- (3) If the system has an immersed anode that is redesigned, causing the anode to be relocated or to become subject to variation in anode current distribution, the owner of the system must retest the system to ensure the potential difference between any 2 accessible points spaced 1m apart in the water or marine environment is not more than 3V when the system is energised.

Maximum penalty—40 penalty units.

- (4) If, when interference tests are being performed, there is a foreign structure for the system for which interference tests have not previously been performed, the person must—
 - (a) arrange with the foreign structure owner a mutually acceptable time for performing the tests; and
 - (b) allow the foreign structure owner to observe the performance of the tests.

Maximum penalty for subsection (4)—40 penalty units.

178 Further tests during operation of system

- (1) The owner of a relevant system must perform interference tests on all foreign structures for the system—
 - (a) when an anode forming part of the system is replaced; and
 - (b) when the system or its method of operation is changed.

Maximum penalty—40 penalty units.

- (2) In this section—

relevant system means—

- (a) a cathodic protection system, other than a registered system, that is an impressed current cathodic protection system; or

- (b) a cathodic protection system with a total anode mass of more than 25kg.

179 Further tests of new foreign structure if required by the chief executive

If required by the chief executive, the owner of a cathodic protection system must perform interference tests on a foreign structure for the system not previously tested by the owner.

Maximum penalty—40 penalty units.

180 Records of tests to be kept

- (1) The owner of a cathodic protection system must keep records of tests carried out under this division for 10 years if the system—
 - (a) is an impressed current cathodic protection system; or
 - (b) has a total anode mass of more than 25kg.

Maximum penalty—20 penalty units.

- (2) If asked by the chief executive, the owner must give to the chief executive copies of the records within 14 days of the request.

Maximum penalty for subsection (2)—20 penalty units.

181 Testing by chief executive

- (1) The chief executive may arrange for the testing the chief executive considers necessary to decide whether a cathodic protection system complies with the requirements of this part.
- (2) If reasonably required by the chief executive, the owner of a cathodic protection system must provide access to, and facilities for the testing of, the system.

Maximum penalty—40 penalty units.

- (3) If, on testing, a system is found not to comply with the requirements of this part, the costs reasonably incurred by the chief executive in conducting the test, including the indirect and overhead costs incurred by the chief executive, are a debt payable by the owner to the State.

Division 5 System requirements

182 Electrical limits

- (1) The owner of a cathodic protection system must ensure that the system is in accordance with the requirements of this section for a cathodic protection system.

Maximum penalty—40 penalty units.

- (2) The maximum open circuit voltage of a cathodic protection system may be more than 50V only if safety requirements have been met to the chief executive's satisfaction.
- (3) If an anode for a cathodic protection system is immersed in water or in a marine environment, the potential difference between any 2 accessible points spaced 1m apart in the water or marine environment must not be more than 3V when the system is energised.
- (4) In a surface area of 1000m² measured radially about an electrode or the centre of a group of electrodes discharging current to ground as part of a cathodic protection system on land or in non-saline water, the total current of 1 polarity must not be more than 100A.
- (5) In an area of surface water of 2000m² bounded by a 100m length of the mean low water level contour and a line displaced 20m in a direction away from land from the contour, the total current of 1 polarity discharged to water or substrata by all electrodes in the area for a cathodic protection system must not be more than 500A.
- (6) Subsections (2) and (3) do not apply to a cathodic protection system installed on an internal surface of an apparatus, structure or item of equipment to which AS 2832.4 (Guide to the cathodic protection of metals—Internal surfaces) applies.

183 Maximum potential change

- (1) The owner of a cathodic protection system must ensure that the system is in accordance with the requirements of this section for a cathodic protection system.

Maximum penalty—40 penalty units.

- (2) This section states requirements for a cathodic protection system in relation to a foreign structure for the system.
- (3) The change in potential, foreign structure to ground, must not be more than any of the following—
 - (a) at a point 100m radially from an anode, if there is no metallic link between the cathodically protected structure and the foreign structure, 150mV in a negative going direction;
 - (b) at a point where buried or submerged parts of the foreign structure are in ground or water generally of 1 ohm metre or higher resistivity, 10mV in a positive going direction;
 - (c) at a point where buried or submerged parts of the foreign structure are in ground or water generally below 1 ohm metre resistivity, 0mV;
 - (d) for a foreign structure that is not connected electrically to the cathodically protected structure, 500mV in a negative going direction or, with the foreign structure owner's written agreement, 1V in a negative going direction.
- (4) However, for short term testing of the cathodic protection system, 5 times the potential change stated in subsection (3)(a) or (b) and twice the potential stated in subsection (3)(d) is permitted.
- (5) The potential change stated in subsection (3)(b) or (c) may be changed with the foreign structure owner's written agreement after an assessment of the effect of any existing cathodic protection or interference mitigation measures on the foreign structure.

184 Tolerances

The owner of a cathodic protection system must ensure that the tolerances for measuring instruments used to test the system are in accordance with the safety and technical requirements of the cathodic protection standard.

Maximum penalty—40 penalty units.

185 Identification of anode groundbed

If a registrable system is installed on land or premises not owned by the owner of the system, the owner of the system must identify the location of each anode groundbed of the system by erecting as close as practicable to the anode groundbed a clearly visible, durable sign suitably and indelibly inscribed with the location of the anode groundbed and the name of the owner of the system.

Maximum penalty—20 penalty units.

Division 6 Registration of registrable systems**186 Register**

- (1) The chief executive must keep a register of registered systems.
- (2) The register may be kept in the form, whether or not a documentary form, the chief executive considers appropriate.

187 Application for registration of registrable system

- (1) An application for registration of a cathodic protection system that is a registrable system must—
 - (a) be made in the approved form; and
 - (b) if required by the chief executive, be accompanied by—
 - (i) the prescribed fee; and
 - (ii) details of the geographical location of the system; and
 - (iii) a plan indicating full particulars about the system; and
 - (iv) a certificate from the owner of the system stating the system has been tested as required by this part and complies with the requirements of this part.
- (2) The certificate mentioned in subsection (1)(b)(iv) must state—

- (a) the value of the maximum operating current on which the tests were based; and
 - (b) for a system operating with an anode immersed in water or in a marine environment—the operating voltage of the system corresponding to the maximum operating current mentioned in paragraph (a); and
 - (c) that the owner has complied with the requirements under division 4¹⁷ for testing of the system before registration.
- (3) If asked in writing by the chief executive, the applicant must give further relevant information the chief executive requires to decide the application.
 - (4) The chief executive must decide the application within 60 days of receiving the application.
 - (5) If the chief executive refuses to register the system, the chief executive must give notice of the refusal to the applicant within 30 days of the decision.
 - (6) The notice must be accompanied by an information notice for the decision to refuse.

187A Refund of fees

- (1) This section applies if an application for registration of a cathodic protection system that is a registrable system—
 - (a) is refused by the chief executive under section 187; or
 - (b) is withdrawn before the application is decided.
- (2) The amount stated in schedule 7 as the administration component of the fee paid for the application must be refunded.

188 Registration of registrable system

- (1) The chief executive must register a cathodic protection system that is a registrable system by entering in the register—

¹⁷ Division 4 (Testing requirements)

- (a) the name and address of the owner of the system notified to the chief executive; and
 - (b) the location of the system; and
 - (c) the description of the structure being cathodically protected; and
 - (d) the conditions of registration about—
 - (i) the permitted maximum operating current of the system; and
 - (ii) for a system operating with an anode immersed in water or a marine environment—the permitted maximum operating voltage of the system; and
 - (e) other conditions imposed by the chief executive on the system's operation; and
 - (f) the date of registration.
- (2) Within 30 days of registering the system, the chief executive must give the owner of the system written notice of the registration, including—
- (a) the conditions about the permitted maximum operating current and, if relevant, the permitted maximum operating voltage of the system; and
 - (b) other conditions the chief executive imposes on the system's operation; and
 - (c) the date of registration.

189 Term of registration

The registration of a registrable system is for 5 years, unless it is earlier cancelled.

190 Change of name and address

- (1) The owner of a registered system whose name or address changes must give written notice of the change to the chief executive within 30 days of the change.

Maximum penalty—20 penalty units.

- (2) The chief executive must enter details of the change in the register of registered systems.

191 Cancellation of registration

- (1) The chief executive may cancel the registration of a registered system if—
 - (a) the chief executive is not satisfied the system is installed or operating in accordance with this part; or
 - (b) the chief executive has been notified by the owner of the system that the system has been taken away or made permanently inoperable.
- (2) On cancellation of registration of a cathodic protection system, the chief executive must—
 - (a) enter in the register of registered systems the date of cancellation; and
 - (b) give written notice of the cancellation to the owner of the system within 14 days of the cancellation.
- (3) If the cancellation is under subsection (1)(a), the notice must be accompanied by an information notice for the decision to cancel.

192 Taking away or making a registered system inoperable

If a registered system is taken away or made permanently inoperable, the owner of the system must give written notice to the chief executive within 30 days of the removal or the making inoperable.

Maximum penalty—40 penalty units.

193 Change to registered system to be notified

- (1) If a registered system or its method of operation is changed, the owner of the system must—
 - (a) immediately advise the chief executive; and

- (b) give written notice to the chief executive within 14 days after the change.

Maximum penalty—20 penalty units.

- (2) The notice must be accompanied by a plan clearly showing how the system has been changed.
- (3) If required by the chief executive, the owner of the registered system must take all or part of the action an applicant for registration of a registrable system is required to take under this part.

Maximum penalty for subsection (3)—40 penalty units.

Part 12 **Incident notification and reporting**

194 **Definitions for pt 12**

In this part—

distribution entity, for a serious electrical incident or dangerous electrical event, see section 195.

incident record see section 199.

195 **Meaning of *distribution entity* for incident or event**

- (1) The *distribution entity* for a serious electrical incident is—
- (a) if the electrical equipment the incident involves is part of the works of a distribution entity—the distribution entity; or
- (b) otherwise—the distribution entity that supplies electricity to the electrical equipment the incident involves.
- (2) The *distribution entity* for a dangerous electrical event is the distribution entity that supplies electricity to, or has as part of its works, the electrical equipment that is—
- (a) the subject of the event; or

- (b) the subject of the electrical work that is the subject of the event.

196 Employer or self-employed person to advise chief executive of serious electrical incident or dangerous electrical event

- (1) This section applies if, in the conduct of the business or undertaking of an employer or self-employed person, a serious electrical incident or dangerous electrical event happens.
- (2) The employer or self-employed person must—
 - (a) give written notice of the incident or event to the chief executive in the approved form; and
 - (b) ensure the written notice is received by the chief executive within 24 hours after the employer or self-employed person first becomes aware of the happening of the incident or event.

Maximum penalty—40 penalty units.

- (3) However, if the incident or event that happens is a serious electrical incident in which a person has been killed, the employer or self-employed person must also advise the chief executive of the incident, immediately the employer or self-employed person becomes aware of the happening of the incident, by phone, fax or another suitable form of immediate and effective communication.

Maximum penalty—40 penalty units.

197 Recording serious electrical incident or dangerous electrical event

- (1) This section applies if an employer or self-employed person is required under this part to notify the chief executive of a serious electrical incident or a dangerous electrical event.
- (2) The employer or self-employed person must make and keep a record of the incident or event in accordance with the requirements of this section.

Maximum penalty—20 penalty units.

- (3) The record of the incident or event must be made in the approved form—
 - (a) within 3 days after the employer or self-employed person becomes aware of the happening of the incident or event; or
 - (b) if the employer or self-employed person is incapacitated by the incident or event—as soon as reasonably practicable after the employer or self-employed person is no longer incapacitated.
- (4) The record must be kept for 3 years.

198 Distribution entity to advise chief executive of serious electrical incident or dangerous electrical event

- (1) This section applies if—
 - (a) a distribution entity is advised about the happening of a serious electrical incident or dangerous electrical event; and
 - (b) the distribution entity is the distribution entity for the incident or event.
- (2) The distribution entity must—
 - (a) give written notice of the incident or event to the chief executive in the approved form; and
 - (b) ensure the written notice is received by the chief executive within 24 hours after the distribution entity first becomes aware of the happening of the incident or event.

Maximum penalty—40 penalty units.

- (3) However, if the incident or event that happens is a serious electrical incident in which a person has been killed, the distribution entity must also advise the chief executive of the incident, immediately the distribution entity becomes aware of the happening of the incident, by phone, fax or another suitable form of immediate and effective communication.

Maximum penalty—40 penalty units.

- (4) The distribution entity is not required to give written notice or immediate advice to the chief executive of the incident or event if the distribution entity knows that the incident or event has already been reported to the chief executive.

199 Action required by distribution entity on report of electric shock

- (1) This section applies if a distribution entity is advised by a consumer to whom the distribution entity supplies electricity that a person has received an electric shock.
- (2) The distribution entity must—
 - (a) take the action necessary to be taken in the interests of the electrical safety of persons; and
 - (b) make a written record of the incident (*incident record*), in a format approved by the chief executive, within 3 days after the distribution entity is advised of the person having received the electric shock; and
 - (c) keep the incident record made under paragraph (b) for 5 years.

Maximum penalty for subsection (2)—40 penalty units.

200 Report of incident records

A distribution entity must, every 3 months, report to the chief executive, in a format approved by the chief executive, about the incident records made by the distribution entity in the 3 months.

Maximum penalty—20 penalty units.

201 Scene not to be interfered with

- (1) This section applies if a serious electrical incident or dangerous electrical event happens at a place.
- (2) A person, other than a person acting under the authority of the distribution entity for the incident or event, must not move or otherwise interfere with any electrical equipment, or part of

any electrical equipment, involved in the happening of the incident or event without the permission of—

- (a) an inspector; or
- (b) if an inspector is not available, a police officer.

Maximum penalty—40 penalty units.

- (3) A person does not commit an offence against subsection (2) if the movement or interference is necessary—
 - (a) to save life or relieve suffering; or
 - (b) to prevent injury to a person or property damage.

201A Storage of electrical equipment after serious electrical incident

- (1) This section applies if—
 - (a) a serious electrical incident happens at a place; and
 - (b) electrical equipment that is part of the works of a distribution entity is involved in the serious electrical incident.
- (2) The distribution entity must ensure that, if the equipment is removed from the place, the equipment is stored securely until—
 - (a) an inspector takes possession of the equipment; or
 - (b) an inspector gives written permission to release the equipment from storage.

Maximum penalty—40 penalty units.

202 Requirement on distribution entity to take action in interests of electrical safety

- (1) If a person has a reasonable concern about the electrical safety of electrical equipment to which a distribution entity supplies electricity, the person may advise the distribution entity of the concern.

- (2) The distribution entity must take the action necessary to be taken in the interests of the electrical safety of persons.

Maximum penalty for subsection (2)—40 penalty units.

Part 13 Miscellaneous provisions

Division 1 Electrical safety contributions

203 Context of div 1

The purpose of this division is to prescribe, for part 14, division 1¹⁸ of the Act, things that are necessary or convenient for establishing and operating arrangements for the payment of electrical safety contributions.

204 Definitions for div 1

In this division—

premises figure, for a distribution entity, means a figure that is a fair estimate of the average number of retail premises for the distribution entity for the current financial year.

total contribution amount, for the current financial year, means \$8225000.

total premises figure means the total of the premises figures for all distribution entities.

unit contribution amount means the total contribution amount divided by the total premises figure.

18 Part 14 (Miscellaneous provisions), division 1 (Electrical safety contributions) of the Act

205 Fixing electrical safety contribution for each distribution entity for current financial year

The method for working out the amount of the electrical safety contribution payable by each distribution entity for the current financial year is as follows—

- The chief executive decides the premises figure for each distribution entity.
- The chief executive works out the total premises figure.
- The chief executive works out the unit contribution amount.
- The chief executive works out the amount of the electrical safety contribution payable by each distribution entity for the current financial year by multiplying the premises figure for the distribution entity by the unit contribution amount.

206 Payment of electrical safety contribution by instalments

The electrical safety contribution for a distribution entity for the current financial year may be paid in equal instalments.

Division 2 Mines, petroleum plants and prescribed workplaces**207 Application of regulation at mine or petroleum plant**

- (1) For section 6(2)¹⁹ of the Act, the following provisions of this regulation have application at a mine or petroleum plant—
 - (a) part 1;
 - (b) part 3, other than to the extent it relates to electrical contractor licences;
 - (c) section 69;
 - (d) part 6, other than divisions 11 and 12;

19 Section 6 (Application of Act to mines and petroleum plant) of the Act

- (e) part 11;
 - (f) part 12.²⁰
- (2) For the application of part 12 at a mine or petroleum plant, a reference to a dangerous electrical event does not include a reference to a matter mentioned in section 12(a), (b) or (c)²¹ of the Act if the matter is required to be reported under the *Coal Mining Safety and Health Act 1999*, the *Mining and Quarrying Safety and Health Act 1999* or the *Petroleum and Gas (Production and Safety) Act 2004*.

207A Prescribed workplaces—Act, s 18(2)(d)

- (1) For section 18(2)(d)²² of the Act, a workplace is prescribed if—
- (a) activities of a kind stated in schedule 6A are conducted at the workplace; and
 - (b) 1 or more persons (whether an employer, self-employed person or person employed part-time or full-time) are employed in a financial year at the workplace.
- (2) Schedule 6A categorises workplaces according to the activities of persons employed at the workplaces using a system known as the Australian and New Zealand Standard Industrial Classification (*ANZSIC*).
- (3) A category of workplace stated in schedule 6A, column 2 has the ANZSIC class stated in the schedule, column 1.

20 Part 1 (Preliminary)
 Part 3 (Licensing)
 Section 69 (Work involving electric motor forming part of vehicle)
 Part 6 (Electrical equipment)
 Part 11 (Cathodic protection systems)
 Part 12 (Incident notification and reporting)

21 Section 12 (Meaning of *dangerous electrical event*) of the Act

22 Section 18 (Meaning of *electrical work*) of the Act

Division 3 Other matters

208 Climbing poles of electricity entity prohibited

- (1) A person must not climb a pole, standard or other structure that is part of the works of an electricity entity, or a ladder attached to a pole, standard or other structure that is part of the works of an electricity entity, if the electricity entity has not authorised the person to climb the pole, standard, other structure or ladder.

Maximum penalty—40 penalty units.

- (2) Subsection (1) does not apply to—
- (a) an inspector; or
 - (b) a licensed electrical contractor or licensed electrical worker who, under part 8, division 1,²³ de-energises and re-energises a consumer's electrical installation by—
 - (i) removing and replacing a fuse wedge from a service fuse; or
 - (ii) switching off and on a circuit breaker installed as a service line disconnecter.

209 Obligations of employer about supervising training person

- (1) The employer of a training person who has not finished 6 months of the person's apprenticeship or training program must ensure the training person does not work—
- (a) in the immediate vicinity of a live high voltage exposed part; or
 - (b) where there is a risk the training person could come into contact with a live low voltage exposed part.

Maximum penalty—40 penalty units.

- (1A) However, subsection (1) does not apply to a training person performing duties as a safety observer if—

23 Part 8 (Electricity supply), division 1 (Connection to source of electricity)

Electrical Safety Regulation 2002

- (a) the training person is a safety observer and has been capable of being a safety observer for at least 1 year immediately before the start of the training person's apprenticeship or training program; and
 - (b) the employer keeps a written record of the assessment mentioned in section 12, definition *safety observer*, paragraph (c) in relation to the training person.
- (2) An employer must ensure that a training person who performs electrical work is supervised at all times by a licensed electrical worker licensed to perform the work.

Maximum penalty—40 penalty units.

- (3) The level of supervision required under subsection (2) must be appropriate, having regard to—
- (a) the type of electrical work performed; and
 - (b) the adequacy of the training person's training; and
 - (c) the competency of the training person.
- (4) In this section—

safety observer see section 12(2).

training person means a person who is undertaking, but has not finished—

- (a) an apprenticeship under the *Vocational Education, Training and Employment Act 2000*, in a calling that requires the person to perform electrical work; or
- (b) a training program approved by the chief executive that requires the person to perform electrical work.

209A Electrical distribution entity may isolate powerlines in emergency

- (1) An electrical distribution entity may isolate powerlines from sources of electricity—
- (a) in an emergency; or
 - (b) to prevent an emergency from happening.

Example of paragraph (a)—

if there is a flood or fire

Example of paragraph (b)—

if there are extreme conditions with the potential to create an emergency, for example, sparking lines in high wind in high fire danger conditions

(2) In this section—

emergency means an emergency in relation to a person or the electrical distributions entity's property or other property.

210 Inspection of entries in registers

- (1) The chief executive must keep each register under this regulation open for inspection, on payment of any fixed fee applying to the inspection, by members of the public during office hours on business days.
- (2) A person may obtain a copy of an entry in a register on payment of any fixed fee applying to obtaining the copy.

210A Time for giving electrical safety undertaking

For section 49A(2)²⁴ of the Act, an electrical safety undertaking must be received by the chief executive within 90 days after the identified person for the undertaking is served with a summons in relation to the alleged contravention.

211 Provision of information by retail entity

The following information is prescribed under section 164²⁵ of the Act—

- (a) a customer's full name;
- (b) the address of the premises at which a customer receives customer retail services;
- (c) a customer's postal address and telephone number;
- (d) a contact person for a customer;

24 Section 49A (Giving electrical safety undertaking) of the Act

25 Section 164 (Provision of information by retail entity) of the Act

- (e) the date a retail entity agreed to provide customer retail services to the premises of a customer;
- (f) the location of a meter at a premises;
- (g) the number of meters at a premises;
- (h) the tariff applying to a meter at a premises;
- (i) the number of a pole or pillar used in supplying electricity to a premises;
- (j) information relevant to locating a premises or gaining access to it;
- (k) for premises that are a domestic residence—whether an approved safety switch is installed for the domestic residence.

211AA Provision of information by Residential Tenancies Authority

- (1) The Residential Tenancies Authority may, if asked, give the chief executive information, obtained by it in performing its functions, that is relevant to a person's compliance with section 80A.

Example of the information that may be given—

the address of the domestic residence

- (2) In this section—

Residential Tenancies Authority means the authority established under the *Residential Tenancies Act 1994*, section 286.

211A Person chief executive may appoint as inspector

For section 122²⁶ of the Act, the chief executive may appoint a public service officer as an inspector.

211B Fees

- (1) The fees payable under the Act are in schedule 7.

26 Section 122 (Appointment and qualifications) of the Act

- (2) Schedule 8 states the classes of types of electrical equipment for the purpose of fees.
- (3) Each type of electrical equipment mentioned in schedule 8 is as described in AS/NZS 4417.2 (Marking of electrical products to indicate compliance with regulations—Specific requirements for electrical safety regulatory applications).

Part 14 Transitional provisions

Division 1 Interpretation

212 Definitions for pt 14

In this part—

Electrical Articles Regulation means the repealed *Electricity (Electrical Articles) Regulation 1994*.

Electricity Regulation means the *Electricity Regulation 1994*.

Division 2 Transitional provisions for 2002 SL No. 260

Subdivision 1 Electrical licences

213 Equivalent licences to previous licences

- (1) This section identifies equivalent licences for previous licences for the Act, section 211, definition *equivalent licence*.
- (2) Electrical work licences are equivalent to previous licences as follows—
 - an electrical mechanic licence is the equivalent of a licence as an electrical mechanic under the *Electricity Regulation*

- an electrical linesperson licence is the equivalent of a licence as an electrical linesperson under the Electricity Regulation
 - an electrical fitter licence is the equivalent of a licence as an electrical fitter under the Electricity Regulation
 - an electrical jointer licence is the equivalent of a licence as an electrical jointer under the Electricity Regulation
 - a restricted electrical work licence is the equivalent of a restricted licence under the Electricity Regulation
 - an electrical work training permit is the equivalent of a training permit under the Electricity Regulation.
- (3) An electrical contractor licence is equivalent to an electrical contractor's licence under the Electricity Regulation.

214 Eligibility for electrical jointer licence

- (1) This section applies to a person if, immediately before the commencement of this section, the person complied with the requirements under section 46(2) or (3) of the Electricity Regulation for the issue of a licence as an electrical jointer.
- (2) The person is taken to comply with the eligibility requirements for the issue and subsequent renewal or reinstatement of an electrical jointer licence under this regulation.
- (3) This section is subject to section 221.

215 Eligibility for electrical linesperson licence

- (1) This section applies to a person if, immediately before the commencement of this section, the person complied with the requirements under section 47(2) or (3) of the Electricity Regulation for the issue of a licence as an electrical linesperson.
- (2) The person is taken to comply with the eligibility requirements for the issue and subsequent renewal or reinstatement of an electrical linesperson licence under this regulation.
- (3) This section is subject to section 222.

Subdivision 2 Matters in place before 1 October 2002

216 Registered cathodic protection system

On the commencement of this section, a cathodic protection system registered under the Electricity Regulation immediately before the commencement of this section is taken to be registered under this regulation, but only for a term that expires when its period of registration under the Electricity Regulation would have expired.

217 Approval of type of prescribed electrical article

- (1) This section applies if, immediately before the commencement of this section there is in force under the Electrical Articles Regulation an approval for a type (the *previously approved type*) of prescribed electrical article.
- (2) On the commencement of this section, there is taken to be in force an approval of the type of electrical equipment of a prescribed class of electrical equipment that is the equivalent type of the previously approved type.
- (3) The approval is for a term that expires when the period of approval for the previously approved type would have expired.

218 Clearances for lines built before 1 January 1995

- (1) This section applies to an overhead electric line built before 1 January 1995 that—
 - (a) immediately before 1 January 1995, complied with the clearance requirements of the *Electricity Regulation 1989*; and
 - (b) immediately before the commencement of this section, was continuing to comply with the clearance requirements of that regulation.
- (2) Until the line is replaced or rebuilt, the line, if it continues to comply with the clearance requirements of that regulation, is

taken to comply with clearance requirements under part 7, division 4²⁷ for overhead electric lines.

219 Termination of low voltage overhead service line built before 1 January 1995

- (1) This section applies to a low voltage overhead service line built before 1 January 1995 that—
 - (a) immediately before 1 January 1995, complied with the termination requirements of the *Electricity Regulation 1989*; and
 - (b) immediately before the commencement of this section, was continuing to comply with the termination requirements of that regulation.
- (2) Until the line is replaced or rebuilt, the line, if it continues to comply with the termination requirements of that regulation, is taken to comply with termination requirements under part 7, division 5²⁸ for low voltage overhead service lines.

220 Clearances for lines built before commencement

- (1) This section applies to an overhead electric line built on or after 1 January 1995 but before the commencement of this section that—
 - (a) immediately before the commencement, complied with the clearance requirements of the *Electricity Regulation*; and
 - (b) would still be in compliance with the clearance requirements of the *Electricity Regulation* if the requirements were still in force.
- (2) Until the line is replaced or rebuilt, the line is taken to comply with clearance requirements under part 7, division 4 for overhead electric lines.

27 Part 7 (Works of an electricity entity), division 4 (Electric lines and control cables)

28 Part 7 (Works of an electricity entity), division 5 (Termination requirements for low voltage overhead service lines)

**Division 3 Transitional provisions for Electrical
Safety and Another Regulation
Amendment Regulation (No. 1) 2007**

221 Further provision for electrical jointer licences

- (1) This section applies to a person mentioned in section 214 if, immediately before 1 October 2002—
 - (a) the person complied with the requirements under section 46(3) of the Electricity Regulation for the issue of a licence as an electrical jointer; and
 - (b) for section 46(3)(a) of the Electricity Regulation, the person had been employed outside Queensland, but not in Australia, as an electrical jointer for at least 2 years.
- (2) Section 214(2) stops applying to the person on the commencement of this section.
- (3) Despite subsection (2), section 214(2) continues to apply to the person if, immediately before the commencement, the person—
 - (a) held a licence as an electrical jointer; or
 - (b) had applied for the issue, renewal or reinstatement of a licence as an electrical jointer.

222 Further provision for electrical linesperson licences

- (1) This section applies to a person mentioned in section 215 if, immediately before 1 October 2002—
 - (a) the person complied with the requirements under section 47(3) of the Electricity Regulation for the issue of a licence as an electrical linesperson; and
 - (b) for section 47(3)(a) of the Electricity Regulation, the person had been employed outside Queensland, but not in Australia, as an electrical linesperson for at least 2 years.
- (2) Section 215(2) stops applying to the person on the commencement of this section.

Electrical Safety Regulation 2002

- (3) Despite subsection (2), section 215(2) continues to apply to the person if, immediately before the commencement, the person—
- (a) held a licence as an electrical linesperson; or
 - (b) had applied for the issue, renewal or reinstatement of a licence as an electrical linesperson.

Schedule 1 External licences and electrical work licence equivalents

section 32

External licence	Equivalent licence
New South Wales	
Under the <i>Home Building Act 1989</i> (NSW)—	
• Qualified supervisor certificate—electrician (endorsed <i>Q</i>)	electrical mechanic licence
• Qualified supervisor certificate—electrical	electrical mechanic licence
Victoria	
Under the <i>Electricity Safety Act 1998</i> (Vic)—	
• Electrician’s licence	electrical mechanic licence
South Australia	
Under the <i>Plumbers, Gas Fitters and Electricians Act 1995</i> (SA)—	
• Electrical workers registration—any electrical work	electrical mechanic licence
Tasmania	
Under the <i>Electricity Industry Safety and Administration Act 1997</i> (Tas)—	
• Electrical technician’s licence	electrical mechanic licence
• Electrician’s licence	electrical mechanic licence
Western Australia	
Under the <i>Electricity Act 1945</i> (WA)—	
• “A” grade electrical workers’ licence—endorsed ‘all electrical work’	electrical mechanic licence

Schedule 1 (continued)

External licence	Equivalent licence
<ul style="list-style-type: none"> • “A” grade electrical workers’ licence—endorsed electrical mechanic 	electrical mechanic licence
<ul style="list-style-type: none"> • “A” grade electrical workers’ licence—endorsed electrical mechanic and electrical fitter 	electrical mechanic licence
<ul style="list-style-type: none"> • “A” grade electrical workers’ licence—endorsed electrical fitter 	electrical fitter licence
 Australian Capital Territory	
Under the <i>Construction Occupations (Licensing) Act 2004</i> (ACT)—	
<ul style="list-style-type: none"> • Unrestricted electrician licence 	electrical mechanic licence
 Northern Territory	
Under the <i>Electrical Workers and Contractors Act</i> (NT)—	
<ul style="list-style-type: none"> • Electrical workers’ licence endorsed electrical mechanic 	electrical mechanic licence
<ul style="list-style-type: none"> • Electrical workers’ licence endorsed electrical fitter and mechanic 	electrical mechanic licence
<ul style="list-style-type: none"> • Electrical workers’ licence endorsed electrical fitter 	electrical fitter licence
 New Zealand	
Under the <i>Electricity Act 1992</i> (NZ)—	
<ul style="list-style-type: none"> • Practising licence for registered electrician 	electrical mechanic licence

Schedule 2 Exclusion zones for electrical parts

section 61

Part 1 Exclusion zones for exposed parts for untrained persons and for operating plant and vehicles operated by untrained persons

Nominal phase to phase voltage of exposed part	Untrained person for the exposed part (mm)	Operating plant operated by untrained person for the exposed part (mm)	Vehicle operated by untrained person for the exposed part (mm)
Low voltage (with consultation with person in control of exposed part)	1 000	3 000	600
Low voltage (without consultation with person in control of exposed part)	3 000	3 000	600
Above low voltage, up to 33kV (with consultation with person in control of exposed part)	2 000	3 000	900
Above low voltage, up to 33kV (without consultation with person in control of exposed part)	3 000	3 000	900

Schedule 2 (continued)

Nominal phase to phase voltage of exposed part	Untrained person for the exposed part (mm)	Operating plant operated by untrained person for the exposed part (mm)	Vehicle operated by untrained person for the exposed part (mm)
Above 33kV up to 50kV	3 000	3 000	2 100
Above 50kV up to 66kV	3 000	3 000	2 100
Above 66kV up to 110kV	3 000	3 000	2 100
Above 110kV up to 132kV	3 000	3 000	2 100
Above 132kV up to 220kV	4 500	6 000	2 900
Above 220kV up to 275kV	5 000	6 000	2 900
Above 275kV up to 330kV	6 000	6 000	3 400
Above 330kV up to 400kV	6 000	8 000	4 400
Above 400kV up to 500kV	6 000	8 000	4 400
Nominal pole to earth dc voltage of exposed part			
+/- 25kV	3 000	3 000	900
+/- 85kV	3 000	3 000	2 100
+/- 150kV	3 000	3 000	2 100
+/- 270kV	4 500	6 000	2 900
+/- 350kV	5 000	6 000	2 900
+/- 400kV	6 000	6 000	3 400

Schedule 2 (continued)

Part 2**Exclusion zones for exposed parts for authorised and instructed persons and for operating plant and vehicles operated by authorised or instructed persons**

Nominal phase to phase voltage of exposed part	Authorised person or instructed person for the exposed part (mm)	Operating plant operated by authorised person or instructed person for the exposed part, with safety observer or another safe system (mm)	Vehicle operated by authorised person or instructed person for the exposed part (mm)
Low voltage (with consultation with person in control of exposed part)	(No exclusion zone prescribed)	1 000	600
Low voltage (without consultation with person in control of exposed part)	(No exclusion zone prescribed)	1 000	600
Above low voltage, up to 33kV (with consultation with person in control of exposed part)	700	1 200	700
Above low voltage, up to 33kV (without consultation with person in control of exposed part)	700	1 200	700

Schedule 2 (continued)

Nominal phase to phase voltage of exposed part	Authorised person or instructed person for the exposed part (mm)	Operating plant operated by authorised person or instructed person for the exposed part, with safety observer or another safe system (mm)	Vehicle operated by authorised person or instructed person for the exposed part (mm)
Above 33kV up to 50kV	750	1 300	750
Above 50kV up to 66kV	1 000	1 400	1 000
Above 66kV up to 110kV	1 000	1 800	1 000
Above 110kV up to 132kV	1 200	1 800	1 200
Above 132kV up to 220kV	1 800	2 400	1 800
Above 220kV up to 275kV	2 300	3 000	2 300
Above 275kV up to 330kV	3 000	3 700	3 000
Above 330kV up to 400kV	3 300	4 000	3 300
Above 400kV up to 500kV	3 900	4 600	3 900

Schedule 2 (continued)

Nominal pole to earth dc voltage of exposed part	Authorised person or instructed person for the exposed part (mm)	Operating plant operated by authorised person or instructed person for the exposed part, with safety observer or another safe system (mm)	Vehicle operated by authorised person or instructed person for the exposed part (mm)
+/- 25kV	700	1 200	700
+/- 85kV	1 000	1 800	1 000
+/- 150kV	1 200	1 800	1 200
+/- 270kV	1 800	2 400	1 800
+/- 350kV	2 500	3 200	2 500
+/- 400kV	2 900	3 600	2 900

Part 3

Exclusion zones for low voltage overhead insulated electric line for untrained persons and for operating plant or vehicles operated by untrained persons

Low voltage overhead insulated electric line	Untrained person (mm)	Operating plant operated by untrained person for the electric line (mm)	Vehicle operated by untrained person for the electric line (mm)
With consultation with, and with insulation verified by, an authorised person for the electric line	(No exclusion zone prescribed)	1 000	300

Schedule 2 (continued)

Low voltage overhead insulated electric line	Untrained person (mm)	Operating plant operated by untrained person for the electric line (mm)	Vehicle operated by untrained person for the electric line (mm)
Without consultation with, and without insulation verified by, an authorised person for the electric line	3 000	3 000	600

Part 4

Exclusion zones for low voltage overhead insulated electric line for authorised or instructed persons and for operating plant or vehicles operated by authorised or instructed persons

Low voltage overhead insulated electric line	Authorised person or instructed person for the electric line (mm)	Operating plant operated by authorised person or instructed person for the electric line, with safety observer or another safe system (mm)	Vehicle operated by authorised person or instructed person for the electric line (mm)
With consultation with, and with insulation verified by, an authorised person for the electric line	(No exclusion zone prescribed)	(No exclusion zone prescribed)	(No exclusion zone prescribed)

Schedule 2 (continued)

Low voltage overhead insulated electric line	Authorised person or instructed person for the electric line (mm)	Operating plant operated by authorised person or instructed person for the electric line, with safety observer or another safe system (mm)	Vehicle operated by authorised person or instructed person for the electric line (mm)
Without consultation with, and without insulation verified by, an authorised person for the electric line	(No exclusion zone prescribed)	(No exclusion zone prescribed)	600

Part 5

Exclusion zones for high voltage overhead insulated electric line for untrained persons and for operating plant or vehicles operated by untrained persons

Nominal phase to phase voltage of high voltage overhead insulated electric line	Untrained person for the electric line (mm)	Operating plant operated by untrained person for the electric line (mm)	Vehicle operated by untrained person for the electric line (mm)
Above low voltage, up to 33kV (with consultation with person in control of electric line)	2 000	3 000	900

Schedule 2 (continued)

Nominal phase to phase voltage of high voltage overhead insulated electric line	Untrained person for the electric line (mm)	Operating plant operated by untrained person for the electric line (mm)	Vehicle operated by untrained person for the electric line (mm)
Above low voltage, up to 33kV (without consultation with person in control of electric line)	3 000	3 000	900
Above 33kV up to 50kV	3 000	3 000	2 100
Above 50kV up to 66kV	3 000	3 000	2 100
Nominal pole to earth dc voltage of electric line			
+/- 25kV	3 000	3 000	900
+/- 85kV	3 000	3 000	2 100

Schedule 2 (continued)

Part 6**Exclusion zones for high voltage overhead insulated electric line for authorised and instructed persons and for operating plant and vehicles operated by authorised or instructed persons**

Nominal phase to phase voltage of high voltage overhead insulated electric line	Authorised person or instructed person for electric line (mm)	Operating plant operated by authorised person or instructed person for electric line, with safety observer or another safe system (mm)	Vehicle operated by authorised person or instructed person for electric line (mm)
Above low voltage, up to 33kV (with consultation with person in control of electric line)	700	700	700
Above low voltage, up to 33kV (without consultation with person in control of electric line)	700	700	700
Above 33kV up to 50kV	750	750	750

Schedule 2 (continued)

Nominal phase to phase voltage of high voltage overhead insulated electric line	Authorised person or instructed person for electric line (mm)	Operating plant operated by authorised person or instructed person for electric line, with safety observer or another safe system (mm)	Vehicle operated by authorised person or instructed person for electric line (mm)
Above 50kV up to 66kV	1 000	1 000	1 000
Nominal pole to earth dc voltage of electric line			
+/- 25kV	700	700	700
+/- 85kV	1 000	1 000	1 000

Schedule 3 Prescribed classes of electrical equipment and relevant standards

sections 96 and 97

Prescribed classes of electrical equipment	Relevant standard
1 Appliance connector	AS/NZS 3109 (Appliance couplers for household and similar general purposes)
2 Arc welding machine	AS/NZS 3195 (Portable machines for electric arc welding and allied processes)
3 Battery charger—automotive type	AS/NZS 3350.2.29 (Particular requirements for battery chargers)
4 Battery charger—general type	AS/NZS 3350.2.29 (Particular requirements for battery chargers) AS/NZS 60065 (Audio, video and similar electronic apparatus—Safety requirements) AS/NZS 60950 (Safety of information technology equipment)
5 Bayonet lampholder	AS 3117 (Bayonet lampholder)
6 Bayonet lampholder adaptor	AS 3119 (Normal bayonet lampholder adaptor)
7 Blanket	AS 3350.2.17 (Particular requirements—Blankets, pads and similar flexible heating appliances)
8 Bread toaster	AS/NZS 3350.2.9 (Particular requirements—Grills, toasters and similar portable cooking appliances)

Schedule 3 (continued)

Prescribed classes of electrical equipment	Relevant standard
9 Clothes dryer	AS/NZS 3350.2.11 (Particular requirements for tumble dryers) AS/NZS 3350.2.43 (Particular requirements for clothes dryers and towel rails)
10 Control or conditioning device	AS/NZS 3197 (Portable electrical control or conditioning device)
11 Cooking appliance—portable type	AS/NZS 3350.2.9 (Particular requirements—Grills, toasters, and similar portable cooking appliances) AS/NZS 3350.2.12 (Particular requirements—Warming plates and similar appliances) AS/NZS 3350.2.13 (Particular requirements for deep fat fryers, frying pans and similar appliances)
12 Cord extension socket	AS/NZS 3120 (Cord extension sockets)
13 Cord-line switch	AS/NZS 3127 (Cord-line switches)
14 Decorative lighting outfit	AZ/NZS 3152 (Decorative lighting outfits) AS/NZS 60598.2.20 (Particular requirements—Lighting chains)
15 Dishwashing machine	AS/NZS 3350.2.5 (Particular requirements—Dishwashers)
16 Edison screw lampholder	AS 3140 (Edison-type screw lampholders)

Schedule 3 (continued)

Prescribed classes of electrical equipment	Relevant standard
17 Extra-low voltage power supply unit	AS/NZS 3108 (Particular requirements for isolating transformers and safety isolating transformers) AS/NZS 61558 (Safety of power transformers, power supply units and similar) AS/NZS 60065 (Audio, video and similar electronic apparatus—Safety requirements) AS/NZS 60950 (Safety of information technology equipment)
18 Fan	AS/NZS 3350.2.80 (Particular requirements—Electric fans)
19 Fence energiser	AS/NZS 3350.2.76 (Particular requirements—Electric fence energizers)
20 Flexible heating pad	AS/NZS 3350.2.17 (Particular requirements—Blankets, pads and similar flexible heating appliances)
21 Floor polisher/scrubber	AS/NZS 3350.2.10 (Particular requirements—Floor treatment machines and wet scrubbing machines)
22 Fluorescent lamp ballast	AS/NZS 60928 (Auxiliaries for lamps—A.C. supplied electronic ballasts for tubular fluorescent lamps—General and safety requirements) AS/NZS 3134 (A.C. supplied electronic ballasts for tubular fluorescent lamps) AS 3168 (Fluorescent lamp ballasts)
23 Fluorescent lamp starter	AS/NZS 60155 (Glow-starters for fluorescent lamps)
24 Hair care appliance	AS/NZS 3350.2.23 (Particular requirements for appliances for skin and hair care)

Schedule 3 (continued)

Prescribed classes of electrical equipment	Relevant standard
25 Hedge clipper	AS/NZS 3160 (Hand-held portable electric tools)
26 Immersion heater	AS/NZS 3350.2.74 (Particular requirements for portable immersion heaters) AS/NZS 3350.2.55 (Particular requirements—Electrical appliances for use with aquariums and garden ponds) AS/NZS 3350.2.73 (Particular requirements—Fixed immersion heaters)
27 Insect electrocutor	AS/NZS 3350.2.59 (Particular requirements—Insect killers)
28 Inspection handlamp	AS/NZS 3118 (Electric inspection handlamp) AS/NZS 60598.2.8 (Particular requirements—Handlamps)
29 Iron	AS/NZS 3350.2.3 (Particular requirements—Electric irons) AS/NZS 3350.2.85 (Particular requirements—Fabric steamers)
30 Kitchen machine	AS/NZS 3350.2.14 (Particular requirements—Kitchen machines)
31 Lawn care appliance	AS/NZS 3156 (Electric lawnmowers) AS/NZS 3160 (Hand-held portable electric tools)
32 Liquid heating appliance	AS/NZS 3350.2.15 (Particular requirements for appliances for heating liquids) AS/NZS 3350.2.98 (Particular requirements—Humidifiers) AS 3106 (Electric jugs with non-metallic bodies)

Schedule 3 (continued)

Prescribed classes of electrical equipment	Relevant standard
33 Luminaire—portable type	AS/NZS 3128 (Portable lamp standards and brackets) AS/NZS 60598.2.4 (Particular requirements—Portable general purpose luminaries) AS/NZS 60598.2.10 (Particular requirements—Portable child-appealing luminaries)
34 Massage appliance	AS/NZS 3350.2.32 (Particular requirements for massage appliances)
35 Microwave oven	AS/NZS 3350.2.25 (Particular requirements for microwave ovens)
36 Miniature overcurrent circuit-breaker	AS 3111 (Miniature overcurrent circuit-breakers) AS/NZS 4898 (Circuit-breakers for overcurrent protection for household and similar installations) AS/NZS 61009 (Residual current operated circuit-breakers with integral overcurrent protection for household and similar uses (RCBOs))
37 Outlet device	AS/NZS 3122 (Socket-outlet adaptors) AS/NZS 3105 (Electrical portable outlet devices)
38 Plug	AS/NZS 3112 (Plugs and socket-outlet)
39 Projector	AS/NZS 3350.2.56 (Particular requirements—Projectors and similar appliances)
40 Range	AS/NZS 3350.2.6 (Particular requirements for stationary cooking ranges, hobs, ovens and similar appliances)

Schedule 3 (continued)

Prescribed classes of electrical equipment	Relevant standard
41 Range hood	AS/NZS 3350.2.31 (Particular requirements for range hoods)
42 Razor/hair clipper	AS/NZS 3350.2.8 (Particular requirements—Shavers, hair clippers and similar appliances)
43 Refrigerating appliance	AS/NZS 3350.2.24 (Particular requirements for refrigerating appliances, ice-cream appliances and ice-makers)
44 Residual current device	AS/NZS 3190 (Residual current devices (current-operated earth-leakage devices)) AS/NZS 3175 (Residual current-operated circuit-breakers without integral overcurrent protection for household and similar uses (RCCBs)) AS/NZS 61009 (Residual current operated circuit-breakers with integral overcurrent protection for household and similar uses (RCBOs))
45 Room heater	AS/NZS 3350.2.30 (Particular requirements—Room heaters) AS/NZS 3350.2.61 (Particular requirements for thermal storage room heaters)
46 Sewing machine	AS/NZS 3350.2.28 (Particular requirements—sewing machines)
47 Socket outlet	AS/NZS 3112 (Plugs and socket-outlets)
48 Soldering-iron	AS/NZS 3350.2.45 (Particular requirements—Portable heating tools and similar appliances)
49 Supply flexible cord	AS/NZS 3191 (Electric flexible cords)

Schedule 3 (continued)

Prescribed classes of electrical equipment	Relevant standard
50 Swimming pool/spa equipment	AS/NZS 3136 (Electrical equipment for spa and swimming pools) AS/NZS 3350.2.41 (Particular requirements—Pumps) AS/NZS 3350.2.60 (Particular requirements—Whirlpool baths)
51 Television receiver	AS/NZS 60065 (Audio, video and similar electronic apparatus—safety requirements)
52 Therapeutic lamp	AS/NZS 3350.2.27 (Particular requirements—Appliances for skin exposure to ultraviolet and infrared radiation)
53 Tool—portable type	AS/NZS 3160 (Hand-held portable electric tools) AS/NZS 7450 (Safety of hand-held motor operated electric tools)
57 Vacuum cleaner	AS/NZS 3350.2.2 (Particular requirements for vacuum cleaners and water suction cleaning appliances)
58 Wall switch	AS 3133 (Air break switches)
59 Washing machine	AS/NZS 3350.2.7 (Particular requirements for washing machines)
60 Waterbed heater	AS/NZS 3350.2.66 (Particular requirements—Water-bed heaters)
61 Water heater	AS/NZS 3350.2.21 (Particular requirements—Storage water heaters) AS/NZS 3350.2.35 (Particular requirements—Instantaneous water heaters)

Schedule 4 Clearance of overhead electric lines (other than low voltage service lines)

sections 139 and 140

Part 1 Low voltage conductor clearance—from ground

Vertical clearance from roads

- 1 The minimum vertical clearance from roads must be—
- (a) crossing the carriageway—
 - (i) insulated. 5.5m
 - (ii) uninsulated. 5.5m
 - (b) at other positions—
 - (i) insulated. 5.5m
 - (ii) uninsulated. 5.5m

Vertical clearance from other than roads

- 2(1) The minimum vertical clearance from other than roads must be—
- (a) insulated. 5.5m
 - (b) uninsulated. 5.5m
- (2) This item does not apply if item 3 or 4 applies.

Vertical clearance over nontrafficable land

- 3 The minimum vertical clearance over land that, because of the steepness or swampiness of its terrain, can not be crossed by traffic or mobile machinery must be—
- (a) insulated. 4.5m
 - (b) uninsulated. 4.5m

Schedule 4 (continued)**Horizontal clearance from road cuttings and embankments**

- 4 The minimum horizontal clearance, in accordance with note 2, from road cuttings, embankments and similar features must be—
- | | |
|--------------------------|------|
| (a) insulated. | 1.5m |
| (b) uninsulated. | 1.5m |

Part 2 Low voltage conductor clearance—from structures

Clearance from unroofed terraces, balconies and sun decks

- 1 The minimum clearance, in accordance with note 2, for unroofed terraces, balconies, sun decks, paved areas and similar areas that are subject to pedestrian traffic only, that have a surrounding hand rail or wall and on which a person is likely to stand must be—
- | | |
|---------------------------|------|
| (a) vertically— | |
| (i) insulated. | 2.7m |
| (ii) uninsulated. | 3.7m |
| (b) horizontally— | |
| (i) insulated. | 1.2m |
| (ii) uninsulated. | 1.5m |

Clearance from roofs or similar structures not used for traffic

- 2 The minimum clearance vertically and horizontally, in accordance with note 2, for roofs or similar structures not used for traffic or resort but on which a person is likely to stand, and for parapets surrounding roofs or similar structures not used for traffic or resort but on which a person is likely to stand, must be—

Schedule 4 (continued)

(a) vertically—	
(i) insulated.....	2.7m
(ii) uninsulated.....	3.7m
(b) horizontally—	
(i) insulated.....	0.9m
(ii) uninsulated.....	1.5m

Clearance from covered places of traffic

3	The minimum clearance in any direction from covered places of traffic or resort, including for example, windows capable of being opened, roofed open verandahs and covered balconies, must be—	
	(a) insulated.....	1.2m
	(b) uninsulated.....	1.5m

Horizontal clearance from blank walls or windows

4	The minimum clearance horizontally from blank walls or windows that can not be opened must be—	
	(a) insulated.....	0.6m
	(b) uninsulated.....	1.5m

Clearance from structures not normally accessible to persons

5	The minimum clearance from other structures not normally accessible to persons must be, in accordance with note 2—	
	(a) vertically—	
	(i) insulated.....	0.6m
	(ii) uninsulated.....	2.7m
	(b) horizontally—	
	(i) insulated.....	0.3m
	(ii) uninsulated.....	1.5m

Schedule 4 (continued)

Part 3 High voltage conductor clearance—from ground

Vertical clearance from roads

- 1 The minimum vertical clearance from roads must be—
- | | |
|--|------|
| (a) crossing the carriageway— | |
| (i) more than 1000V but not more than 33kV | 6.7m |
| (ii) more than 33kV but not more than 66kV | 6.7m |
| (iii) more than 66kV but not more than 132kV | 6.7m |
| (iv) more than 132kV but not more than 275kV . . . | 7.5m |
| (v) more than 275kV but not more than 330kV . . . | 8.0m |
| (vi) more than 330kV but not more than 500kV . . . | 9.0m |
| (b) at other places— | |
| (i) more than 1000V but not more than 33kV | 5.5m |
| (ii) more than 33kV but not more than 66kV | 6.7m |
| (iii) more than 66kV but not more than 132kV | 6.7m |
| (iv) more than 132kV but not more than 275kV . . . | 7.5m |
| (v) more than 275kV but not more than 330kV . . . | 8.0m |
| (vi) more than 330kV but not more than 500kV . . . | 9.0m |

Vertical clearance from other than roads

- 2(1) The minimum vertical clearance from other than roads must be—
- | | |
|---|------|
| (a) more than 1000V but not more than 33kV | 5.5m |
| (b) more than 33kV but not more than 66kV | 6.7m |
| (c) more than 66kV but not more than 132kV | 6.7m |
| (d) more than 132kV but not more than 275kV | 7.5m |
| (e) more than 275kV but not more than 330kV | 8.0m |
| (f) more than 330kV but not more than 500kV | 9.0m |
- (2) This item does not apply if item 3 or 4 applies.

Schedule 4 (continued)**Vertical clearance over nontrafficable land**

- 3 The minimum vertical clearance over land that, because of the steepness or swampiness of its terrain, can not be crossed by traffic or mobile machinery must be—
- | | |
|---|------|
| (a) more than 1000V but not more than 33kV | 4.5m |
| (b) more than 33kV but not more than 66kV | 5.5m |
| (c) more than 66kV but not more than 132kV | 5.5m |
| (d) more than 132kV but not more than 275kV | 6.0m |
| (e) more than 275kV but not more than 330kV | 6.7m |
| (f) more than 330kV but not more than 500kV | 7.5m |

Horizontal clearance from road cuttings and embankments etc.

- 4 The minimum horizontal clearance, in accordance with note 2, from road cuttings, embankments and other similar places must be—
- | | |
|---|------|
| (a) more than 1000V but not more than 33kV | 2.1m |
| (b) more than 33kV but not more than 66kV | 4.6m |
| (c) more than 66kV but not more than 132kV | 4.6m |
| (d) more than 132kV but not more than 275kV | 5.5m |
| (e) more than 275kV but not more than 330kV | 6.0m |
| (f) more than 330kV but not more than 500kV | 7.0m |

Part 4 High voltage conductor clearance—from structures

Clearance from unroofed terraces, balconies and sun decks

- 1 The minimum clearance, in accordance with note 2, for unroofed terraces, balconies, sun decks, paved areas and similar areas that are subject to pedestrian traffic only, that have a surrounding hand rail or wall and on which a person is likely to stand, must be—

Schedule 4 (continued)

(a) vertically—	
(i) more than 1000V but not more than 33kV . . .	4.6m
(ii) more than 33kV but not more than 66kV	5.5m
(iii) more than 66kV but not more than 132kV . . .	5.5m
(iv) more than 132kV but not more than 275kV . .	6.5m
(v) more than 275kV but not more than 330kV . .	7.0m
(vi) more than 330kV but not more than 500kV . .	8.0m
(b) horizontally—	
(i) more than 1000V but not more than 33kV . . .	2.1m
(ii) more than 33kV but not more than 66kV	4.6m
(iii) more than 66kV but not more than 132kV . . .	4.6m
(iv) more than 132kV but not more than 275kV . .	5.5m
(v) more than 275kV but not more than 330kV . .	5.5m
(vi) more than 330kV but not more than 500kV . .	6.0m

Clearance from roofs or similar structures not used for traffic

2 The minimum clearance vertically and horizontally, in accordance with note 2, for roofs or similar structures not used for traffic or resort but on which a person is likely to stand, and for parapets surrounding roofs or similar structures not used for traffic or resort but on which a person is likely to stand, must be—

(a) vertically—	
(i) more than 1000V but not more than 33kV . . .	3.7m
(ii) more than 33kV but not more than 66kV	4.6m
(iii) more than 66kV but not more than 132kV . . .	4.6m
(iv) more than 132kV but not more than 275kV . .	6.0m
(v) more than 275kV but not more than 330kV . .	6.5m
(vi) more than 330kV but not more than 500kV . .	7.5m
(b) horizontally—	
(i) more than 1000V but not more than 33kV . . .	2.1m
(ii) more than 33kV but not more than 66kV	4.6m
(iii) more than 66kV but not more than 132kV . . .	4.6m

Schedule 4 (continued)

(iv) more than 132kV but not more than 275kV . .	5.5m
(v) more than 275kV but not more than 330kV . .	5.5m
(vi) more than 330kV but not more than 500kV . .	6.0m

Clearance from covered places of traffic

- 3 The minimum clearance in any direction from covered places of traffic or resort such as windows capable of being opened, roofed open verandahs and covered balconies must be—
- | | |
|---|------|
| (a) more than 1000V but not more than 33kV | 2.1m |
| (b) more than 33kV but not more than 66kV | 4.6m |
| (c) more than 66kV but not more than 132kV | 4.6m |
| (d) more than 132kV but not more than 275kV | 5.5m |
| (e) more than 275kV but not more than 330kV | 5.5m |
| (f) more than 330kV but not more than 500kV | 6.0m |

Horizontal clearance from blank walls or windows

- 4 The minimum clearance horizontally from blank walls or windows that can not be opened must be—
- | | |
|---|------|
| (a) more than 1000V but not more than 33kV | 1.5m |
| (b) more than 33kV but not more than 66kV | 3.0m |
| (c) more than 66kV but not more than 132kV | 4.6m |
| (d) more than 132kV but not more than 275kV | 5.5m |
| (e) more than 275kV but not more than 330kV | 5.5m |
| (f) more than 330kV but not more than 500kV | 6.0m |

Clearance from structures not normally accessible to persons

- 5 The minimum clearance from other structures not normally accessible to persons must be, in accordance with note 2—
- | | |
|--|------|
| (a) vertically— | |
| (i) more than 1000V but not more than 33kV . . . | 3.0m |
| (ii) more than 33kV but not more than 66kV . . . | 3.0m |

Schedule 4 (continued)

(iii) more than 66kV but not more than 132kV . . .	4.6m
(iv) more than 132kV but not more than 275kV ..	5.5m
(v) more than 275kV but not more than 330kV ..	5.5m
(vi) more than 330kV but not more than 500kV ..	6.0m
(b) horizontally—	
(i) more than 1000V but not more than 33kV . . .	1.5m
(ii) more than 33kV but not more than 66kV	3.0m
(iii) more than 66kV but not more than 132kV . . .	4.6m
(iv) more than 132kV but not more than 275kV ..	5.5m
(v) more than 275kV but not more than 330kV ..	5.5m
(vi) more than 330kV but not more than 500kV ..	6.0m

Note 1—

For this schedule, a conductor is taken to be insulated if it is insulated in accordance with AS/NZS 5000.1 (Electric cables—Polymeric insulated—For working voltages up to and including 0.6/1 (1.2) kV) or AS/NZS 3560.1 (Electric cables—Cross-linked polyethylene insulated—Aerial bundled—For working voltages up to and including 0.6/1(1.2)kV). Otherwise, it is taken to be uninsulated.

Note 2—

Either the vertical clearance or the horizontal clearance stated must be maintained. Also, in the zone outside the vertical alignment of the building, road cutting, embankments and similar places, either the horizontal clearance from the vertical alignment or the vertical clearance from the horizontal level on which a person is likely to stand must be maintained.

Schedule 5 Clearance of low voltage overhead service lines

sections 139 and 140

Part 1 Clearance from ground

Vertical clearance from roads

- 1 The minimum vertical clearance from roads must be—
- | | |
|---|------|
| (a) at centre line of the carriageway | 5.5m |
| (b) at kerb line | 4.9m |
| (c) at fence alignment | 3.7m |

Vertical clearance from other than roads

- 2 The minimum vertical clearance from other than roads must be—
- | | |
|---|------|
| (a) private driveways and areas including elevated areas used by vehicles | 4.5m |
| (b) areas not normally used by vehicles | 2.7m |

Horizontal clearance from road cuttings and embankments

- 3 The minimum horizontal clearance from road cuttings, embankments and other similar places . . .
- | | |
|--|------|
| | 1.5m |
|--|------|

Schedule 5 (continued)

Part 2 Clearance from structures**Clearance from unroofed terraces, balconies and sun decks**

- 1 The minimum clearance, in accordance with note 1, for unroofed terraces, balconies, sun decks, paved areas and similar areas that are subject to pedestrian traffic only, that have a hand rail or wall surrounding the area and on which a person is likely to stand (see note 2) must be—
- | | |
|--------------------------------|------|
| (a) vertically above | 2.4m |
| (b) vertically below | 1.2m |
| (c) horizontally | 0.9m |

Clearance from roofs or similar structures not used for traffic

- 2 The minimum clearance, in accordance with note 1, for roofs or similar structures not used for traffic or resort but on which a person is likely to stand, and for parapets surrounding roofs or similar structures not used for traffic or resort but on which a person is likely to stand (see note 2), must be—
- | | |
|----------------------------|------|
| (a) vertically | 0.5m |
| (b) horizontally | 0.2m |

Clearance from covered places of traffic

- 3 The minimum clearance in any direction from covered places of traffic or resort, including, for example, windows capable of being opened, roofed open verandahs and covered balconies, must be . . .
- | | |
|--|------|
| | 1.2m |
|--|------|

Horizontal clearance from blank walls or windows

- 4 The minimum clearance horizontally from blank walls or windows that can not be opened (see note 2) must be
- | | |
|--|------|
| | 0.2m |
|--|------|

Schedule 5 (continued)**Clearance from structures not normally accessible to persons**

- 5 The minimum clearance in any direction from other structures not normally accessible to persons must be, in accordance with note 2 1.2m

Note 1—

Either the vertical clearance or the horizontal clearance stated must be maintained. Also, in the zone outside the vertical alignment of the building or structure, either the horizontal clearance from the vertical alignment or the vertical clearance above the horizontal level on which a person is likely to stand must be maintained.

Note 2—

The clearance stated applies for the service line not attached to the part of the building described.

Note 3—

The clearance stated does not apply to the part of a low voltage overhead service line not under tension.

Schedule 6 Prescribed electricity entities

section 165

Part 1 Original prescribed electricity entities

- Comalco Aluminium Limited (ABN 51 009 679 127)
- Country Energy (ABN 37 428 185 226)
- Energex Limited (ABN 40 078 849 055)
- Ergon Energy Corporation Limited (ABN 50 087 646 062)
- Powerlink Queensland (ABN 82 078 849 233)
- QR (ABN 47 564 947 264)

Part 2 Later prescribed electricity entities

- *[No electricity entities prescribed]*

Schedule 6A Prescribed workplaces

section 207A

Column 1	Column 2
2811	Motor vehicle manufacturing
2812	Motor vehicle body manufacturing
2813	Automotive electrical and instrument manufacturing
2819	Automotive component manufacturing N.E.C.
2821	Shipbuilding
2822	Boatbuilding
2823	Railway equipment manufacturing
2824	Aircraft manufacturing
2829	Transport equipment manufacturing N.E.C.
2832	Medical and surgical equipment manufacturing
2839	Professional and scientific equipment manufacturing N.E.C.
2841	Computer and business machine manufacturing
2842	Telecommunication, broadcasting and transceiving equipment manufacturing
2849	Electronic equipment manufacturing N.E.C.
2851	Household appliance manufacturing
2852	Electric cable and wire manufacturing
2853	Battery manufacturing
2854	Electric light and sign manufacturing
2859	Electrical equipment manufacturing N.E.C.
2862	Mining and construction machinery manufacturing
2863	Food processing machinery manufacturing
2864	Machine tool and part manufacturing

Schedule 6A (continued)

Column 1	Column 2
2865	Lifting and material handling equipment manufacturing
2866	Pump and compressor manufacturing
2867	Commercial space heating and cooling equipment manufacturing
2869	Industrial machinery and equipment manufacturing N.E.C.
2911	Prefabricated metal building manufacturing
2919	Prefabricated building manufacturing N.E.C.
5261	Household equipment repair services (Electrical)
7810	Scientific research

Schedule 7 Fees

section 211B

\$

Electrical work licence

1	Application for electrical work licence	55.50
2	Application for renewal of electrical work licence	55.50
3	Application for reinstatement of electrical work licence. . .	55.50
4	Administration component of fee paid for an application under item 1, 2 or 3 refundable under section 55	27.70

Electrical contractor licence

5	Application for electrical contractor licence	267.15
6	Application for renewal of electrical contractor licence . . .	267.15
7	Application for reinstatement of electrical contractor licence	267.15
8	Administration component of fee paid for an application under item 5, 6 or 7 refundable under section 55	211.40

Electrical equipment

9	Application for approval, or renewal of approval, of a type of electrical equipment of a prescribed class of electrical equipment—	
	• class 1 electrical equipment.	306.20
	• class 2 electrical equipment.	428.60
	• class 3 electrical equipment.	612.40
10	Administration component of fee paid for an application under item 9 refundable under section 126A.	nil
11	Application for an extension under section 103A of an approval of a type of electrical equipment of a prescribed class of electrical equipment—	
	• class 1 electrical equipment.	79.40
	• class 2 electrical equipment.	79.40
	• class 3 electrical equipment.	79.40

Schedule 7 (continued)

	\$
12 Administration component of fee paid for an application under item 11 refundable under section 126A.	nil
13 Application to change the approval of a type of electrical equipment—	
(a) if a partial test report or other information that is not a test report is required.	122.35
(b) if a test report is required.	306.20
14 Administration component of fee paid for an application under item 13 refundable under section 126A.	nil
15 Application for transfer of approval of a type of electrical equipment	61.10
 Cathodic protection system	
16 Application for registration of cathodic protection system that is a registrable system.	222.70
17 Administration component of fee paid for an application under item 16 refundable under section 187A.	32.50
 Accredited auditors	
18 Application for appointment as an accredited auditor.	278.30
19 Application for renewal of appointment as an accredited auditor	166.95
20 Cost of administering an appointment as an accredited auditor refundable under section 168	166.95

Schedule 8 Classes of electrical equipment for fees

section 211B

Class 1

appliance connector
bayonet lampholder
bayonet lampholder adaptor
bread toaster
cord extension socket
cord-line switch
decorative lighting outfit
edison screw lampholder
fluorescent lamp ballast
fluorescent lamp starter
immersion heater
inspection handlamp
iron
luminaire-portable type
outlet device-portable
plug
socket outlet
socket outlet adaptor
therapeutic lamp
wall switch

Schedule 8 (continued)

Class 2

battery charger/saver²⁹
conditioning or control device
cooking appliance-portable
extra low voltage power supply unit
floor polisher/scrubber
hair care appliance
hedge clipper
kitchen machine
lawn care appliance
liquid heating appliance
massage appliance
razor/hair clipper
room heater
sewing machine
soldering iron
tool-portable type
vacuum cleaner
waterbed heater

Class 3

arc welding machine
battery charger automotive type
blanket

²⁹ See 'battery charger automotive type' under class 3.

Schedule 8 (continued)

clothes dryer

dishwashing machine

fan

fence energiser

flexible heating pad

insect electrocutor

microwave oven

miniature overcurrent circuit-breaker

projector

range

range hood

refrigerating appliance

residual current device

supply flexible cord

swimming pool/spa equipment

television receiver

washing machine

water heater

Schedule 9 Dictionary

section 5

accredited auditor means a person holding an appointment as an accredited auditor under part 10, division 2 of the Act.

active conductor means—

- (a) in a system that has a neutral or earthed conductor—a conductor of electricity kept at a difference of potential from the neutral or earthed conductor; or
- (b) in a system that does not have a neutral or earthed conductor—all conductors.

amusement device, for part 5, division 5, see section 83.

amusement ride, for part 5, division 5, see section 83.

amusement work, for part 5, division 5, see section 83.

anode, in relation to a cathodic protection system, means a part of the system that is an electrical conductor placed in contact with ground or water.

approved safety switch, for part 5, division 4 and section 211, see section 77.

approved testing entity means—

- (a) a body accredited by NATA to perform the relevant test or examination; or
- (b) a body accredited by another body, operating under a reciprocal agreement with NATA, to perform the relevant test or examination; or
- (c) a body approved by the chief executive to perform the relevant test or examination.

AS/NZS means a joint Standards Australia and Standards New Zealand standard.

authorised person, for part 4, see section 59.

caisson means a structure that provides an underground passageway or a passageway through water.

Schedule 9 (continued)

cathodically protected structure, for part 11, see section 170.

cathodic protection standard, for part 11, see section 170.

chief executive (land), for part 5, division 4, see section 77.

cofferdam means a temporary wall erected to exclude water from an area normally under water.

combined form, for part 5, division 4, see section 77.

competent person means a person who has acquired, through training, qualifications, experience or a combination of these, the knowledge and skill enabling the person to inspect and test electrical equipment.

conductive object means a tool or other object readily able to conduct electricity.

construction wiring, for part 5, division 5, see section 83.

construction work—

- (a) generally, see the WHS Act, section 14; or
- (b) for part 5, division 5, see section 83.

construction workplace means—

- (a) a workplace where construction work is performed, if the construction work—
 - (i) is a prescribed activity; or
 - (ii) is not a prescribed activity and the estimated final price for the construction work is more than \$80000; or
- (b) a place intended to become a construction workplace under paragraph (a) when work starts at the place.

consumer mains, of a consumer, means the conductors between the consumer's consumer terminals and the consumer's main switchboard.

consumer terminals, of a consumer, means the point where the consumer's electrical installation is connected to the works of an electricity entity.

cord extension set, for part 5, division 5, see section 83.

Schedule 9 (continued)

date of possession, for part 5, division 4, see section 77.

direct contact, for part 4, see section 59.

distribution entity, for part 12, see section 194.

domestic residence, for part 5, division 4 and section 211, see section 77.

earthed means connected to the general mass of the earth.

Electrical Articles Regulation, for part 14, see section 212.

electrical part, for part 4, see section 59.

electrical work, for part 2, division 2, see section 9.

Electricity Regulation, for part 14, see section 212.

ENA means Energy Networks Association Limited ABN 75 106 735 406.

equivalent non-Queensland training organisation means a training organisation outside Queensland that is equivalent to a registered training organisation.

estimated final price, for construction work, see the WHS Act.

excavation means a hole in the earth, or a face of earth, formed after rock, sand, soil or other material is removed.

Examples—

- a trench, ditch, shaft, well, tunnel, pier hole, cutting, caisson or cofferdam
- a hole drilled in the earth

exclusion zone, see section 59.

existing type, for part 6, see section 95.

external approval, for part 6, see section 95.

external approvals entity means an entity in another State or New Zealand that has powers similar to the chief executive to approve, register or certify types of electrical equipment of prescribed classes of electrical equipment.

external contracting authority means a licence or other authority under a law of another State that authorises the

Schedule 9 (continued)

holder to contract for the performance of electrical work in the other State.

externally approved, for part 6, see section 95.

fixed fee means a fee fixed by the chief executive under section 209 of the Act.

foreign structure, for part 11, see section 170.

foreign structure owner, for part 11, see section 170.

general purpose socket-outlet, for part 5, division 4, see section 77.

high voltage live line work means live work on exposed live high voltage conductors or exposed live parts of high voltage electrical equipment.

impressed current cathodic protection system, for part 11, see section 170.

incident record, for part 12, see section 194.

instructed person, for part 4, see section 59.

insulated cable means an insulated aerial cable complying with AS/NZS 5000.1 (Electric cables—Polymeric insulated—For working voltages up to and including 0.6/1 (1.2) kV) or ASNZS 3560.1 (Electric cables—Cross-linked polyethylene insulated—Aerial bundled—For working voltages up to and including 0.6/1(1.2)kV).

jurisdiction, of an external approvals entity, includes the place where it operates.

kerb line, of a road, means—

- (a) if there is a formed footpath—the line where the formed footpath meets the carriageway; or
- (b) if there is no formed footpath but a formed footpath is proposed—the line where the proposed formed footpath can reasonably be expected to meet the carriageway; or
- (c) if there is no formed footpath and no formed footpath is proposed—

Schedule 9 (continued)

- (i) if widening of the existing carriageway is proposed—the line of the edge of the carriageway as proposed to be widened; or
- (ii) if no widening of the existing carriageway is proposed—the line of the edge of the existing carriageway.

live work means electrical work performed in circumstances in which the part of the electrical equipment the subject of the electrical work is energised.

manufacturing work, for part 5, division 5, see section 83.

maximum operating current, for part 11, see section 170.

NATA means the National Association of Testing Authorities, Australia ABN 59 004 379 748.

neutral screened cable means a cable complying with AS 3155 (Approval and test specification—Neutral screened cables for working voltages of 0.6/1kV).

new, in relation to electrical equipment, means the equipment had not been introduced into service or otherwise used.

new type, for part 6, see section 95.

nonprescribed electrical equipment, for part 6, see section 95.

non-profit organisation, for part 5, division 5, see section 83.

operating plant, for part 4, see section 59.

portable outlet device has the meaning given by AS/NZS 3105 (Approval and test specification—Electrical portable outlet devices).³⁰

premises figure, for part 13, division 1, see section 204.

prescribed activity see the WHS Act.

30 AS/NZS 3105—

4.2 Portable outlet device—a device, other than a cord extension set, having a single means of connection to a low voltage supply, and one or more outlet facilities. It may incorporate a reeling or coiling arrangement. The term ‘device’ means ‘electrical portable outlet device’.

Schedule 9 (continued)

prescribed class, for part 6, see section 95.

prescribed details see section 83.

prescribed information, about an underground electrical service, means the information about the service necessary to safely do excavation work at or near the service, including—

- (a) the location of the service; and
- (b) the type of the service; and
- (c) the depth of the service; and
- (d) whether the service is or is not live; and
- (e) the restrictions to be followed in doing the work.

principal contractor has the meaning given by the WHS Act, section 13.

qualification see the *Vocational Education, Training and Employment Act 2000*.

qualified business person see section 7.

qualified technical person see section 7.

Queensland approval, for part 6, see section 95.

Queensland approved, for part 6, see section 95.

reasonable interval, in relation to the inspection and maintenance of insulation, means an interval, based on historic performance and the degree of electrical risk, that is reasonable in the circumstances.

registered system, for part 11, see section 170.

registered training organisation see the *Vocational Education, Training and Employment Act 2000*.

register of electrical licences means the register the chief executive is required to keep under section 52.

registrable system, for part 11, see section 170.

registrar, for part 5, division 4, see section 77.

relevant standard, for part 6, see section 95.

residential land, for part 5, division 4, see section 77.

Schedule 9 (continued)

rural industry work, for part 5, division 5, see section 83.

safety observer see section 12(2).

safety switch, for part 5, division 5, see section 83.

serious defect means a defect likely to cause a fire or a person to suffer an electric shock or other personal injury.

service line means an electric line that—

- (a) forms part of the works of an electricity entity; and
- (b) connects consumer terminals to—
 - (i) other parts of the works of the electricity entity; or
 - (ii) the works of another electricity entity.

service work, for part 5, division 5, see section 83.

short term testing, for part 11, see section 170.

specified electrical equipment, for part 5, division 5, see section 83.

statement of attainment see the *Vocational Education, Training and Employment Act 2000*.

structure includes the following—

- (a) anything attached to a structure;
- (b) anything erected or standing at a place.

total contribution amount, for part 13, division 1, see section 204.

total premises figure, for part 13, division 1, see section 204.

training person see section 209(4).

training plan see the *Vocational Education, Training and Employment Act 2000*.

transfer and safety switch information, for part 5, division 4, see section 77.

transfer date, for part 5, division 4, see section 77.

transferee, for part 5, division 4, see section 77.

transferor, for part 5, division 4, see section 77.

Schedule 9 (continued)

type, for part 6, see section 95.

type 1 safety switch, for part 5, division 5, see section 83.

type 2 safety switch, for part 5, division 5, see section 83.

type approval certificate, for part 6, see section 95.

type approval holder, for part 6, see section 95.

type approval number, for part 6, see section 95.

underground electrical service means a cable, pipe or other thing laid or installed underground for the transmission of electricity.

Example—

underground electrical cables

unit contribution amount, for part 13, division 1, see section 204.

untrained person, for part 4, see section 59.

WHS Act means the *Workplace Health and Safety Act 1995*.

wiring rules means AS/NZS 3000 (Electrical installations) (known as the Australian/New Zealand Wiring Rules).³¹

work, for part 4, see section 59.

31 AS/NZS 3000 (Electrical installations) may be purchased from Standards Australia.

Endnotes

1 Index to endnotes

	Page
2 Date to which amendments incorporated	230
3 Key	230
4 Table of reprints	231
5 List of legislation	231
6 List of annotations	233

2 Date to which amendments incorporated

This is the reprint date mentioned in the Reprints Act 1992, section 5(c). Accordingly, this reprint includes all amendments that commenced operation on or before 1 March 2008. Future amendments of the Electrical Safety Regulation 2002 may be made in accordance with this reprint under the Reprints Act 1992, section 49.

3 Key

Key to abbreviations in list of legislation and annotations

Key	Explanation	Key	Explanation
AIA	= Acts Interpretation Act 1954	(prev)	= previously
amd	= amended	proc	= proclamation
amdt	= amendment	prov	= provision
ch	= chapter	pt	= part
def	= definition	pubd	= published
div	= division	R[X]	= Reprint No. [X]
exp	= expires/expired	RA	= Reprints Act 1992
gaz	= gazette	reloc	= relocated
hdg	= heading	renum	= renumbered
ins	= inserted	rep	= repealed
lap	= lapsed	(retro)	= retrospectively
notfd	= notified	rv	= revised edition
num	= numbered	s	= section
o in c	= order in council	sch	= schedule
om	= omitted	sdiv	= subdivision
orig	= original	SIA	= Statutory Instruments Act 1992
p	= page	SIR	= Statutory Instruments Regulation 2002
para	= paragraph	SL	= subordinate legislation
prec	= preceding	sub	= substituted
pres	= present	unnum	= unnumbered
prev	= previous		

4 Table of reprints

Reprints are issued for both future and past effective dates. For the most up-to-date table of reprints, see the reprint with the latest effective date.

If a reprint number includes a letter of the alphabet, the reprint was released in unauthorised, electronic form only.

Reprint No.	Amendments included	Effective	Notes
1	none	1 October 2002	
1A	2002 SL No. 300	8 November 2002	
1B	2003 SL No. 32	28 February 2003	
1C	—	1 March 2003	provs exp end of 28 February 2003
1D	2003 SL No. 102	1 June 2003	
1E	2003 SL No. 32 2003 SL No. 149	1 July 2003	
1F	2003 Act No. 63	1 January 2004	
1G	2004 SL No. 87	1 July 2004	
1H	2004 SL No. 289	1 January 2005	
1I rv	2004 SL No. 289	1 February 2005	
1J rv	2005 SL No. 28	1 April 2005	
1K rv	2005 SL No. 94	27 May 2005	
1L rv	2005 SL No. 141	1 July 2005	
1M	2005 SL No. 244	7 October 2005	
1N	2005 SL No. 308	16 December 2005	
2	2006 SL No. 14	1 March 2006	
2A	2006 SL No. 142	1 July 2006	
2B	2007 SL No. 146	1 July 2007	
2C	2008 SL No. 2	1 March 2008	

5 List of legislation

Electrical Safety Regulation 2002 SL No. 260

made by the Governor in Council on 26 September 2002

notfd gaz 27 September 2002 pp 340–4

ss 1–2 commenced on date of notification

remaining provisions commenced 1 October 2002 (see s 2)

exp 1 September 2013 (see SIA s 54)

Notes—(1) The expiry date may have changed since this reprint was published. See the latest reprint of the SIR for any change.

(2) A regulatory impact statement and explanatory note were prepared.

amending legislation—

Electrical Safety Amendment Regulation (No. 1) 2002 SL No. 300

notfd gaz 8 November 2002 pp 857–8

commenced on date of notification

Electrical Safety Amendment Regulation (No. 1) 2003 SL No. 32

notfd gaz 28 February 2003 pp 774–5
 ss 20, 21 and 23(1) commenced 1 July 2003 (see s 2)
 remaining provisions commenced on date of notification

Workplace Health and Safety Amendment Regulation (No. 2) 2003 SL No. 102 pts 1, 3

notfd gaz 30 May 2003 pp 371–6
 ss 1–2 commenced on date of notification
 remaining provisions commenced 1 June 2003 (see s 2)

Electrical Safety Amendment Regulation (No. 2) 2003 SL No. 149

notfd gaz 27 June 2003 pp 749–56
 ss 1–2 commenced on date of notification
 remaining provisions commenced 1 July 2003 (see s 2)

Training Reform Act 2003 No. 63 ss 1, 2(2), 60 sch

date of assent 13 October 2003
 ss 1–2 commenced on date of assent
 remaining provisions commenced 1 January 2004 (2003 SL No. 293)

Electrical Safety Amendment Regulation (No. 1) 2004 SL No. 87

notfd gaz 25 June 2004 pp 573–81
 ss 1–2 commenced on date of notification
 remaining provisions commenced 1 July 2004 (see s 2)

Workers' Compensation and Rehabilitation and Other Legislation Amendment Regulation (No. 1) 2004 SL No. 289 ss 1–2(1)–(2), pt 4

notfd gaz 17 December 2004 pp 1277–85
 ss 1–2, 34 commenced on date of notification
 s 37 commenced 1 January 2005 (see s 2(1))
 remaining provisions commenced 1 February 2005 (see s 2(2))
 Note—An explanatory note was prepared

Electrical Safety Amendment Regulation (No. 1) 2005 SL No. 28 pts 1–2

notfd gaz 11 March 2005 pp 845–6
 ss 1–2 commenced on date of notification
 remaining provisions commenced 1 April 2005 (see s 2)

Electrical Safety Amendment Regulation (No. 2) 2005 SL No. 94 pts 1–2

notfd gaz 27 May 2005 pp 308–11
 commenced on date of notification

Electrical Safety Amendment Regulation (No. 3) 2005 SL No. 141

notfd gaz 1 July 2005 pp 763–6
 ss 1–2 commenced on date of notification
 remaining provisions commenced 1 July 2005 (see s 2)

Electrical Safety and Another Regulation Amendment Regulation (No. 1) 2005 SL No. 244 pts 1–2

notfd gaz 7 October 2005 pp 507–9
 commenced on date of notification

Workers' Compensation and Rehabilitation and Other Legislation Amendment Regulation (No. 1) 2005 SL No. 308 s 1, pt 4

notfd gaz 16 December 2005 pp 1490–6

commenced on date of notification

Note—Two regulatory impact statements and an explanatory note were prepared.

Electrical Safety Amendment Regulation (No. 1) 2006 SL No. 14

notfd gaz 17 February 2006 pp 699–700

ss 1–2 commenced on date of notification

remaining provisions commence 1 March 2006 (see s 2)

Note—A regulatory impact statement and explanatory note were prepared.

Electrical Safety and Another Regulation Amendment Regulation (No. 1) 2006 SL No. 142 pts 1–2, s 3 sch

notfd gaz 23 June 2006 pp 898–902

ss 1–2 commenced on date of notification

remaining provisions commenced 1 July 2006 (see s 2)

Electrical Safety and Another Regulation Amendment Regulation (No. 1) 2007 SL No. 146 pts 1–2

notfd gaz 29 June 2007 pp 1157–65

ss 1–2 commenced on date of notification

remaining provisions commenced 1 July 2007 (see s 2)

Electrical Safety and Other Legislation Amendment Regulation (No. 1) 2008 SL No. 2 ss 1, 2(2), pt 2

notfd gaz 25 January 2008 pp 324–5

ss 1–2 commenced on date of notification

remaining provisions commenced 1 March 2008 (see s 2(2))

6 List of annotations

Definitions

s 5 amd 2003 SL No. 149 s 4

References to standards and other documents

s 6 amd 2007 SL No. 146 s 4

Meaning of “qualified business person” and “qualified technical person”

s 7 sub 2003 SL No. 32 s 4

amd 2004 SL No. 87 s 4; 2006 SL No. 142 s 4

Requirements for performance of live work

s 12 amd 2005 SL No. 28 s 4; 2005 SL No. 141 s 4; 2005 SL No. 244 s 3; 2006 SL No. 142 s 3 sch; 2007 SL No. 146 s 5

Performance of high voltage live line work

s 13 amd 2007 SL No. 146 s 6

Testing of electrical equipment after electrical work

s 14 sub 2002 SL No. 300 s 3

amd 2005 SL No. 28 s 5; 2007 SL No. 146 s 7

Employer or self-employed person to ensure suitability of testing instruments

s 18 amd 2007 SL No. 146 s 8

Signs on switches and disconnection points

s 20 amd 2002 SL No. 300 s 4; 2003 SL No. 32 s 5

Rescue and resuscitation training

s 21 amd 2004 SL No. 87 s 5; 2006 SL No. 142 s 5

Who may sign documents about electrical work

s 23 amd 2003 SL No. 32 s 6

Misrepresentations about electrical equipment or work

s 24 amd 2005 SL No. 141 s 5

Misrepresentations about lawful authority to contract for the performance of electrical works 24A ins 2005 SL No. 28 s 6
 amd 2005 SL No. 141 s 6**What electrical mechanic licence authorises**

s 26 amd 2003 SL No. 32 s 7

General requirements

s 33 amd 2004 SL No. 87 s 6; 2006 SL No. 142 s 6

Eligibility requirements for electrical mechanic licence

s 34 amd 2003 SL No. 149 s 5; 2003 No. 63 s 60 sch; 2004 SL No. 87 s 7

Eligibility requirements for electrical linesperson licence

s 35 amd 2003 SL No. 149 s 6; 2003 No. 63 s 60 sch; 2004 SL No. 87 s 8

Eligibility requirements for electrical fitter licence

s 36 amd 2003 SL No. 149 s 7; 2003 No. 63 s 60 sch; 2004 SL No. 87 s 9

Eligibility requirements for electrical jointer licence

s 37 amd 2003 SL No. 149 s 8; 2003 No. 63 s 60 sch; 2004 SL No. 87 s 10

Eligibility requirements for restricted electrical work licence

s 38 amd 2003 SL No. 149 s 9; 2003 No. 63 s 60 sch; 2004 SL No. 87 s 11

Eligibility requirements for electrical work training permit

s 38A ins 2007 SL No. 146 s 9

Eligibility requirements for electrical contractor licence for individuals 40 amd 2002 SL No. 300 s 5
 sub 2003 SL No. 32 s 8
 amd 2004 SL No. 87 s 12; 2006 SL No. 142 s 7**Eligibility requirements for electrical contractor licence for partnership**s 41 amd 2002 SL No. 300 s 6; 2003 SL No. 32 s 9; 2004 SL No. 87 s 13; 2006 SL
 No. 142 s 8**Eligibility requirements for electrical contractor licence for corporation**s 42 amd 2002 SL No. 300 s 7; 2003 SL No. 32 s 10; 2004 SL No. 87 s 14; 2006
 SL No. 142 s 9

Financial and insurance requirements for applicant for electrical contractor licence
 s 43 amd 2004 SL No. 87 s 15

Change of name of corporation or partnership
 s 44 amd 2007 SL No. 146 s 10

Change in membership of partnership
 s 45 amd 2003 SL No. 32 s 11

Application requirements
 s 48 sub 2003 SL No. 149 s 10

Replacement of electrical licence
 s 50 amd 2003 SL No. 149 s 11

Register of electrical licences
 s 52 amd 2002 SL No. 300 s 8; 2005 SL No. 141 s 7

Examinations
 s 53 amd 2003 SL No. 32 s 12; 2003 No. 63 s 60 sch

Approved examiners
 s 54 sub 2003 SL No. 32 s 13

Refund of fees
 s 55 sub 2003 SL No. 149 s 12
 amd 2004 SL No. 87 s 16

Operation of trade contractor's licence
 s 55A ins 2002 SL No. 300 s 9
 amd 2006 SL No. 142 s 3 sch

Advertising by licensed electrical contractor
 s 56 amd 2004 SL No. 87 s 17

Performing electrical work without electrical licence
 s 57 amd 2003 SL No. 149 s 13

Details to be included in register of workers
 s 57A ins 2008 SL No. 2 s 4

PART 4—WORKING AROUND ELECTRICAL PARTS

Definitions for pt 4

s 59 amd 2002 SL No. 300 s 10
 def “**handling**” ins 2002 SL No. 300 s 10(1)
 def “**operating plant**” amd 2002 SL No. 300 s 10(2)–(3)

Meaning of “direct contact”
 s 60 amd 2002 SL No. 300 s 11

Meaning of “exclusion zone”
 s 61 amd 2002 SL No. 300 s 12; 2005 SL No. 244 s 4

Division 2—Requirements for working around electrical parts and underground electrical services

div hdg amd 2007 SL No. 146 s 11

Employer or self-employed person to ensure work is performed in accordance with requirements

s 62 amd 2002 SL No. 300 s 13; 2003 SL No. 32 s 14; 2007 SL No. 146 s 12

Principal contractor for construction workplace—excavating and underground electrical services

s 62A ins 2005 SL No. 28 s 7

Purpose of ss 62C and 62D

s 62B ins 2005 SL No. 28 s 7
om 2005 SL No. 244 s 5

Employer or self-employed person at construction workplace—excavating and underground electrical services

s 62C ins 2005 SL No. 28 s 7

Employer or self-employed person not at construction workplace—excavating and underground electrical services

s 62D ins 2005 SL No. 28 s 7

Work within exclusion zone for electrical part

s 64 amd 2005 SL No. 244 s 6

Division 3—Consultation with persons in control of electric lines

div hdg ins 2002 SL No. 300 s 14
amd 2003 SL No. 32 s 15

Requirement to consult

s 64A ins 2002 SL No. 300 s 14

PART 5—ELECTRICAL INSTALLATIONS**Employer to ensure electrical installation complies**

s 67 sub 2005 SL No. 28 s 8

Self-employed person to ensure electrical installation complies

s 67A ins 2005 SL No. 28 s 8

Service line

s 72 amd 2003 SL No. 149 s 14

Obligation to preserve insulation of electric line

s 74 amd 2003 SL No. 32 s 16

Obligation to ensure safety of disconnected overhead electric line

s 76 sub 2002 SL No. 300 s 15

Definitions for div 4

s 77 def “**date of possession**” amd 2006 SL No. 142 s 10(1)
def “**transfer date**” amd 2006 SL No. 142 s 10(2)
def “**transferor**” sub 2002 SL No. 300 s 16
amd 2006 SL No. 142 s 10(3)

Installation of approved safety switch if residential tenancy agreement entered into or to be entered into

s 80A ins 2006 SL No. 14 s 4
amd 2006 SL No. 142 s 11

Division 5—Workplace electrical installations**Definitions for div 5**

- s 83** def “**amusement device**” ins 2006 SL No. 14 s 5(2)
 def “**amusement ride**” ins 2006 SL No. 14 s 5(2)
 def “**amusement work**” ins 2006 SL No. 14 s 5(2)
 def “**class 1 work**” amd 2003 SL No. 102 s 40(1)
 om 2006 SL No. 14 s 5(1)
 def “**class 2 work**” om 2006 SL No. 14 s 5(1)
 def “**class 3 work**” om 2006 SL No. 14 s 5(1)
 def “**class 4 work**” om 2006 SL No. 14 s 5(1)
 def “**construction-type work**” om 2003 SL No. 102 s 40(2)
 def “**construction wiring**” amd 2003 SL No. 102 s 40(3); 2006 SL No. 14 s 5(3)
 def “**construction work**” amd 2003 SL No. 102 s 40(4)
 om 2005 SL No. 28 s 9
 ins 2006 SL No. 14 s 5(2)
 def “**construction workplace**” om 2005 SL No. 28 s 9
 def “**manufacturing work**” ins 2006 SL No. 14 s 5(2)
 def “**non-profit organisation**” ins 2006 SL No. 14 s 5(2)
 def “**prescribed details**” ins 2007 SL No. 146 s 13
 def “**principal contractor**” om 2005 SL No. 28 s 9
 def “**rural industry work**” ins 2006 SL No. 14 s 5(2)
 def “**service work**” ins 2006 SL No. 14 s 5(2)
 def “**specified electrical equipment**” sub 2002 SL No. 300 s 17
 amd 2006 SL No. 14 s 5(4)–(5)

Meaning of “rural industry work”

- s 83A** ins 2006 SL No. 14 s 6

Cord extension sets and flexible cables

- s 85** amd 2006 SL No. 14 s 7

Subdivision 3—Construction work

- sdiv hdg** amd 2006 SL No. 14 s 3 sch

Application of sdiv 3

- s 86** amd 2006 SL No. 14 s 3 sch

Requirements for construction wiring and electrical equipment

- s 87** amd 2005 SL No. 244 s 7; 2007 SL No. 146 s 14

Subdivision 4—Manufacturing work

- sdiv hdg** amd 2006 SL No. 14 s 3 sch

Application of sdiv 4

- s 88** amd 2006 SL No. 14 s 4 sch

Specified electrical equipment

- s 90** amd 2005 SL No. 244 s 8; 2006 SL No. 14 s 8; 2007 SL No. 146 s 15

Manufacturing work—safety switch

- s 90A** ins 2006 SL No. 14 s 9

Exemption for safety switches

s 90B ins 2006 SL No. 14 s 9

Safety switches, including portable safety switches

s 91 sub 2003 SL No. 149 s 15
amd 2006 SL No. 14 s 10

Subdivision 5—Service work or office work

sdiv hdg amd 2006 SL No. 14 s 3 sch

Application of sdiv 5

s 92 amd 2006 SL No. 14 s 3 sch

Specified electrical equipment

s 93 amd 2005 SL No. 244 s 9; 2006 SL No. 14 s 3 sch; 2006 SL No. 142 s 12;
2007 SL No. 146 s 16

Safety switches, including portable safety switches

s 94 sub 2003 SL No. 149 s 16
amd 2006 SL No. 14 s 11

Subdivision 6—Amusement work

sdiv hdg ins 2006 SL No. 14 s 12

Application of sdiv 6

s 94A ins 2006 SL No. 14 s 12

Double adaptors and piggyback plugs prohibited

s 94B ins 2006 SL No. 14 s 12

Specified electrical equipment

s 94C ins 2006 SL No. 14 s 12
amd 2007 SL No. 146 s 17

Amusement devices and amusement rides

s 94D ins 2006 SL No. 14 s 12
amd 2007 SL No. 146 s 18

Safety switches, including portable safety switches

s 94E ins 2006 SL No. 14 s 12

Subdivision 7—Rural industry work

sdiv hdg ins 2006 SL No. 14 s 12

Application of sdiv 7

s 94F ins 2006 SL No. 14 s 12

Requirements for rural industry work

s 94G ins 2006 SL No. 14 s 12
amd 2007 SL No. 146 s 19

PART 6—ELECTRICAL EQUIPMENT**Definitions for pt 6**

s 95 def “second-hand” ins 2006 SL No. 142 s 13
def “sell” ins 2006 SL No. 142 s 13

Hire or sale of electrical equipment of prescribed class

s 100 amd 2005 SL No. 28 s 10

Application for approval of type of electrical equipment

s 101 amd 2003 SL No. 149 s 17; 2005 SL No. 28 s 11; 2007 SL No. 146 s 20

Approval of type of electrical equipment

s 102 amd 2005 SL No. 28 s 12

Term of approval

s 103 amd 2005 SL No. 28 s 13

Extension of term of approval by up to 1 years 103A ins 2005 SL No. 28 s 14
 amd 2005 SL No. 141 s 8
 sub 2006 SL No. 142 s 14**Renewal of approval**s 103B ins 2005 SL No. 28 s 14
 amd 2005 SL No. 141 s 9
 sub 2006 SL No. 142 s 14**Register of approved types of electrical equipment**

s 104 amd 2007 SL No. 146 s 21

Changing name and address

s 105 amd 2003 SL No. 149 s 18

Application to change approval to include new type

s 106 amd 2003 SL No. 149 s 19; 2005 SL No. 28 s 15

Transfer of approval of type of electrical equipment

s 108 amd 2003 SL No. 149 s 20

Cancellation of approval of type of electrical equipment

s 109 amd 2005 SL No. 28 s 16

Sale of particular nonprescribed electrical equipment prohibited

s 120 amd 2005 SL No. 28 s 17; 2005 SL No. 94 s 3

Limitation on sale of second-hand electrical equipment

s 122 amd 2005 SL No. 28 s 18

Hiring electrical equipment

s 126 amd 2003 SL No. 149 s 21; 2004 SL No. 87 s 18; 2007 SL No. 146 s 22

Division 13—Miscellaneous

div hdg ins 2004 SL No. 87 s 19

Refund of feess 126A ins 2004 SL No. 87 s 19
 amd 2005 SL No. 244 s 10; 2006 SL No. 142 s 15**Performance and other requirements for works**

s 131 amd 2005 SL No. 28 s 19; 2006 SL No. 142 s 16

Application of div 4

s 134A ins 2003 SL No. 32 s 17

Electric lines and control cables

s 136 amd 2003 SL No. 32 s 18

Inspection and maintenance of integrity of insulation

s 147 sub 2003 SL No. 149 s 22

Reconnection of electrical installation to electricity source

s 152 amd 2002 SL No. 300 s 18; 2005 SL No. 28 s 20

High voltage or hazardous area electrical installation not to be connected to electricity source without inspection

s 153 amd 2003 SL No. 149 s 23

Licensed electrical contractor not to connect electricity source without being satisfied of compliance with Act and regulation

s 154 sub 2003 SL No. 32 s 19

Disconnection and reconnection of low voltage electrical installation

s 155 amd 2007 SL No. 146 s 23

Notice by licensed electrical contractor of test

prov hdg amd 2007 SL No. 146 s 24(1)

s 158 amd 2007 SL No. 146 s 24(2)–(3)

Refund of part of fee

s 168 amd 2005 SL No. 141 s 10

Exclusion from application

s 172 amd 2006 SL No. 142 s 3 sch

Refund of fees

s 187A ins 2004 SL No. 87 s 20

Change of name and address

s 190 amd 2003 SL No. 149 s 24

Scene not to be interfered with

s 201 amd 2006 SL No. 142 s 3 sch

Storage of electrical equipment after serious electrical incident

s 201A ins 2007 SL No. 146 s 25

PART 13—MISCELLANEOUS PROVISIONS**Definitions for div 1**

s 204 amd 2007 SL No. 146 s 26(1)

def “**current financial year**” om 2003 SL No. 32 s 20(1)def “**financial year**” om 2003 SL No. 32 s 20(1)def “**total contribution amount**” amd 2003 SL No. 32 s 20(2); 2004 SL No. 87 s 21; 2005 SL No. 28 s 21; 2005 SL No. 141 s 11; 2006 SL No. 142 s 17; 2007 SL No. 146 s 26(2)**Payment of electrical safety contribution by instalments**

s 206 amd 2003 SL No. 32 s 21; 2004 SL No. 87 s 22

Division 2—Mines, petroleum plants and prescribed workplaces

div hdg sub 2004 SL No. 289 s 35

Application of regulation at mine or petroleum plant

s 207 amd 2006 SL No. 142 s 18

Prescribed workplaces—Act, s 18(2)(d)

s 207A ins 2004 SL No. 289 s 36

Obligations of employer about supervising training person

s 209 amd 2003 No. 63 s 60 sch; 2005 SL No. 141 s 12

Electrical distribution entity may isolate powerlines in emergency

s 209A ins 2005 SL No. 244 s 11

Time for giving electrical safety undertaking

s 210A ins 2004 SL No. 289 s 37

Provision of information by retail entity

s 211 amd 2005 SL No. 141 s 13

Provision of information by Residential Tenancies Authority

s 211AA ins 2006 SL No. 14 s 13

Person chief executive may appoint as inspector

s 211A ins 2003 SL No. 149 s 25

Fees

s 211B ins 2003 SL No. 149 s 25

PART 14—TRANSITIONAL PROVISIONS**Division 2—Transitional provisions for 2002 SL No. 260**

div hdg sub 2007 SL No. 146 s 27

Subdivision 1—Electrical licences

sdiv hdg ins 2007 SL No. 146 s 27

Eligibility for electrical jointer licence

s 214 amd 2007 SL No. 146 s 28

Eligibility for electrical linesperson licence

s 215 amd 2007 SL No. 146 s 29

Subdivision 2—Matters in place before 1 October 2002

sdiv hdg ins 2007 SL No. 146 s 30

**Division 3—Transitional provisions for Electrical Safety and Another Regulation
Amendment Regulation (No. 1) 2007**

div hdg prev div 3 hdg om 2007 SL No. 146 s 30

pres div 3 hdg ins 2007 SL No. 146 s 31

Further provision for electrical jointer licences

s 221 ins 2007 SL No. 146 s 31

Further provision for electrical linesperson licences

s 222 ins 2007 SL No. 146 s 31

Division 4—Transitional provisions for rural industry

div 4 (ss 221–223) om 2006 SL No. 14 s 3 sch

Division 5—Workplace requirements for class 1 work until 28 February 2003
div 5 (ss 224–231) exp end of 28 February 2003 (see s 231)

Division 6—Workplace requirements for class 2 work until 28 February 2003
div 6 (ss 232–234) exp end of 28 February 2003 (see s 234)

PART 15—AMENDMENTS OF OTHER SUBORDINATE LEGISLATION

pt hdg om R1 (see RA s 7(1)(k))

Amendments in sch 7

s 235 om R1 (see RA s 40)

**SCHEDULE 1—EXTERNAL LICENCES AND ELECTRICAL WORK LICENCE
EQUIVALENTS**

sub 2007 SL No. 146 s 32

SCHEDULE 2—EXCLUSION ZONES FOR ELECTRICAL PARTS

amd 2002 SL No. 300 s 19; 2005 SL No. 28 s 22

**SCHEDULE 3—PRESCRIBED CLASSES OF ELECTRICAL EQUIPMENT AND
RELEVANT STANDARDS**

amd 2006 SL No. 142 s 3 sch

**SCHEDULE 4—CLEARANCE OF OVERHEAD ELECTRIC LINES (OTHER
THAN LOW VOLTAGE SERVICE LINES)**

amd 2002 SL No. 300 s 20; 2006 SL No. 142 s 3 sch

SCHEDULE 6—PRESCRIBED ELECTRICITY ENTITIES

amd 2003 SL No. 32 s 22

SCHEDULE 6A—PRESCRIBED WORKPLACES

ins 2004 SL No. 289 s 38

SCHEDULE 7—FEES

prev sch 7 om R1 (see RA s 40)

pres sch 7 ins 2003 SL No. 149 s 27

sub 2004 SL No. 87 s 23

amd 2005 SL No. 28 s 23

sub 2005 SL No. 141 s 14

amd 2005 SL No. 244 s 12

sub 2006 SL No. 142 s 19; 2007 SL No. 146 s 33

SCHEDULE 8—CLASSES OF ELECTRICAL EQUIPMENT FOR FEES

ins 2003 SL No. 149 s 27

SCHEDULE 9—DICTIONARY

(prev sch 8) renum 2003 SL No. 149 s 26

def “**amusement device**” ins 2006 SL No. 14 s 14(2)

def “**amusement ride**” ins 2006 SL No. 14 s 14(2)

def “**amusement work**” ins 2006 SL No. 14 s 14(2)

def “**approved safety switch**” amd 2005 SL No. 141 s 15(1)

def “**approved testing entity**” sub 2005 SL No. 244 s 13(2)

def “**caisson**” ins 2005 SL No. 28 s 24(2)

def “**class 1 work**” om 2006 SL No. 14 s 14(1)

def “**class 2 work**” om 2006 SL No. 14 s 14(1)

- def “**class 3 work**” om 2006 SL No. 14 s 14(1)
- def “**class 4 work**” om 2006 SL No. 14 s 14(1)
- def “**cofferdam**” ins 2005 SL No. 28 s 24(2)
- def “**construction-type work**” om 2003 SL No. 102 s 41
- def “**construction wiring**” amd 2006 SL No. 14 s 5(3)
- def “**construction work**” sub 2005 SL No. 28 s 24(1)–(2)
 - amd 2005 SL No. 308 s 65(2)
 - sub 2006 SL No. 14 s 14(1)–(2)
- def “**construction workplace**” sub 2005 SL No. 28 s 24(1)–(2); 2005 SL No. 308 s 65(3)
- def “**current financial year**” om 2003 SL No. 32 s 23(1)
- def “**domestic residence**” amd 2005 SL No. 141 s 15(2)
- def “**ENA**” ins 2007 SL No. 146 s 34(2)
- def “**equivalent non-Queensland training organisation**” ins 2003 SL No. 149 s 28
- def “**ESAA**” om 2007 SL No. 146 s 34(1)
- def “**estimated final price**” ins 2005 SL No. 308 s 65(1)
- def “**excavation**” ins 2005 SL No. 28 s 24(2)
- def “**exclusion zone**” amd 2007 SL No. 146 s 34(3)
- def “**financial year**” om 2003 SL No. 32 s 23(1)
- def “**insulated cable**” sub 2002 SL No. 300 s 21
 - amd 2006 SL No. 142 s 3 sch
- def “**live work**” sub 2005 SL No. 28 s 24(1)–(2)
- def “**manufacturing work**” ins 2006 SL No. 14 s 14(2)
 - amd 2006 SL No. 142 s 20(2)
- def “**new**” ins 2005 SL No. 244 s 13(1)
- def “**non-profit organisation**” ins 2006 SL No. 14 s 5(2)
- def “**prescribed activity**” ins 2005 SL No. 308 s 65(1)
- def “**prescribed details**” ins 2007 SL No. 146 s 34(2)
- def “**prescribed information**” ins 2005 SL No. 28 s 24(2)
- def “**principal contractor**” ins 2005 SL No. 28 s 24(2)
- def “**qualification**” ins 2003 SL No. 149 s 28
 - amd 2004 SL No. 87 s 23(1)
- def “**qualified business person**” ins 2003 SL No. 32 s 23(3)
- def “**qualified individual**” om 2003 SL No. 32 s 23(2)
- def “**qualified person**” om 2003 SL No. 32 s 23(2)
- def “**qualified technical person**” ins 2003 SL No. 32 s 23(3)
- def “**reasonable interval**” ins 2003 SL No. 149 s 28
- def “**registered training organisation**” ins 2003 SL No. 149 s 28
 - amd 2004 SL No. 87 s 23(2)
- def “**rural industry**” om 2006 SL No. 14 s 14(1)
- def “**rural industry work**” ins 2006 SL No. 14 s 14(2)
 - amd 2006 SL No. 142 s 3 sch
- def “**safety observer**” ins 2006 SL No. 142 s 20(1)
- def “**service work**” ins 2006 SL No. 14 s 14(2)
- def “**statement of attainment**” ins 2003 SL No. 149 s 28
 - amd 2004 SL No. 87 s 23(3)
- def “**training person**” ins 2005 SL No. 28 s 24(2)

def **“training plan”** ins 2003 SL No. 149 s 28
amd 2004 SL No. 87 s 23(4)

def **“underground electrical service”** ins 2005 SL No. 28 s 24(2)